

Package ‘spant’

August 18, 2025

Type Package

Title MR Spectroscopy Analysis Tools

Version 3.5.0

Date 2025-08-18

Description Tools for reading, visualising and processing Magnetic Resonance Spectroscopy data. The package includes methods for spectral fitting: Wilson (2021) <[DOI:10.1002/mrm.28385](https://doi.org/10.1002/mrm.28385)>, Wilson (2025) <[DOI:10.1002/mrm.30462](https://doi.org/10.1002/mrm.30462)> and spectral alignment: Wilson (2018) <[DOI:10.1002/mrm.27605](https://doi.org/10.1002/mrm.27605)>.

BugReports <https://github.com/martin3141/spant/issues/>

License GPL-3

RoxygenNote 7.3.2

NeedsCompilation yes

Depends R (>= 4.1.0)

Imports abind, plyr, pracma, stringr, expm (>= 1.0-0), signal, minpack.lm, utils, graphics, grDevices, ptw, mmand, RNifti, RNiftyReg, fields, numDeriv, nloptr, irlba, jsonlite

Suggests viridisLite, shiny, ggplot2, miniUI, knitr, kableExtra, rmarkdown, testthat, ragg, doParallel, parallel, digest, readxl, fsR, car, divest

VignetteBuilder knitr

Encoding UTF-8

Language en-GB

URL <https://spantdoc.wilsonlab.co.uk/>,
<https://martin3141.github.io/spant/>,
<https://github.com/martin3141/spant/>

Author Martin Wilson [cre, aut] (ORCID:
<<https://orcid.org/0000-0002-2089-3956>>),
Yong Wang [ctb],
John Muschelli [ctb]

Maintainer Martin Wilson <martin@pipegreg.co.uk>

Repository CRAN

Date/Publication 2025-08-18 09:20:11 UTC

Contents

spant-package	10
abfit_opts	11
abfit_opts_v1_9_0	14
abfit_reg_opts	15
acquire	19
add_noise	19
add_noise_spec_snr	20
align	20
apodise_xy	21
append_basis	22
append_coils	22
append_dyns	23
append_regs	23
apply_axes	24
apply_mrs	24
apply_pulse	25
Arg.mrs_data	26
array2mrs_data	26
auto_phase	27
auto_phase_bl	28
back_extrap_ar	28
basis2dyn_mrs_data	29
basis2mrs_data	30
bbase	30
bc_als	31
bc_constant	32
bc_gauss	32
bc_poly	33
bc_spline	33
beta2lw	34
bin_spec	34
calc_basis_corr_mat	35
calc_basis_crlbs	35
calc_coil_noise_cor	36
calc_coil_noise_sd	36
calc_design_efficiency	37
calc_ed_from_lambda	37
calc_peak_info_vec	38
calc_sd_poly	38
calc_spec_diff	39
calc_spec_snr	39
check_lcm	40

check_tqn	40
circ_mask	41
coherence_filter	41
collapse_to_dyns	42
comb_coils	42
comb_coils_mrsi_gls	43
comb_coils_svs_gls	44
comb_fit_list_dyns	44
comb_fit_list_fit_tables	45
comb_fit_list_result_tables	46
comb_fit_tables	46
comb_metab_ref	47
Conj.mrs_data	47
conv_mrs	48
crop_basis	48
crop_spec	49
crop_td_pts	49
crop_td_pts_end	50
crop_td_pts_pot	50
crop_xy	51
crossprod_3d	51
decimate_mrs_fd	52
decimate_mrs_td	52
deconv_mrs	53
def_acq_paras	53
def_fs	54
def_ft	54
def_N	55
def_nuc	55
def_ref	55
dicom_reader	56
diff_mrs	56
downsample_mrs_fd	57
downsample_mrs_td	57
dyn_acq_times	58
ecc	58
elliptical_mask	59
est_noise_sd	60
fd2td	60
fd_conv_filt	61
fd_gauss_smo	61
find_bids_mrs	62
find_mrs_files	62
fit_amps	63
fit_diags	63
fit_mrs	64
fit_res2csv	65
fit_svs	66

fit_svs_edited	69
fit_svs_group_results	73
fit_svs_gui	73
fit_t1_ti_array	73
fit_t1_tr_array	74
fit_t2_te_array	75
fp_phase	75
fp_phase_correct	76
fp_scale	76
fs	77
ft_dyns	77
ft_shift	78
ft_shift_mat	78
gausswin_2d	79
gen_baseline_reg	79
gen_bold_reg	80
gen_conv_reg	81
gen_F	82
gen_F_xy	82
gen_group_reg	83
gen_I	83
gen_impulse_reg	84
gen_numeric_reg	84
gen_poly_reg	85
gen_trap_reg	86
get_1h_braino_basis_names	87
get_1h_brain_basis_names	87
get_1h_brain_basis_paras	88
get_1h_brain_basis_paras_v1	88
get_1h_brain_basis_paras_v2	89
get_1h_brain_basis_paras_v3	89
get_1h_spectre_basis_names	90
get_2d_psf	90
get_acq_paras	91
get_basis_subset	91
get_dyns	92
get_even_dyns	92
get_fh_dyns	93
get_fit_map	93
get_fp	94
get_guassian_pulse	94
get_head_dyns	95
get_hrf	95
get_lcm_cmd	96
get_metab	96
get_mol_names	96
get_mol_paras	97
get_mrsi2d_seg	97

get_mrsi_voi	98
get_mrsi_voxel	98
get_mrsi_voxel_xy_psf	99
get_mrs_affine	99
get_odd_dyns	100
get_ref	100
get_seg_ind	101
get_sh_dyns	101
get_slice	102
get_spin_num	102
get_subset	103
get_svs_voi	104
get_tail_dyns	104
get_td_amp	105
get_tqn_cmd	105
get_uncoupled_mol	106
get_voi_cog	106
get_voi_seg	107
get_voi_seg_psf	107
get_voxel	108
glm_spec	108
glm_spec_fmrs_fl	109
glm_spec_fmrs_group	110
glm_spec_group_linhyp	110
gridplot	111
gridplot.mrs_data	111
grid_shift_xy	112
hsvd	112
hsvd_filt	113
hsvd_vec	114
hz	114
ift_shift	115
ift_shift_mat	115
Im.mrs_data	116
image.mrs_data	116
img2kpace_xy	118
Imzap	118
install_cli	119
interleave_dyns	119
int_spec	120
inv_even_dyns	120
inv_odd_dyns	121
is.def	121
is_fd	122
kpace2img_xy	122
l2_reg	123
lb	124
lofdc	124

lw2alpha	125
lw2beta	126
make_basis_from_raw	126
mask_dyns	127
mask_fit_res	127
mask_xy	128
mask_xy_corners	128
mask_xy_ellipse	129
mask_xy_mat	129
mat2mrs_data	130
matexp	130
max_mrs	131
max_mrs_interp	131
mean.list	132
mean.mrs_data	132
mean_dyns	133
mean_dyn_blocks	133
mean_dyn_pairs	134
mean_mrs_list	134
mean_vec_blocks	135
median_dyns	135
Mod.mrs_data	136
mod_td	136
mrs_data2basis	137
mrs_data2bids	137
mrs_data2list	138
mrs_data2mat	139
mrs_data2spec_mat	139
mrs_data2vec	140
mr_data2bids	140
mvfftshift	141
mvifftshift	142
n2coord	142
Ncoils	143
Ndyns	143
nifti_flip_lr	143
Npts	144
Nspec	144
Ntrans	145
Nx	145
Ny	145
Nz	146
one_page_pdf	146
ortho3	147
ortho3_inter	148
peak_info	149
pg_extrap_xy	149
phase	150

phase_ref_1h_brain	151
plot.fit_result	151
plot.mrs_data	153
plot_bc	155
plot_reg	156
plot_slice_fit	156
plot_slice_fit_inter	157
plot_slice_map	157
plot_slice_map_inter	158
plot_spec_sd	160
plot_voi_overlay	160
plot_voi_overlay_seg	161
ppm	161
precomp	162
preproc_svs	162
preproc_svs_dataset	163
print.fit_result	163
print.mrs_data	164
qn_states	164
rats	165
Re.mrs_data	166
read_basis	167
read_dkd_moco_log	167
read_ima_coil_dir	168
read_ima_dyn_dir	168
read_lcm_coord	169
read_mrs	169
read_mrs_tqn	171
read_pulse_ascii	172
read_pulse_bruker	172
read_pulse_pta	173
read_siemens_txt_hdr	173
read_tqn_fit	174
read_tqn_result	174
recon_imag	175
recon_imag_vec	175
recon_twix_2d_mrsi	176
rectangular_mask	176
rep_array_dim	177
rep_dyn	177
rep_mrs	178
resample_basis	178
resample_img	179
resample_voi	179
reslice_to_mrs	180
reson_table2mrs_data	180
re_weighting	181
rm_dyns	181

scale_amp_legacy	182
scale_amp_molal	183
scale_amp_molal_pvc	184
scale_amp_molar	184
scale_amp_molar2molal_pvc	185
scale_amp_ratio	186
scale_amp_ratio_value	186
scale_amp_water_ratio	187
scale_basis_amp	187
scale_basis_from_singlet	188
scale_mrs_amp	188
scale_spec	189
sd.list	189
sd.mrs_data	190
seconds	191
segment_t1_fsl	191
seq_cpmg_ideal	192
seq_mega_press_ideal	192
seq_press_2d_shaped	193
seq_press_ideal	194
seq_pulse_acquire	195
seq_slaser_ideal	195
seq_spin_echo_ideal	196
seq_steam_ideal	196
seq_steam_ideal_cof	197
seq_steam_ideal_young	197
set_def_acq_paras	198
set_lcm_cmd	199
set_lw	199
set_mask_xy_mat	200
set_Ntrans	200
set_precomp_mode	201
set_precomp_verbose	201
set_ref	201
set_td_pts	202
set_tqn_cmd	202
set_tr	203
shift	203
shift_basis	204
sim_basis	204
sim_basis_1h_brain	205
sim_basis_1h_brain_press	206
sim_basis_mm_lip_lcm	207
sim_basis_tqn	207
sim_brain_1h	208
sim_mol	209
sim_noise	210
sim_resonances	211

sim_th_excit_profile	212
sim_zero	212
smooth_dyns	213
sort_basis	214
spant_abfit_benchmark	214
spant_simulation_benchmark	215
spant_sim_fmrs_dataset	215
spec_decomp	216
spec_op	216
spin_sys	217
spm_pve2categorical	218
ssp	218
stackplot	219
stackplot.fit_result	219
stackplot.mrs_data	221
sub_first_dyn	223
sub_mean_dyns	223
sub_median_dyns	224
sum_coils	224
sum_dyns	225
sum_mrs	225
sum_mrs_list	226
svs_1h_brain_analysis	226
svs_1h_brain_analysis_dev	227
svs_1h_brain_batch_analysis	229
sv_res_table	230
td2fd	230
tdsr	231
td_conv_filt	231
te	232
tr	232
t_test_spec	233
varpro_3_para_opts	233
varpro_basic_opts	234
varpro_opts	235
vec2mrs_data	236
write_basis	237
write_basis_tqn	237
write_mrs	238
write_mrs_nifti	238
write_pulse_ascii	239
zero_fade_spec	239
zero_higher_orders	240
zero_td_pts_end	240
zf	241
zf_xy	241

spant-package

spant: spectroscopy analysis tools.

Description

spant provides a set of tools for reading, visualising and processing Magnetic Resonance Spectroscopy (MRS) data.

Details

To get started with spant, take a look at the introduction vignette:

```
vignette("spant-intro", package="spant")
```

Full list of vignettes:

```
browseVignettes(package = "spant")
```

Full list of functions:

```
help(package = spant, help_type = "html")
```

An online version of the documentation is available from:

<https://martin3141.github.io/spant/>

Author(s)

Maintainer: Martin Wilson <martin@pipegrep.co.uk> ([ORCID](#))

Other contributors:

- Yong Wang [contributor]
- John Muschelli [contributor]

See Also

Useful links:

- <https://spantdoc.wilsonlab.co.uk/>
- <https://martin3141.github.io/spant/>
- <https://github.com/martin3141/spant/>
- Report bugs at <https://github.com/martin3141/spant/issues/>

abfit_opts

Return a list of options for an ABfit analysis.

Description

Return a list of options for an ABfit analysis.

Usage

```
abfit_opts(
  init_damping = 5,
  maxiters = 1024,
  max_shift_pre = 0.078,
  max_shift_fine = NULL,
  max_damping = 15,
  max_phase = 360,
  lambda = NULL,
  ppm_left = 4,
  ppm_right = 0.2,
  zp = TRUE,
  bl_ed_pppm = 2,
  auto_bl_flex = TRUE,
  bl_comps_pppm = 15,
  adaptive_bl_comps_pppm = FALSE,
  export_sp_fit = FALSE,
  max_asym = 0.25,
  max_basis_shift = 0.0078,
  max_basis_damping = 2,
  maxiters_pre = 1000,
  algo_pre = "NLOPT_LN_NELDERMEAD",
  min_bl_ed_pppm = NULL,
  max_bl_ed_pppm = 7,
  auto_bl_flex_n = 20,
  pre_fit_bl_ed_pppm = 1,
  remove_lip_mm_prefit = FALSE,
  pre_align = TRUE,
  max_pre_align_shift = 0.1,
  pre_align_ref_freqs = c(2.01, 3.03, 3.22),
  noise_region = c(-0.5, -2.5),
  optimal_smooth_criterion = "maic",
  aic_smoothing_factor = 5,
  anal_jac = TRUE,
  pre_fit_ppm_left = 4,
  pre_fit_ppm_right = 1.8,
  phi1_optim = FALSE,
  phi1_init = 0,
  max_dphi1 = 0.2,
```

```

max_basis_shift_broad = NULL,
max_basis_damping_broad = NULL,
ahat_calc_method = "lh_pnnls",
prefit_phase_search = TRUE,
freq_reg = NULL,
freq_reg_naa = NULL,
lb_reg = NULL,
asym_reg = NULL,
output_all_paras = FALSE,
output_all_paras_raw = FALSE,
input_paras_raw = NULL,
optim_lw_only = FALSE,
optim_lw_only_limit = 20,
lb_init = 0.001,
lb_init_approx_fit = FALSE,
zf_offset = NULL
)

```

Arguments

<code>init_damping</code>	initial value of the Gaussian global damping parameter (Hz). Very poorly shimmed or high field data may benefit from a larger value.
<code>maxiters</code>	The maximum number of iterations to run for the detailed fit.
<code>max_shift_pre</code>	The maximum allowable global shift to be applied in the approximate (pre-fit) phases of analysis (ppm).
<code>max_shift_fine</code>	The maximum allowable global shift to be applied in the detailed fit phase of analysis (ppm).
<code>max_damping</code>	maximum permitted value of the global damping parameter (Hz).
<code>max_phase</code>	the maximum absolute permitted value of the global zero-order phase term (degrees). Note, the <code>prefit_phase_search</code> option is not constrained by this term.
<code>lambda</code>	manually set the the baseline smoothness parameter.
<code>ppm_left</code>	downfield frequency limit for the fitting range (ppm).
<code>ppm_right</code>	upfield frequency limit for the fitting range (ppm).
<code>zp</code>	zero pad the data to twice the original length before fitting.
<code>bl_ed_pppm</code>	manually set the the baseline smoothness parameter (ED per ppm).
<code>auto_bl_flex</code>	automatically determine the level of baseline smoothness.
<code>bl_comps_pppm</code>	spline basis density (signals per ppm).
<code>adaptive_bl_comps_pppm</code>	adjust the spline basis density in the detailed fit phase, based on the required level of smoothness, to reduce computation time.
<code>export_sp_fit</code>	add the fitted spline functions to the fit result.
<code>max_asym</code>	maximum allowable value of the asymmetry parameter.
<code>max_basis_shift</code>	maximum allowable frequency shift for individual basis signals (ppm).

max_basis_damping	maximum allowable Lorentzian damping factor for individual basis signals (Hz).
maxiters_pre	maximum iterations for the coarse (pre-)fit.
algo_pre	optimisation method for the coarse (pre-)fit.
min_bl_ed_ppm	minimum value for the candidate baseline flexibility analyses (ED per ppm).
max_bl_ed_ppm	maximum value for the candidate baseline flexibility analyses (ED per ppm).
auto_bl_flex_n	number of candidate baseline analyses to perform.
pre_fit_bl_ed_ppm	level of baseline flexibility to use in the coarse fitting stage of the algorithm (ED per ppm).
remove_lip_mm_prefit	remove broad signals in the coarse fitting stage of the algorithm.
pre_align	perform a pre-alignment step before coarse fitting.
max_pre_align_shift	maximum allowable shift in the pre-alignment step (ppm).
pre_align_ref_freqs	a vector of prominent spectral frequencies used in the pre-alignment step (ppm).
noise_region	spectral region to estimate the noise level (ppm).
optimal_smooth_criterion	method to determine the optimal smoothness.
aic_smoothing_factor	modification factor for the AIC calculation. Larger values result in less flexible baselines.
anal_jac	use an analytical approximation to the jacobian in the detailed fitting stage.
pre_fit_ppm_left	downfield frequency limit for the fitting range in the coarse fitting stage of the algorithm (ppm).
pre_fit_ppm_right	upfield frequency limit for the fitting range in the coarse fitting stage of the algorithm (ppm).
phi1_optim	apply and optimise a frequency dependant phase term.
phi1_init	initial value for the frequency dependant phase term (ms).
max_dphi1	maximum allowable change from the initial frequency dependant phase term (ms).
max_basis_shift_broad	maximum allowable shift for broad signals in the basis (ppm). Determined based on their name beginning with Lip or MM. The default value is set to max_basis_shift.
max_basis_damping_broad	maximum allowable Lorentzian damping for broad signals in the basis (Hz). Determined based on their name beginning with Lip or MM. The default value is set to max_basis_damping.

ahat_calc_method	method to calculate the metabolite amplitudes. May be one of: "lh_pnnls" or "ls".
prefit_phase_search	perform a 1D search for the optimal phase in the prefit stage of the algorithm.
freq_reg	frequency shift parameter.
freq_reg_naa	frequency shift parameter for NAA and NAAG.
lb_reg	individual line broadening parameter.
asym_reg	lineshape asymmetry parameter.
output_all_paras	include more fitting parameters in the fit table, e.g. individual shift and damping factors for each basis set element.
output_all_paras_raw	include raw fitting parameters in the fit table. For advanced diagnostic use only.
input_paras_raw	input raw fitting parameters. For advanced diagnostic use only.
optim_lw_only	optimize the global line-broadening term only.
optim_lw_only_limit	limits for the line-broadening term as a percentage of the starting value when optim_lw_only is TRUE.
lb_init	initial Lorentzian line broadening value (in Hz) for the individual basis signals. Setting to 0 will clash with the minimum allowable value (eg hard constraint) during the detailed fit.
lb_init_approx_fit	apply lb_init to the basis during the approximate iterative fit.
zf_offset	offset in number of data points from the end of the FID to zero-fill. Default is NULL and will automatically set this to 50 points when the FID distortion flag is set for the mrs_data.

Value

full list of options.

Examples

```
opts <- abfit_opts(ppm_left = 4.2, noise_region = c(-1, -3))
```

abfit_opts_v1_9_0	<i>Return a list of options for an ABfit analysis to maintain comparability with analyses performed with version 1.9.0 (and earlier) of spant.</i>
-------------------	--

Description

Return a list of options for an ABfit analysis to maintain comparability with analyses performed with version 1.9.0 (and earlier) of spant.

Usage

```
abfit_opts_v1_9_0(...)
```

Arguments

... arguments passed to [abfit_opts](#).

Value

full list of options.

abfit_reg_opts	<i>Return a list of options for an ABfit analysis with regularisation.</i>
----------------	--

Description

Return a list of options for an ABfit analysis with regularisation.

Usage

```
abfit_reg_opts(
  init_damping = 5,
  maxiters = 128,
  max_shift_pre = 0.078,
  max_shift_fine = 0.05,
  max_damping = 15,
  max_phase = 360,
  lambda = NULL,
  ppm_left = 4,
  ppm_right = 0.2,
  zp = TRUE,
  bl_ed_pppm = 2,
  auto_bl_flex = TRUE,
  bl_comps_pppm = 15,
  adaptive_bl_comps_pppm = TRUE,
  export_sp_fit = FALSE,
  max_asym = Inf,
  max_basis_shift = Inf,
  max_basis_damping = Inf,
  maxiters_pre = 1000,
  algo_pre = "NLOPT_LN_NELDERMEAD",
  min_bl_ed_pppm = NULL,
  max_bl_ed_pppm = 7,
  auto_bl_flex_n = 20,
  pre_fit_bl_ed_pppm = 1,
  remove_lip_mm_prefit = FALSE,
  pre_align = TRUE,
```

```

max_pre_align_shift = 0.1,
pre_align_ref_freqs = c(2.01, 3.03, 3.22),
noise_region = c(-0.5, -2.5),
optimal_smooth_criterion = "maic",
aic_smoothing_factor = 5,
anal_jac = TRUE,
pre_fit_ppm_left = 4,
pre_fit_ppm_right = 1.8,
phi1_optim = FALSE,
phi1_init = 0,
max_dphi1 = 0.2,
max_basis_shift_broad = NULL,
max_basis_damping_broad = NULL,
ahat_calc_method = "lh_pnnls",
prefit_phase_search = TRUE,
freq_reg = 0.004,
freq_reg_naa = NULL,
lb_reg = "lcm_compat",
asym_reg = 0.1,
output_all_paras = FALSE,
output_all_paras_raw = FALSE,
input_paras_raw = NULL,
optim_lw_only = FALSE,
optim_lw_only_limit = 20,
lb_init = "lcm_compat",
lb_init_approx_fit = FALSE,
zf_offset = NULL
)

```

Arguments

<code>init_damping</code>	initial value of the Gaussian global damping parameter (Hz). Very poorly shimmed or high field data may benefit from a larger value.
<code>maxiters</code>	The maximum number of iterations to run for the detailed fit.
<code>max_shift_pre</code>	The maximum allowable global shift to be applied in the approximate (pre-fit) phases of analysis (ppm).
<code>max_shift_fine</code>	The maximum allowable global shift to be applied in the detailed fit phase of analysis (ppm).
<code>max_damping</code>	maximum permitted value of the global damping parameter (Hz).
<code>max_phase</code>	the maximum absolute permitted value of the global zero-order phase term (degrees). Note, the <code>prefit_phase_search</code> option is not constrained by this term.
<code>lambda</code>	manually set the the baseline smoothness parameter.
<code>ppm_left</code>	downfield frequency limit for the fitting range (ppm).
<code>ppm_right</code>	upfield frequency limit for the fitting range (ppm).
<code>zp</code>	zero pad the data to twice the original length before fitting.
<code>bl_ed_pppm</code>	manually set the the baseline smoothness parameter (ED per ppm).

auto_bl_flex	automatically determine the level of baseline smoothness.
bl_comps_pppm	spline basis density (signals per ppm).
adaptive_bl_comps_pppm	adjust the spline basis density in the detailed fit phase, based on the required level of smoothness, to reduce computation time.
export_sp_fit	add the fitted spline functions to the fit result.
max_asym	maximum allowable value of the asymmetry parameter.
max_basis_shift	maximum allowable frequency shift for individual basis signals (ppm).
max_basis_damping	maximum allowable Lorentzian damping factor for individual basis signals (Hz).
maxiters_pre	maximum iterations for the coarse (pre-)fit.
algo_pre	optimisation method for the coarse (pre-)fit.
min_bl_ed_pppm	minimum value for the candidate baseline flexibility analyses (ED per ppm).
max_bl_ed_pppm	maximum value for the candidate baseline flexibility analyses (ED per ppm).
auto_bl_flex_n	number of candidate baseline analyses to perform.
pre_fit_bl_ed_pppm	level of baseline flexibility to use in the coarse fitting stage of the algorithm (ED per ppm).
remove_lip_mm_prefit	remove broad signals in the coarse fitting stage of the algorithm.
pre_align	perform a pre-alignment step before coarse fitting.
max_pre_align_shift	maximum allowable shift in the pre-alignment step (ppm).
pre_align_ref_freqs	a vector of prominent spectral frequencies used in the pre-alignment step (ppm).
noise_region	spectral region to estimate the noise level (ppm).
optimal_smooth_criterion	method to determine the optimal smoothness.
aic_smoothing_factor	modification factor for the AIC calculation. Larger values result in less flexible baselines.
anal_jac	use a analytical approximation to the jacobian in the detailed fitting stage.
pre_fit_ppm_left	downfield frequency limit for the fitting range in the coarse fitting stage of the algorithm (ppm).
pre_fit_ppm_right	upfield frequency limit for the fitting range in the coarse fitting stage of the algorithm (ppm).
phi1_optim	apply and optimise a frequency dependant phase term.
phi1_init	initial value for the frequency dependant phase term (ms).

max_dphi1	maximum allowable change from the initial frequency dependant phase term (ms).
max_basis_shift_broad	maximum allowable shift for broad signals in the basis (ppm). Determined based on their name beginning with Lip or MM. The default value is set to max_basis_shift.
max_basis_damping_broad	maximum allowable Lorentzian damping for broad signals in the basis (Hz). Determined based on their name beginning with Lip or MM. The default value is set to max_basis_damping.
ahat_calc_method	method to calculate the metabolite amplitudes. May be one of: "lh_pnnls" or "ls".
prefit_phase_search	perform a 1D search for the optimal phase in the prefit stage of the algorithm.
freq_reg	frequency shift parameter.
freq_reg_naa	frequency shift parameter for NAA and NAAG.
lb_reg	individual line broadening parameter.
asym_reg	lineshape asymmetry parameter.
output_all_paras	include more fitting parameters in the fit table, e.g. individual shift and damping factors for each basis set element.
output_all_paras_raw	include raw fitting parameters in the fit table. For advanced diagnostic use only.
input_paras_raw	input raw fitting parameters. For advanced diagnostic use only.
optim_lw_only	optimize the global line-broadening term only.
optim_lw_only_limit	limits for the line-breading term as a percentage of the starting value when optim_lw_only is TRUE.
lb_init	initial Lorentzian line broadening value (in Hz) for the individual basis signals. Setting to 0 will clash with the minimum allowable value (eg hard constraint) during the detailed fit.
lb_init_approx_fit	apply lb_init to the basis during the approximate iterative fit.
zf_offset	offset in number of data points from the end of the FID to zero-fill. Default is NULL and will automatically set this to 50 points when the FID distortion flag is set for the mrs_data.

Value

full list of options.

Examples

```
opts <- abfit_reg_opts(ppm_left = 4.2, noise_region = c(-1, -3))
```

acquire	<i>Simulate pulse sequence acquisition.</i>
---------	---

Description

Simulate pulse sequence acquisition.

Usage

```
acquire(sys, rec_phase = 0, tol = 1e-04, detect = NULL, amp_scale = 1)
```

Arguments

sys	spin system object.
rec_phase	receiver phase in degrees.
tol	ignore resonance amplitudes below this threshold.
detect	detection nuclei.
amp_scale	scaling factor for the output amplitudes.

Value

a list of resonance amplitudes and frequencies.

add_noise	<i>Add noise to an mrs_data object.</i>
-----------	---

Description

Add noise to an mrs_data object.

Usage

```
add_noise(mrs_data, sd = 0.1, fd = TRUE)
```

Arguments

mrs_data	data to add noise to.
sd	standard deviation of the noise.
fd	generate the noise samples in the frequency-domain (TRUE) or time-domain (FALSE). This is required since the absolute value of the standard deviation of noise samples changes when data is Fourier transformed.

Value

mrs_data object with additive normally distributed noise.

add_noise_spec_snr	<i>Add noise to an mrs_data object to match a given SNR.</i>
--------------------	--

Description

Add noise to an mrs_data object to match a given SNR.

Usage

```
add_noise_spec_snr(
  mrs_data,
  target_snr,
  sig_region = c(4, 0.5),
  ref_data = NULL
)
```

Arguments

mrs_data	data to add noise to.
target_snr	desired spectral SNR, note this assumes the input data is noise-free, eg simulated data. Note the SNR is estimated from the first scan in the dataset and the same noise level is added to all spectra.
sig_region	spectral limits to search for the strongest spectral data point.
ref_data	measure the signal from the first scan in this reference data and apply the same target noise level to mrs_data.

Value

mrs_data object with additive normally distributed noise.

align	<i>Align spectra to a reference frequency using a convolution based method.</i>
-------	---

Description

Align spectra to a reference frequency using a convolution based method.

Usage

```
align(
  mrs_data,
  ref_freq = 4.65,
  ref_amp = 1,
  zf_factor = 2,
  lb = 2,
  max_shift = 20,
  ret_df = FALSE,
  mean_dyns = FALSE
)
```

Arguments

mrs_data	data to be aligned.
ref_freq	reference frequency in ppm units. More than one frequency may be specified.
ref_amp	amplitude value for the reference signal. More than one value may be specified to match the number of ref_freq signals.
zf_factor	zero filling factor to increase alignment resolution.
lb	line broadening to apply to the reference signal.
max_shift	maximum allowable shift in Hz.
ret_df	return frequency shifts in addition to aligned data (logical).
mean_dyns	align the mean spectrum and apply the same shift to each dynamic.

Value

aligned data object.

apodise_xy	<i>Apodise MRSI data in the x-y direction with a k-space filter.</i>
------------	--

Description

Apodise MRSI data in the x-y direction with a k-space filter.

Usage

```
apodise_xy(mrs_data, func = "hamming", w = 2.5)
```

Arguments

mrs_data	MRSI data.
func	must be "hamming", "hanning" or "gaussian".
w	the reciprocal of the standard deviation for the Gaussian function.

Value

apodised data.

append_basis	<i>Combine a pair of basis set objects.</i>
--------------	---

Description

Combine a pair of basis set objects.

Usage

```
append_basis(basis_a, basis_b)
```

Arguments

basis_a	first basis.
basis_b	second basis.

Value

combined basis set object.

append_coils	<i>Append MRS data across the coil dimension, assumes they matched across the other dimensions.</i>
--------------	---

Description

Append MRS data across the coil dimension, assumes they matched across the other dimensions.

Usage

```
append_coils(...)
```

Arguments

...	MRS data objects as arguments, or a list of MRS data objects.
-----	---

Value

a single MRS data object with the input objects concatenated together.

append_dyns	<i>Append MRS data across the dynamic dimension, assumes they matched across the other dimensions.</i>
-------------	--

Description

Append MRS data across the dynamic dimension, assumes they matched across the other dimensions.

Usage

```
append_dyns(...)
```

Arguments

... MRS data objects as arguments, or a list of MRS data objects.

Value

a single MRS data object with the input objects concatenated together.

append_regs	<i>Append multiple regressor data frames into a single data frame.</i>
-------------	--

Description

Append multiple regressor data frames into a single data frame.

Usage

```
append_regs(...)
```

Arguments

... input regressor data frames.

Value

output regressor data frame.

apply_axes	<i>Apply a function over specified array axes.</i>
------------	--

Description

Apply a function over specified array axes.

Usage

```
apply_axes(x, axes, fun, ...)
```

Arguments

x	an array.
axes	a vector of axes to apply fun over.
fun	function to be applied.
...	optional arguments to fun.

Value

array.

Examples

```
z <- array(1:1000, dim = c(10, 10, 10))
a <- apply_axes(z, 3, fft)
a[1,1,] == fft(z[1,1,])
a <- apply_axes(z, 3, sum)
a[1,1,] == sum(z[1,1,])
```

apply_mrs	<i>Apply a function across given dimensions of a MRS data object.</i>
-----------	---

Description

Apply a function across given dimensions of a MRS data object.

Usage

```
apply_mrs(mrs_data, dims, fun, ..., data_only = FALSE)
```

Arguments

<code>mrs_data</code>	MRS data.
<code>dims</code>	dimensions to apply the function.
<code>fun</code>	name of the function.
<code>...</code>	arguments to the function.
<code>data_only</code>	return an array rather than an MRS data object.

<code>apply_pulse</code>	<i>Simulate an RF pulse on a single spin.</i>
--------------------------	---

Description

Simulate an RF pulse on a single spin.

Usage

```
apply_pulse(sys, rho, spin_n, angle, nuc, xy)
```

Arguments

<code>sys</code>	spin system object.
<code>rho</code>	density matrix.
<code>spin_n</code>	spin index.
<code>angle</code>	RF flip angle in degrees.
<code>nuc</code>	nucleus influenced by the pulse.
<code>xy</code>	x or y pulse.

Value

density matrix.

Arg.mrs_data	<i>Apply Arg operator to an MRS dataset.</i>
--------------	--

Description

Apply Arg operator to an MRS dataset.

Usage

```
## S3 method for class 'mrs_data'
Arg(z)
```

Arguments

z MRS data.

Value

MRS data following Arg operator.

array2mrs_data	<i>Convert a 7 dimensional array in into a mrs_data object. The array dimensions should be ordered as : dummy, X, Y, Z, dynamic, coil, FID.</i>
----------------	---

Description

Convert a 7 dimensional array in into a mrs_data object. The array dimensions should be ordered as : dummy, X, Y, Z, dynamic, coil, FID.

Usage

```
array2mrs_data(
  data_array,
  mrs_data = NULL,
  fs = NULL,
  ft = NULL,
  ref = NULL,
  nuc = NULL,
  fd = FALSE
)
```

Arguments

data_array	7d data array.
mrs_data	example data to copy acquisition parameters from.
fs	sampling frequency in Hz.
ft	transmitter frequency in Hz.
ref	reference value for ppm scale.
nuc	nucleus that is resonant at the transmitter frequency.
fd	flag to indicate if the matrix is in the frequency domain (logical).

Value

mrs_data object.

auto_phase	<i>Perform zeroth-order phase correction based on the minimisation of the squared difference between the real and magnitude components of the spectrum.</i>
------------	---

Description

Perform zeroth-order phase correction based on the minimisation of the squared difference between the real and magnitude components of the spectrum.

Usage

```
auto_phase(mrs_data, xlim = c(4, 1.8), smo_ppm_sd = 0.05, ret_phase = FALSE)
```

Arguments

mrs_data	an object of class mrs_data.
xlim	frequency range (default units of PPM) to including in the phase.
smo_ppm_sd	Gaussian smoother sd in ppm units.
ret_phase	return phase values (logical).

Value

MRS data object and phase values (optional).

auto_phase_bl	<i>Perform zeroth-order phase correction based on expected baseline regions.</i>
---------------	--

Description

Default arguments are appropriate for water suppressed 1H MRS of the brain. The following options are suitable for a water signal at 4.65 ppm: ppm_start = c(5.2, 4.0), ppm_end = c(5.3, 4.1), xlim = c(5.2, 4.1)

Usage

```
auto_phase_bl(
  mrs_data,
  ppm_start = c(0.5, 4),
  ppm_end = c(0, 4.2),
  xlim = c(1.8, 4),
  mean_dyns = FALSE,
  ret_phase = FALSE
)
```

Arguments

mrs_data	an object of class mrs_data.
ppm_start	a vector of ppm values designating baseline regions.
ppm_end	a vectors of ppm values designating baseline regions.
xlim	region containing signal of interest, eg strong metabolite resonances.
mean_dyns	phase the mean spectrum and apply the same value to each dynamic.
ret_phase	return phase values (logical).

Value

MRS data object with corrected phase.

back_extrap_ar	<i>Back extrapolate time-domain data points using an autoregressive model.</i>
----------------	--

Description

Back extrapolate time-domain data points using an autoregressive model.

Usage

```
back_extrap_ar(
  mrs_data,
  extrap_pts,
  pred_pts = NULL,
  method = "burg",
  rem_add = TRUE,
  ...
)
```

Arguments

mrs_data	mrs_data object.
extrap_pts	number of points to extrapolate.
pred_pts	number of points to base the extrapolation on.
method	character string specifying the method to fit the model. Must be one of the strings in the default argument (the first few characters are sufficient). Defaults to "burg".
rem_add	remove additional points from the end of the FID to maintain the original length of the dataset. Default to TRUE.
...	additional arguments to specific methods, see ?ar.

Value

back extrapolated data.

basis2dyn_mrs_data	<i>Convert a basis object to a dynamic mrs_data object.</i>
--------------------	---

Description

Convert a basis object to a dynamic mrs_data object.

Usage

```
basis2dyn_mrs_data(basis, amps, tr)
```

Arguments

basis	basis set object.
amps	a data frame with each column corresponding to a basis element and each row corresponding to each dynamic scan.
tr	the dataset repetition time in seconds.

Value

a dynamic mrs_data object.

basis2mrs_data	<i>Convert a basis object to an mrs_data object - where basis signals are spread across the dynamic dimension.</i>
----------------	--

Description

Convert a basis object to an mrs_data object - where basis signals are spread across the dynamic dimension.

Usage

```
basis2mrs_data(
  basis,
  sum_elements = FALSE,
  amps = NULL,
  shifts = NULL,
  lbs = NULL
)
```

Arguments

basis	basis set object.
sum_elements	return the sum of basis elements (logical)
amps	a vector of scaling factors to apply to each basis element.
shifts	a vector of frequency shifts (in ppm) to apply to each basis element.
lbs	a vector of Lorentzian line broadening terms (in Hz) to apply to each basis element.

Value

an mrs_data object with basis signals spread across the dynamic dimension or summed.

bbase	<i>Generate a spline basis, slightly adapted from : "Splines, knots, and penalties", Eilers 2010.</i>
-------	---

Description

Generate a spline basis, slightly adapted from : "Splines, knots, and penalties", Eilers 2010.

Usage

```
bbase(N, number, deg = 3)
```

Arguments

N	number of data points.
number	number of spline functions.
deg	spline degree : deg = 1 linear, deg = 2 quadratic, deg = 3 cubic.

Value

spline basis as a matrix.

bc_als	<i>Baseline correction using the ALS method.</i>
--------	--

Description

Eilers P. H. C. and Boelens H. F. M. (2005) Baseline correction with asymmetric least squares smoothing. Leiden Univ. Medical Centre Report.

Usage

```
bc_als(mrs_data, lambda = 10000, p = 0.001, ret_bc_only = TRUE)
```

Arguments

mrs_data	mrs_data object.
lambda	controls the baseline flexibility.
p	controls the penalty for negative data points.
ret_bc_only	return the baseline corrected data only. When FALSE the baseline estimate and input data will be returned.

Value

baseline corrected data.

bc_constant	<i>Remove a constant baseline offset based on a reference spectral region.</i>
-------------	--

Description

Remove a constant baseline offset based on a reference spectral region.

Usage

```
bc_constant(mrs_data, xlim)
```

Arguments

mrs_data	MRS data.
xlim	spectral range containing a flat baseline region to measure the offset.

Value

baseline corrected data.

bc_gauss	<i>Apply and subtract a Gaussian smoother in the spectral domain.</i>
----------	---

Description

Apply and subtract a Gaussian smoother in the spectral domain.

Usage

```
bc_gauss(mrs_data, smo_ppm_sd)
```

Arguments

mrs_data	mrs_data object.
smo_ppm_sd	Gaussian smoother sd in ppm units.

Value

smoother subtracted data.

bc_poly	<i>Fit and subtract a polynomial to each spectrum in a dataset.</i>
---------	---

Description

Fit and subtract a polynomial to each spectrum in a dataset.

Usage

```
bc_poly(mrs_data, p_deg = 1)
```

Arguments

mrs_data	mrs_data object.
p_deg	polynomial degree.

Value

polynomial subtracted data.

bc_spline	<i>Fit and subtract a smoothing spline to each spectrum in a dataset.</i>
-----------	---

Description

Fit and subtract a smoothing spline to each spectrum in a dataset.

Usage

```
bc_spline(mrs_data, spar = 0.5, nknots = 100)
```

Arguments

mrs_data	mrs_data object.
spar	smoothing parameter typically between 0 and 1.
nknots	number of spline knots.

Value

smoothing spline subtracted data.

beta2lw	<i>Covert a beta value in the time-domain to an equivalent linewidth in Hz: $x * \exp(-i * t * t * \text{beta})$.</i>
---------	--

Description

Covert a beta value in the time-domain to an equivalent linewidth in Hz: $x * \exp(-i * t * t * \text{beta})$.

Usage

```
beta2lw(beta)
```

Arguments

beta	beta damping value.
------	---------------------

Value

linewidth value in Hz.

bin_spec	<i>Bin equally spaced spectral regions.</i>
----------	---

Description

Bin equally spaced spectral regions.

Usage

```
bin_spec(mrs_data, width = 0.05, unit = "ppm")
```

Arguments

mrs_data	data to be "binned".
width	bin width.
unit	bin width unit, can be "ppm" (default) or "pts".

Value

binned mrs_data object.

calc_basis_corr_mat	<i>Estimate the correlation matrix for a basis set.</i>
---------------------	---

Description

Estimate the correlation matrix for a basis set.

Usage

```
calc_basis_corr_mat(basis, xlim = c(4, 0.2), zf = TRUE)
```

Arguments

basis	basis_set object.
xlim	spectral range to use in ppm.
zf	zero-fill the basis set.

Value

correlation matrix.

calc_basis_crlbs	<i>Estimate the CRLB for each element in a basis set.</i>
------------------	---

Description

Estimate the CRLB for each element in a basis set.

Usage

```
calc_basis_crlbs(  
  basis,  
  xlim = c(4, 0.2),  
  zf = TRUE,  
  sd = 1,  
  bl_comp_pppm = NULL  
)
```

Arguments

basis	basis_set object.
xlim	spectral range to use in ppm.
zf	zero-fill the basis set.
sd	standard deviation of the noise.
bl_comp_pppm	number spline baseline components to append per-ppm.

Value

a vector of predicted errors.

calc_coil_noise_cor	<i>Calculate the noise correlation between coil elements.</i>
---------------------	---

Description

Calculate the noise correlation between coil elements.

Usage

```
calc_coil_noise_cor(noise_data)
```

Arguments

noise_data mrs_data object with one FID for each coil element.

Value

correlation matrix.

calc_coil_noise_sd	<i>Calculate the noise standard deviation for each coil element.</i>
--------------------	--

Description

Calculate the noise standard deviation for each coil element.

Usage

```
calc_coil_noise_sd(noise_data)
```

Arguments

noise_data mrs_data object with one FID for each coil element.

Value

array of standard deviations.

`calc_design_efficiency`*Calculate the efficiency of a regressor data frame.*

Description

Calculate the efficiency of a regressor data frame.

Usage

```
calc_design_efficiency(regressor_df, contrasts)
```

Arguments

<code>regressor_df</code>	input regressor data frame.
<code>contrasts</code>	a vector of contrast values.

`calc_ed_from_lambda` *Calculate the effective dimensions of a spline smoother from lambda.*

Description

Calculate the effective dimensions of a spline smoother from lambda.

Usage

```
calc_ed_from_lambda(spline_basis, deriv_mat, lambda)
```

Arguments

<code>spline_basis</code>	spline basis.
<code>deriv_mat</code>	derivative matrix.
<code>lambda</code>	smoothing parameter.

Value

the effective dimension value.

calc_peak_info_vec	<i>Calculate the FWHM of a peak from a vector of intensity values.</i>
--------------------	--

Description

Calculate the FWHM of a peak from a vector of intensity values.

Usage

```
calc_peak_info_vec(data_pts, interp_f)
```

Arguments

data_pts	input vector.
interp_f	interpolation factor to improve the FWHM estimate.

Value

a vector of: x position of the highest data point, maximum peak value in the y axis, FWHM in the units of data points.

calc_sd_poly	<i>Perform a polynomial fit, subtract and return the standard deviation of the residuals.</i>
--------------	---

Description

Perform a polynomial fit, subtract and return the standard deviation of the residuals.

Usage

```
calc_sd_poly(y, degree = 1)
```

Arguments

y	array.
degree	polynomial degree.

Value

standard deviation of the fit residuals.

calc_spec_diff	<i>Calculate the sum of squares differences between two mrs_data objects.</i>
----------------	---

Description

Calculate the sum of squares differences between two mrs_data objects.

Usage

```
calc_spec_diff(mrs_data, ref = NULL, xlim = c(4, 0.5))
```

Arguments

mrs_data	mrs_data object.
ref	reference mrs_data object to calculate differences.
xlim	spectral limits to perform calculation.

Value

an array of the sum of squared difference values.

calc_spec_snr	<i>Calculate the spectral SNR.</i>
---------------	------------------------------------

Description

SNR is defined as the maximum signal value divided by the standard deviation of the noise.

Usage

```
calc_spec_snr(
  mrs_data,
  sig_region = c(4, 0.5),
  noise_region = c(-0.5, -2.5),
  p_order = 2,
  interp_f = 4,
  full_output = FALSE
)
```

Arguments

mrs_data	an object of class mrs_data.
sig_region	a ppm region to define where the maximum signal value should be estimated.
noise_region	a ppm region to defined where the noise level should be estimated.
p_order	polynomial order to fit to the noise region before estimating the standard deviation.
interp_f	interpolation factor to improve detection of the highest signal value.
full_output	output signal, noise and SNR values separately.

Details

The mean noise value is subtracted from the maximum signal value to reduce DC offset bias. A polynomial detrending fit (second order by default) is applied to the noise region before the noise standard deviation is estimated.

Value

an array of SNR values.

check_lcm	<i>Check LCModel can be run</i>
-----------	---------------------------------

Description

Check LCModel can be run

Usage

```
check_lcm()
```

check_tqn	<i>Check the TARQUIN binary can be run</i>
-----------	--

Description

Check the TARQUIN binary can be run

Usage

```
check_tqn()
```

circ_mask	<i>Create a logical circular mask spanning the full extent of an $n \times n$ matrix.</i>
-----------	--

Description

Create a logical circular mask spanning the full extent of an $n \times n$ matrix.

Usage

```
circ_mask(d, n, offset = 1)
```

Arguments

d	diameter of the mask.
n	number of matrix rows and columns.
offset	offset the mask centre in matrix dimension units.

Value

logical $n \times n$ mask matrix.

coherence_filter	<i>Zero all coherence orders other than the one supplied as an argument.</i>
------------------	--

Description

Zero all coherence orders other than the one supplied as an argument.

Usage

```
coherence_filter(sys, rho, order = 0)
```

Arguments

sys	spin system object.
rho	density matrix.
order	coherence order to keep (default is 0).

Value

density matrix.

collapse_to_dyns	<i>Collapse MRS data by concatenating spectra along the dynamic dimension.</i>
------------------	--

Description

Collapse MRS data by concatenating spectra along the dynamic dimension.

Usage

```
collapse_to_dyns(x, rm_masked = FALSE)

## S3 method for class 'mrs_data'
collapse_to_dyns(x, rm_masked = FALSE)

## S3 method for class 'fit_result'
collapse_to_dyns(x, rm_masked = FALSE)
```

Arguments

x	data object to be collapsed (mrs_data or fit_result object).
rm_masked	remove masked dynamics from the output.

Value

collapsed data with spectra or fits concatenated along the dynamic dimension.

comb_coils	<i>Combine coil data based on the first data point of a reference signal.</i>
------------	---

Description

By default, elements are phased and scaled prior to summation. Where a reference signal is not given, the mean dynamic signal will be used instead.

Usage

```
comb_coils(
  metab,
  ref = NULL,
  noise = NULL,
  scale = TRUE,
  scale_method = "sig_noise_sq",
  sum_coils = TRUE,
  noise_region = c(-0.5, -2.5),
```

```

    average_ref_dyns = TRUE,
    ref_pt_index = 1,
    ret_metab_only = FALSE
  )

```

Arguments

metab	MRS data containing metabolite data.
ref	MRS data containing reference data (optional).
noise	MRS data from a noise scan (optional).
scale	option to rescale coil elements based on the first data point (logical).
scale_method	one of "sig_noise_sq", "sig_noise" or "sig".
sum_coils	sum the coil elements as a final step (logical).
noise_region	the spectral region (in ppm) to estimate the noise.
average_ref_dyns	take the mean of the reference scans in the dynamic dimension before use.
ref_pt_index	time-domain point to use for estimating phase and scaling values.
ret_metab_only	return the metabolite data only, even if reference data has been specified.

Value

MRS data.

comb_coils_mrsi_gls	<i>Combine MRSI coil data using the GLS method presented by An et al JMRI 37:1445-1450 (2013).</i>
---------------------	--

Description

Combine MRSI coil data using the GLS method presented by An et al JMRI 37:1445-1450 (2013).

Usage

```
comb_coils_mrsi_gls(metab, noise_pts = 30, noise_mrs = NULL)
```

Arguments

metab	MRSI data containing metabolite data.
noise_pts	number of points from the end of the FIDs to use for noise covariance estimation.
noise_mrs	MRS data containing noise information for each coil.

Value

coil combined MRSI data.

comb_coils_svs_gls	<i>Combine SVS coil data using the GLS method presented by An et al JMRI 37:1445-1450 (2013).</i>
--------------------	---

Description

Combine SVS coil data using the GLS method presented by An et al JMRI 37:1445-1450 (2013).

Usage

```
comb_coils_svs_gls(
  metab,
  ref = NULL,
  noise_pts = 256,
  noise_mrs = NULL,
  use_mean_sens = TRUE
)
```

Arguments

metab	MRS data containing metabolite data.
ref	MRS data containing reference data (optional).
noise_pts	number of points from the end of the FIDs to use for noise covariance estimation.
noise_mrs	MRS data containing noise information for each coil.
use_mean_sens	use the dynamic mean to estimate coil sensitivities.

Value

coil combined MRS data.

comb_fit_list_dyns	<i>Combine a list of fit results into a single fit result object across the dynamic dimension.</i>
--------------------	--

Description

Combine a list of fit results into a single fit result object across the dynamic dimension.

Usage

```
comb_fit_list_dyns(fit_list, dyn_basis_sets = FALSE)
```

Arguments

`fit_list` a list of `fit_result` objects.

`dyn_basis_sets` save all basis sets separately as a list, defaults to `FALSE`.

Value

fit result object.

`comb_fit_list_fit_tables`

Combine all fitting data points from a list of fits into a single data frame.

Description

Combine all fitting data points from a list of fits into a single data frame.

Usage

```
comb_fit_list_fit_tables(
  fit_list,
  add_extra = TRUE,
  harmonise_ppm = TRUE,
  inc_basis_sigs = FALSE,
  inc_indices = TRUE,
  add_res_id = TRUE
)
```

Arguments

`fit_list` list of `fit_result` objects.

`add_extra` add variables in the extra data frame to the output (`TRUE`).

`harmonise_ppm` ensure the ppm scale for each fit is identical to the first.

`inc_basis_sigs` include the individual fitting basis signals in the output table, defaults to `FALSE`.

`inc_indices` include indices such as X, Y and coil in the output, defaults to `TRUE`. These are generally not useful for SVS analysis.

`add_res_id` add a `res_id` column to the output to distinguish between datasets.

Value

a data frame containing the fit data points.

comb_fit_list_result_tables

Combine the fit result tables from a list of fit results.

Description

Combine the fit result tables from a list of fit results.

Usage

```
comb_fit_list_result_tables(fit_list, add_extra = TRUE, add_res_id = TRUE)
```

Arguments

fit_list	a list of fit_result objects.
add_extra	add variables in the extra data frame to the output (TRUE).
add_res_id	add a res_id column to the output to distinguish between datasets.

Value

a data frame combine all fit result tables with an additional id column to differentiate between data sets. Any variables in the extra data frame may be optionally added to the result.

comb_fit_tables

Combine all fitting data points into a single data frame.

Description

Combine all fitting data points into a single data frame.

Usage

```
comb_fit_tables(fit_res, inc_basis_sigs = FALSE, inc_indices = TRUE)
```

Arguments

fit_res	a single fit_result object.
inc_basis_sigs	include the individual fitting basis signals in the output table, defaults to FALSE.
inc_indices	include indices such as X, Y and coil in the output, defaults to TRUE. These are generally not useful for SVS analysis.

Value

a data frame containing the fit data points.

comb_metab_ref	Combine a reference and metabolite mrs_data object.
----------------	---

Description

Combine a reference and metabolite mrs_data object.

Usage

```
comb_metab_ref(metab, ref)
```

Arguments

metab	metabolite mrs_data object.
ref	reference mrs_data object.

Value

combined metabolite and reference mrs_data object.

Conj.mrs_data	Apply Conj operator to an MRS dataset.
---------------	--

Description

Apply Conj operator to an MRS dataset.

Usage

```
## S3 method for class 'mrs_data'  
Conj(z)
```

Arguments

z	MRS data.
---	-----------

Value

MRS data following Conj operator.

conv_mrs	<i>Convolve two MRS data objects.</i>
----------	---------------------------------------

Description

Convolve two MRS data objects.

Usage

```
conv_mrs(mrs_data, conv)
```

Arguments

mrs_data	MRS data to be convolved.
conv	convolution data stored as an mrs_data object.

Value

convolved data.

crop_basis	<i>Crop basis_set object based on a frequency range.</i>
------------	--

Description

Crop basis_set object based on a frequency range.

Usage

```
crop_basis(basis, xlim = c(4, 0.2), scale = "ppm")
```

Arguments

basis	basis_set object to be cropped in the spectral dimension.
xlim	range of values to crop in the spectral dimension eg xlim = c(4, 0.2).
scale	the units to use for the frequency scale, can be one of: "ppm", "hz" or "points".

Value

cropped mrs_data object.

crop_spec	<i>Crop mrs_data object based on a frequency range.</i>
-----------	---

Description

Crop mrs_data object based on a frequency range.

Usage

```
crop_spec(mrs_data, xlim = c(4, 0.2), scale = "ppm")
```

Arguments

mrs_data	MRS data.
xlim	range of values to crop in the spectral dimension eg xlim = c(4, 0.2).
scale	the units to use for the frequency scale, can be one of: "ppm", "hz" or "points".

Value

cropped mrs_data object.

crop_td_pts	<i>Crop mrs_data object data points in the time-domain.</i>
-------------	---

Description

Crop mrs_data object data points in the time-domain.

Usage

```
crop_td_pts(mrs_data, start = NULL, end = NULL)
```

Arguments

mrs_data	MRS data.
start	starting data point (defaults to 1).
end	ending data point (defaults to the last saved point).

Value

cropped mrs_data object.

crop_td_pts_end	<i>Crop mrs_data object data points at the end of the FID.</i>
-----------------	--

Description

Crop mrs_data object data points at the end of the FID.

Usage

crop_td_pts_end(mrs_data, pts)

Arguments

- mrs_data MRS data.
- pts number of points to remove from the end of the FID.

Value

cropped mrs_data object.

crop_td_pts_pot	<i>Crop mrs_data object data points in the time-domain rounding down to the next smallest power of two (pot). Data that already has a pot length will not be changed.</i>
-----------------	---

Description

Crop mrs_data object data points in the time-domain rounding down to the next smallest power of two (pot). Data that already has a pot length will not be changed.

Usage

crop_td_pts_pot(mrs_data)

Arguments

- mrs_data MRS data.

Value

cropped mrs_data object.

crop_xy	<i>Crop an MRSI dataset in the x-y direction</i>
---------	--

Description

Crop an MRSI dataset in the x-y direction

Usage

```
crop_xy(mrs_data, x_dim, y_dim)
```

Arguments

mrs_data	MRS data object.
x_dim	x dimension output length.
y_dim	y dimension output length.

Value

selected subset of MRS data.

crossprod_3d	<i>Compute the vector cross product between vectors x and y. Adapted from http://stackoverflow.com/questions/15162741/what-is-rs-crossproduct-function</i>
--------------	---

Description

Compute the vector cross product between vectors x and y. Adapted from <http://stackoverflow.com/questions/15162741/what-is-rs-crossproduct-function>

Usage

```
crossprod_3d(x, y)
```

Arguments

x	vector of length 3.
y	vector of length 3.

Value

vector cross product of x and y.

decimate_mrs_fd	<i>Decimate an MRS signal to half the original sampling frequency by filtering in the frequency domain before down sampling.</i>
-----------------	--

Description

Decimate an MRS signal to half the original sampling frequency by filtering in the frequency domain before down sampling.

Usage

```
decimate_mrs_fd(mrs_data)
```

Arguments

mrs_data	MRS data object.
----------	------------------

Value

decimated data at half the original sampling frequency.

decimate_mrs_td	<i>Decimate an MRS signal by filtering in the time domain before down-sampling.</i>
-----------------	---

Description

Decimate an MRS signal by filtering in the time domain before downsampling.

Usage

```
decimate_mrs_td(mrs_data, q = 2, n = 4, ftype = "iir")
```

Arguments

mrs_data	MRS data object.
q	integer factor to downsample by (default = 2).
n	filter order used in the downsampling.
ftype	filter type, "iir" or "fir".

Value

decimated data.

deconv_mrs	<i>Deconvolve two MRS data objects.</i>
------------	---

Description

Deconvolve two MRS data objects.

Usage

```
deconv_mrs(mrs_data_a, mrs_data_b)
```

Arguments

mrs_data_a	MRS data to be deconvolved.
mrs_data_b	MRS data to be deconvolved.

Value

deconvolved data.

def_acq_paras	<i>Return (and optionally modify using the input arguments) a list of the default acquisition parameters.</i>
---------------	---

Description

Return (and optionally modify using the input arguments) a list of the default acquisition parameters.

Usage

```
def_acq_paras(
  ft = getOption("spant.def_ft"),
  fs = getOption("spant.def_fs"),
  N = getOption("spant.def_N"),
  ref = getOption("spant.def_ref"),
  nuc = getOption("spant.def_nuc")
)
```

Arguments

ft	specify the transmitter frequency in Hz.
fs	specify the sampling frequency in Hz.
N	specify the number of data points in the spectral dimension.
ref	specify the reference value for ppm scale.
nuc	specify the resonant nucleus.

Value

A list containing the following elements:

- ft transmitter frequency in Hz.
- fs sampling frequency in Hz.
- N number of data points in the spectral dimension.
- ref reference value for ppm scale.
- nuc resonant nucleus.

def_fs	<i>Return the default sampling frequency in Hz.</i>
--------	---

Description

Return the default sampling frequency in Hz.

Usage

```
def_fs()
```

Value

sampling frequency in Hz.

def_ft	<i>Return the default transmitter frequency in Hz.</i>
--------	--

Description

Return the default transmitter frequency in Hz.

Usage

```
def_ft()
```

Value

transmitter frequency in Hz.

def_N	<i>Return the default number of data points in the spectral dimension.</i>
-------	--

Description

Return the default number of data points in the spectral dimension.

Usage

def_N()

Value

number of data points in the spectral dimension.

def_nuc	<i>Return the default nucleus.</i>
---------	------------------------------------

Description

Return the default nucleus.

Usage

def_nuc()

Value

number of data points in the spectral dimension.

def_ref	<i>Return the default reference value for ppm scale.</i>
---------	--

Description

Return the default reference value for ppm scale.

Usage

def_ref()

Value

reference value for ppm scale.

dicom_reader	<i>A very simple DICOM reader.</i>
--------------	------------------------------------

Description

Note this reader is very basic and does not use a DICOM dictionary or try to convert the data to the correct datatype. For a more robust and sophisticated reader use the `oro.dicom` package.

Usage

```
dicom_reader(
  input,
  tags = list(sop_class_uid = "0008,0016"),
  endian = "little",
  debug = FALSE
)
```

Arguments

input	either a file path or raw binary object.
tags	a named list of tags to be extracted from the file. eg <code>tags <- list(spec_data = "7FE1,1010", pat_name = "0010,0010")</code>
endian	can be "little" or "big".
debug	print out some debugging information, can be "little" or "big".

Value

a list with the same structure as the input, but with tag codes replaced with the corresponding data in a raw format.

diff_mrs	<i>Apply the diff operator to an MRS dataset in the FID/spectral dimension.</i>
----------	---

Description

Apply the diff operator to an MRS dataset in the FID/spectral dimension.

Usage

```
diff_mrs(mrs_data, ...)
```

Arguments

mrs_data	MRS data.
...	additional arguments to the diff function.

Value

MRS data following diff operator.

downsample_mrs_fd	<i>Downsample an MRS signal by a factor of 2 using an FFT "brick-wall" filter.</i>
-------------------	--

Description

Downsample an MRS signal by a factor of 2 using an FFT "brick-wall" filter.

Usage

```
downsample_mrs_fd(mrs_data)
```

Arguments

mrs_data	MRS data object.
----------	------------------

Value

downsampled data.

downsample_mrs_td	<i>Downsample an MRS signal by a factor of 2 by removing every other data point in the time-domain. Note, signals outside the new sampling frequency will be aliased.</i>
-------------------	---

Description

Downsample an MRS signal by a factor of 2 by removing every other data point in the time-domain. Note, signals outside the new sampling frequency will be aliased.

Usage

```
downsample_mrs_td(mrs_data)
```

Arguments

mrs_data	MRS data object.
----------	------------------

Value

downsampled data.

<code>dyn_acq_times</code>	<i>Return a time scale vector of acquisition times for a dynamic MRS scan. The first temporal scan is assigned a value of 0.</i>
----------------------------	--

Description

Return a time scale vector of acquisition times for a dynamic MRS scan. The first temporal scan is assigned a value of 0.

Usage

```
dyn_acq_times(mrs_data = NULL, tr = NULL, Ndyns = NULL, Ntrans = NULL)
```

Arguments

<code>mrs_data</code>	MRS data.
<code>tr</code>	repetition time.
<code>Ndyns</code>	number of dynamic scans stored, potentially less than <code>Ntrans</code> if block averaging has been performed.
<code>Ntrans</code>	number of dynamic scans acquired.

Value

time scale vector in units of seconds.

<code>ecc</code>	<i>Eddy current correction.</i>
------------------	---------------------------------

Description

Apply eddy current correction using the Klose method.

Usage

```
ecc(metab, ref, rev = FALSE)
```

Arguments

<code>metab</code>	MRS data to be corrected.
<code>ref</code>	reference dataset.
<code>rev</code>	reverse the correction.

Details

In vivo proton spectroscopy in presence of eddy currents. Klose U. Magn Reson Med. 1990 Apr;14(1):26-30.

Value

corrected data in the time domain.

elliptical_mask	Create an elliptical mask stored as a matrix of logical values.
-----------------	---

Description

Create an elliptical mask stored as a matrix of logical values.

Usage

```
elliptical_mask(xN, yN, x0, y0, xr, yr, angle)
```

Arguments

xN	number of pixels in the x dimension.
yN	number of pixels in the y dimension.
x0	centre of ellipse in the x direction in units of pixels.
y0	centre of ellipse in the y direction in units of pixels.
xr	radius in the x direction in units of pixels.
yr	radius in the y direction in units of pixels.
angle	angle of rotation in degrees.

Value

logical mask matrix with dimensions fov_yN x fov_xN.

<code>est_noise_sd</code>	<i>Estimate the standard deviation of the noise from a segment of an <code>mrs_data</code> object.</i>
---------------------------	--

Description

Estimate the standard deviation of the noise from a segment of an `mrs_data` object.

Usage

```
est_noise_sd(mrs_data, n = 100, offset = 100, p_order = 2)
```

Arguments

<code>mrs_data</code>	MRS data object.
<code>n</code>	number of data points (taken from the end of array) to use in the estimation.
<code>offset</code>	number of final points to exclude from the calculation.
<code>p_order</code>	polynomial order to fit to the data before estimating the standard deviation.

Value

standard deviation array.

<code>fd2td</code>	<i>Transform frequency-domain data to the time-domain.</i>
--------------------	--

Description

Transform frequency-domain data to the time-domain.

Usage

```
fd2td(mrs_data)
```

Arguments

<code>mrs_data</code>	MRS data in frequency-domain representation.
-----------------------	--

Value

MRS data in time-domain representation.

fd_conv_filt	<i>Frequency-domain convolution based filter.</i>
--------------	---

Description

Frequency-domain convolution based filter.

Usage

```
fd_conv_filt(mrs_data, K = 25, ext = 1)
```

Arguments

mrs_data	MRS data to be filtered.
K	window width in data points.
ext	point separation for linear extrapolation.

fd_gauss_smo	<i>Apply a Gaussian smoother in the spectral domain.</i>
--------------	--

Description

Apply a Gaussian smoother in the spectral domain.

Usage

```
fd_gauss_smo(mrs_data, smo_ppm_sd)
```

Arguments

mrs_data	mrs_data object.
smo_ppm_sd	Gaussian smoother sd in ppm units.

Value

spectrally smoothed data.

find_bids_mrs	<i>Search for MRS data files in a BIDS filesystem structure.</i>
---------------	--

Description

Search for MRS data files in a BIDS filesystem structure.

Usage

```
find_bids_mrs(path, output_full_path = FALSE)
```

Arguments

path	path to the directory containing the BIDS structure.
output_full_path	output the full normalised data paths.

Value

data frame containing full paths and information on each MRS file.

find_mrs_files	<i>Find valid MRS data files recursively from a directory path.</i>
----------------	---

Description

Find valid MRS data files recursively from a directory path.

Usage

```
find_mrs_files(dir)
```

Arguments

dir	a directory path.
-----	-------------------

Value

a vector of valid MRS data files.

fit_amps	<i>Extract the fit amplitudes from an object of class fit_result.</i>
----------	---

Description

Extract the fit amplitudes from an object of class fit_result.

Usage

```
fit_amps(  
  x,  
  inc_index = FALSE,  
  sort_names = FALSE,  
  append_common_1h_comb = TRUE  
)
```

Arguments

x	fit_result object.
inc_index	include columns for the voxel index.
sort_names	sort the basis set names alphabetically.
append_common_1h_comb	append commonly used 1H metabolite combinations eg tNAA = NAA + NAAG.

Value

a dataframe of amplitudes.

fit_diags	<i>Calculate diagnostic information for object of class fit_result.</i>
-----------	---

Description

Calculate diagnostic information for object of class fit_result.

Usage

```
fit_diags(x, amps = NULL)
```

Arguments

x	fit_result object.
amps	known metabolite amplitudes.

Value

a dataframe of diagnostic information.

fit_mrs

Perform a fit based analysis of MRS data.

Description

Note that TARQUIN and LCModel require these packages to be installed, and the functions `set_tqn_cmd` and `set_lcm_cmd` (respectively) need to be used to specify the location of these software packages.

Usage

```
fit_mrs(
  metab,
  basis = NULL,
  method = "ABFIT",
  w_ref = NULL,
  opts = NULL,
  parallel = FALSE,
  cl = NULL,
  time = TRUE,
  progress = "text",
  extra = NULL
)
```

Arguments

metab	metabolite data.
basis	basis class object or character vector to basis file in LCModel .basis format.
method	'ABFIT' (default), 'VARPRO', 'VARPRO_3P', 'TARQUIN' or 'LCMODEL'.
w_ref	water reference data for concentration scaling (optional).
opts	options to pass to the analysis method.
parallel	perform analyses in parallel (TRUE or FALSE).
cl	a parallel socket cluster required to run analyses in parallel. Eg, <code>cl <- parallel::makeCluster(4)</code> .
time	measure the time taken for the analysis to complete (TRUE or FALSE).
progress	option is passed to <code>plyr::alply</code> function to display a progress bar during fitting. Default value is "text", set to "none" to disable.
extra	an optional data frame to provide additional variables for use in subsequent analysis steps, eg id or grouping variables.

Details

Fitting approaches described in the following references: ABfit Wilson, M. Adaptive baseline fitting for 1H MR spectroscopy analysis. *Magn Reson Med* 2012;85:13-29.

VARPRO van der Veen JW, de Beer R, Luyten PR, van Ormondt D. Accurate quantification of in vivo ³¹P NMR signals using the variable projection method and prior knowledge. Magn Reson Med 1988;6:92-98.

TARQUIN Wilson, M., Reynolds, G., Kauppinen, R. A., Arvanitis, T. N. & Peet, A. C. A constrained least-squares approach to the automated quantitation of in vivo ¹H magnetic resonance spectroscopy data. Magn Reson Med 2011;65:1-12.

LCModel Provencher SW. Estimation of metabolite concentrations from localized in vivo proton NMR spectra. Magn Reson Med 1993;30:672-679.

Value

MRS analysis object.

Examples

```
fname <- system.file("extdata", "philips_spar_sdat_WS.SDAT", package =
"spant")
svs <- read_mrs(fname)
## Not run:
basis <- sim_basis_1h_brain_press(svs)
fit_result <- fit_mrs(svs, basis)

## End(Not run)
```

fit_res2csv

Write fit results table to a csv file.

Description

Write fit results table to a csv file.

Usage

```
fit_res2csv(fit_res, fname, unscaled = FALSE)
```

Arguments

fit_res	fit result object.
fname	filename of csv file.
unscaled	output the unscaled result table (default = FALSE).

fit_svs

Standard SVS 1H brain analysis pipeline.

Description

Note this function is still under development and liable to changes.

Usage

```
fit_svs(
  input,
  w_ref = NULL,
  output_dir = NULL,
  mri = NULL,
  mri_seg = NULL,
  external_basis = NULL,
  append_external_basis = FALSE,
  p_vols = NULL,
  format = NULL,
  pul_seq = NULL,
  TE = NULL,
  TR = NULL,
  TE1 = NULL,
  TE2 = NULL,
  TE3 = NULL,
  TM = NULL,
  append_basis = NULL,
  remove_basis = NULL,
  pre_align = TRUE,
  dfp_corr = TRUE,
  dfp_corr_ref_subset = NULL,
  output_ratio = NULL,
  ecc = FALSE,
  hsvd_width = NULL,
  decimate = FALSE,
  trunc_fid_pts = NULL,
  fit_method = NULL,
  fit_opts = NULL,
  fit_subset = NULL,
  w_ref_subset = NULL,
  legacy_ws = FALSE,
  w_att = 0.7,
  w_conc = 35880,
  use_basis_cache = "auto",
  summary_measures = NULL,
  dyn_av_block_size = NULL,
  dyn_av_scheme = NULL,
```

```

    dyn_av_scheme_file = NULL,
    lcm_bin_path = NULL,
    plot_ppm_xlim = NULL,
    extra_output = FALSE,
    verbose = FALSE
)

```

Arguments

input	path or mrs_data object containing MRS data.
w_ref	path or mrs_data object containing MRS water reference data.
output_dir	directory path to output fitting results.
mri	filepath or nifti object containing anatomical MRI data.
mri_seg	filepath or nifti object containing segmented MRI data.
external_basis	precompiled basis set object to use for analysis.
append_external_basis	append the external basis with the internally generated one. Useful for adding experimentally acquired baseline signals to internally simulated basis sets. Defaults to FALSE - meaning only signals from the external basis will be used in analysis.
p_vols	a numeric vector of partial volumes expressed as percentages. Defaults to 100% white matter. A voxel containing 100% gray matter tissue would use : p_vols = c(WM = 0, GM = 100, CSF = 0).
format	Override automatic data format detection. See format argument in read_mrs() for permitted values.
pul_seq	Pulse sequence to use for basis simulation. Can be one of the following values : "press", "press_ideal", "press_shaped", "steam" or "slaser". If "press" then "press_ideal" will be assumed unless the magnetic field is stronger than 2.8 Tesla, "press_shaped" will be assumed for 2.9 Tesla and above.
TE	metabolite mrs data echo time in seconds. If not supplied this will be guessed from the metab data file.
TR	metabolite mrs data repetition time in seconds. If not supplied this will be guessed from the metab data file.
TE1	PRESS or sLASER sequence timing parameter in seconds.
TE2	PRESS or sLASER sequence timing parameter in seconds.
TE3	sLASER sequence timing parameter in seconds.
TM	STEAM mixing time parameter in seconds.
append_basis	names of extra signals to add to the default basis. Eg append_basis = c("peth", "cit"). Cannot be used with precompiled basis sets.
remove_basis	grep expression to match names of signals to remove from the basis. For example: use "*" to remove all signals, "^mml^lip" to remove all macromolecular and lipid signals, "^lac" to remove lactate. This operation is performed before signals are added with append_basis. Cannot be used with precompiled basis sets.

pre_align	perform simple frequency alignment to known reference peaks.
dfp_corr	perform dynamic frequency and phase correction using the RATS method.
dfp_corr_ref_subset	specify a subset of dynamics to use as reference scans for dynamic frequency and phase correction. For example, 1:16 would use the mean of the first 16 dynamic scans as a reference spectrum.
output_ratio	optional string to specify a metabolite ratio to output. Defaults to "tCr". Multiple metabolites may be specified for multiple outputs. Set to NA to omit.
ecc	option to perform water reference based eddy current correction, defaults to FALSE.
hsvd_width	set the width of the HSDV filter in Hz. Note the applied width is between -width and +width Hz, with 0 Hz being defined at the centre of the spectral width. Default is disabled (set to NULL), 30 Hz is a reasonable value.
decimate	option on decimate the data by a factor of 2 before analysis. Defaults to FALSE.
trunc_fid_pts	number of points to truncate the input data by in the time-domain. E.g. setting to 1024 will ensure data with more time-domain points will be truncated to a length of 1024. Defaults to NULL, where truncation is not performed.
fit_method	can be "ABFIT-REG" or "LCMODEL". Defaults to "ABFIT-REG".
fit_opts	options to pass to the fitting method.
fit_subset	specify a subset of dynamics to analyse, for example 1:16 would only fit the first 16 dynamic scans.
w_ref_subset	specify a subset of dynamics to use as water reference following rats alignment and averaging. For example c(1, 2) would only use the average of the first two dynamic water reference scans. Default value of NULL uses all available water reference scans.
legacy_ws	perform and output legacy water scaling compatible with default LCModel and TARQUIN behaviour. See w_att and w_conc arguments to change the default assumptions. Default value is FALSE.
w_att	water attenuation factor (default = 0.7) for legacy water scaling. Assumes water T2 of 80ms and a TE = 30 ms. $\exp(-30\text{ms} / 80\text{ms}) \sim 0.7$.
w_conc	assumed water concentration (default = 35880) for legacy water scaling. Default value corresponds to typical white matter. Set to 43300 for gray matter, and 55556 for phantom measurements.
use_basis_cache	Pre-cache basis sets to reduce analysis speed. Can be one of the following : "auto", "all" or "none". The default value of "auto" will only use the cache for 3T PRESS - which generally requires more detailed simulation due to high CSD.
summary_measures	output an additional table with a subset of metabolite levels, eg c("tNAA", "tNAA/tCr", "tNAA/tCho", "Lac/tNAA").
dyn_av_block_size	perform temporal averaging with the specified block size. Defaults to NULL, eg average across all dynamic scans.

dyn_av_scheme a numeric vector of sequential integers (starting at 1), with the same length as the number of dynamic scans in the metabolite data. For example: c(1, 1, 2, 1, 1, 3, 1, 1).
 dyn_av_scheme_file a file path containing a single column of sequential integers (starting at 1) with the same length as the number of dynamic scans in the metabolite data. File may be formatted as .xlsx, .xls, text or csv format.
 lcm_bin_path set the path to LCModel binary.
 plot_ppm_xlim plotting ppm axis limits in the html results. results.
 extra_output write extra output files for generating custom plots. Defaults to FALSE.
 verbose output potentially useful information.

Examples

```

metab <- system.file("extdata", "philips_spar_sdat_WS.SDAT",
  package = "spant")
w_ref <- system.file("extdata", "philips_spar_sdat_W.SDAT",
  package = "spant")
out_dir <- file.path("~", "fit_svs_result")
## Not run:
fit_result <- fit_svs(metab, w_ref, out_dir)

## End(Not run)

```

fit_svs_edited	<i>Edited SVS 1H brain analysis pipeline.</i>
----------------	---

Description

Note this function is still under development and liable to changes.

Usage

```

fit_svs_edited(
  input,
  w_ref = NULL,
  output_dir = NULL,
  mri = NULL,
  mri_seg = NULL,
  external_basis = NULL,
  p_vols = NULL,
  format = NULL,
  editing_scheme = NULL,
  invert_edit_on = NULL,
  invert_edit_off = NULL,
  pul_seq = NULL,

```

```

TE = NULL,
TR = NULL,
TE1 = NULL,
TE2 = NULL,
TE3 = NULL,
TM = NULL,
append_basis_ed_off = NULL,
remove_basis_ed_off = NULL,
pre_align = TRUE,
dfp_corr = TRUE,
output_ratio = NULL,
ecc = FALSE,
hsvd_width = NULL,
decimate = FALSE,
trunc_fid_pts = NULL,
fit_opts_edited = NULL,
fit_opts_ed_off = NULL,
fit_subset = NULL,
legacy_ws = FALSE,
w_att = 0.7,
w_conc = 35880,
use_basis_cache = "auto",
summary_measures = NULL,
dyn_av_block_size = NULL,
dyn_av_scheme = NULL,
dyn_av_scheme_file = NULL,
plot_ppm_xlim = NULL,
extra_output = FALSE,
verbose = FALSE
)

```

Arguments

input	path or mrs_data object containing MRS data.
w_ref	path or mrs_data object containing MRS water reference data.
output_dir	directory path to output fitting results.
mri	filepath or nifti object containing anatomical MRI data.
mri_seg	filepath or nifti object containing segmented MRI data.
external_basis	precompiled basis set object to use for analysis.
p_vols	a numeric vector of partial volumes expressed as percentages. Defaults to 100% white matter. A voxel containing 100% gray matter tissue would use : p_vols = c(WM = 0, GM = 100, CSF = 0).
format	Override automatic data format detection. See format argument in read_mrs() for permitted values.
editing_scheme	describes the dynamic data ordering. Can be one of: 'on-off-blocks', 'on-off-interleaved', 'off-on-blocks' or 'off-on-interleaved'.

invert_edit_on	set to TRUE to invert the edit-on sub-spectra.
invert_edit_off	set to TRUE to invert the edit-off sub-spectra.
pul_seq	Pulse sequence to use for basis simulation. Can be one of the following values : "press", "press_ideal", "press_shaped", "steam" or "slaser". If "press" then "press_ideal" will be assumed unless the magnetic field is stronger than 2.8 Tesla, "press_shaped" will be assumed for 2.9 Tesla and above.
TE	metabolite mrs data echo time in seconds. If not supplied this will be guessed from the metab data file.
TR	metabolite mrs data repetition time in seconds. If not supplied this will be guessed from the metab data file.
TE1	PRESS or sLASER sequence timing parameter in seconds.
TE2	PRESS or sLASER sequence timing parameter in seconds.
TE3	sLASER sequence timing parameter in seconds.
TM	STEAM mixing time parameter in seconds.
append_basis_ed_off	names of extra signals to add to the default basis. Eg append_basis_ed_off = c("peth", "cit"). Cannot be used with precompiled basis sets.
remove_basis_ed_off	grep expression to match names of signals to remove from the basis. For example: use "*" to remove all signals, "^mml^lip" to remove all macromolecular and lipid signals, "^lac" to remove lactate. This operation is performed before signals are added with append_basis_ed_off. Cannot be used with precompiled basis sets.
pre_align	perform simple frequency alignment to known reference peaks.
dfp_corr	perform dynamic frequency and phase correction using the RATS method.
output_ratio	optional string to specify a metabolite ratio to output. Defaults to "tCr". Multiple metabolites may be specified for multiple outputs. Set to NA to omit.
ecc	option to perform water reference based eddy current correction, defaults to FALSE.
hsvd_width	set the width of the HSVD filter in Hz. Note the applied width is between -width and +width Hz, with 0 Hz being defined at the centre of the spectral width. Default is disabled (set to NULL), 30 Hz is a reasonable value.
decimate	option to decimate the data by a factor of 2 before analysis. Defaults to FALSE.
trunc_fid_pts	number of points to truncate the input data by in the time-domain. E.g. setting to 1024 will ensure data with more time-domain points will be truncated to a length of 1024. Defaults to NULL, where truncation is not performed.
fit_opts_edited	options to pass to the fitting method for the edited spectrum.
fit_opts_ed_off	options to pass to the fitting method for the edit-off spectrum.
fit_subset	specify a subset of dynamics to analyse, for example 1:16 would only fit the first 16 dynamic scans.

legacy_ws	perform and output legacy water scaling compatible with default LCModel and TARQUIN behaviour. See w_att and w_conc arguments to change the default assumptions. Default value is FALSE.
w_att	water attenuation factor (default = 0.7) for legacy water scaling. Assumes water T2 of 80ms and a TE = 30 ms. $\exp(-30\text{ms} / 80\text{ms}) \sim 0.7$.
w_conc	assumed water concentration (default = 35880) for legacy water scaling. Default value corresponds to typical white matter. Set to 43300 for gray matter, and 55556 for phantom measurements.
use_basis_cache	Pre-cache basis sets to reduce analysis speed. Can be one of the following : "auto", "all" or "none". The default value of "auto" will only use the cache for 3T PRESS - which generally requires more detailed simulation due to high CSD.
summary_measures	output an additional table with a subset of metabolite levels, eg c("tNAA", "tNAA/tCr", "tNAA/tCho", "Lac/tNAA").
dyn_av_block_size	perform temporal averaging with the specified block size. Defaults to NULL, eg average across all dynamic scans.
dyn_av_scheme	a numeric vector of sequential integers (starting at 1), with the same length as the number of dynamic scans in the metabolite data. For example: c(1, 1, 2, 1, 1, 3, 1, 1).
dyn_av_scheme_file	a file path containing a single column of sequential integers (starting at 1) with the same length as the number of dynamic scans in the metabolite data. File may be formatted as .xlsx, .xls, text or csv format.
plot_ppm_xlim	plotting ppm axis limits in the html results. results.
extra_output	write extra output files for generating custom plots. Defaults to FALSE.
verbose	output potentially useful information.

Examples

```

metab <- system.file("extdata", "philips_spar_sdat_WS.SDAT",
                    package = "spant")
w_ref <- system.file("extdata", "philips_spar_sdat_W.SDAT",
                    package = "spant")
out_dir <- file.path("~", "fit_svs_result")
## Not run:
fit_result <- fit_svs(metab, w_ref, out_dir)

## End(Not run)

```

fit_svs_group_results	<i>Combine fitting results for group analysis.</i>
-----------------------	--

Description

Combine fitting results for group analysis.

Usage

```
fit_svs_group_results(search_path, output_dir = "fit_svs_group_results")
```

Arguments

search_path	path to start recursive search for fitting results.
output_dir	directory path to store group results.

fit_svs_gui	<i>GUI interface for the standard SVS 1H brain analysis pipeline, this is a work in progress, and not ready for serious use.</i>
-------------	--

Description

GUI interface for the standard SVS 1H brain analysis pipeline, this is a work in progress, and not ready for serious use.

Usage

```
fit_svs_gui()
```

fit_t1_ti_array	<i>Fit a T1 recovery curve, from multiple TIs, to a set of amplitudes.</i>
-----------------	--

Description

Fit a T1 recovery curve, from multiple TIs, to a set of amplitudes.

Usage

```
fit_t1_ti_array(
  ti_vec,
  amp_vec,
  lower = 0,
  upper = 10,
  output_fit_res = 0.01,
  ret_full = TRUE
)
```

Arguments

ti_vec	vector of TI values in seconds.
amp_vec	vector of amplitudes.
lower	minimum allowable T1 value.
upper	maximum allowable T1 value.
output_fit_res	temporal resolution (seconds) of the ideal output relaxation curve.
ret_full	return full fitting information including ideal relaxation curve.

Value

a list containing relaxation parameters and an ideal curve for fit evaluation.

fit_t1_tr_array	<i>Fit a T1 recovery curve, from multiple TRs, to a set of amplitudes.</i>
-----------------	--

Description

Fit a T1 recovery curve, from multiple TRs, to a set of amplitudes.

Usage

```
fit_t1_tr_array(
  tr_vec,
  amp_vec,
  lower = 0,
  upper = 10,
  output_fit_res = 0.01,
  ret_full = TRUE
)
```

Arguments

tr_vec	vector of TR values in seconds.
amp_vec	vector of amplitudes.
lower	minimum allowable T1 value.
upper	maximum allowable T1 value.
output_fit_res	temporal resolution (seconds) of the ideal output relaxation curve.
ret_full	return full fitting information including ideal relaxation curve.

Value

a list containing relaxation parameters and an ideal curve for fit evaluation.

fit_t2_te_array	<i>Fit a T2 relaxation curve, from multiple TEs, to a set of amplitudes.</i>
-----------------	--

Description

Fit a T2 relaxation curve, from multiple TEs, to a set of amplitudes.

Usage

```
fit_t2_te_array(
    te_vec,
    amp_vec,
    lower = 0,
    upper = 10,
    output_fit_res = 0.01,
    ret_full = TRUE
)
```

Arguments

te_vec	vector of TE values in seconds.
amp_vec	vector of amplitudes.
lower	minimum allowable T2 value.
upper	maximum allowable T2 value.
output_fit_res	temporal resolution (seconds) of the ideal output relaxation curve.
ret_full	return full fitting information including ideal relaxation curve.

Value

a list containing relaxation parameters and an ideal curve for fit evaluation.

fp_phase	<i>Return the phase of the first data point in the time-domain.</i>
----------	---

Description

Return the phase of the first data point in the time-domain.

Usage

```
fp_phase(mrs_data)
```

Arguments

mrs_data	MRS data.
----------	-----------

Value

phase values in degrees.

fp_phase_correct	<i>Perform a zeroth order phase correction based on the phase of the first data point in the time-domain.</i>
------------------	---

Description

Perform a zeroth order phase correction based on the phase of the first data point in the time-domain.

Usage

```
fp_phase_correct(mrs_data, ret_phase = FALSE)
```

Arguments

mrs_data	MRS data to be corrected.
ret_phase	return phase values (logical).

Value

corrected data or a list with corrected data and optional phase values.

fp_scale	<i>Scale the first time-domain data point in an mrs_data object.</i>
----------	--

Description

Scale the first time-domain data point in an mrs_data object.

Usage

```
fp_scale(mrs_data, scale = 0.5)
```

Arguments

mrs_data	MRS data.
scale	scaling value, defaults to 0.5.

Value

scaled mrs_data object.

fs	<i>Return the sampling frequency in Hz of an MRS dataset.</i>
----	---

Description

Return the sampling frequency in Hz of an MRS dataset.

Usage

```
fs(mrs_data)
```

Arguments

mrs_data	MRS data.
----------	-----------

Value

sampling frequency in Hz.

ft_dyns	<i>Apply the Fourier transform over the dynamic dimension.</i>
---------	--

Description

Apply the Fourier transform over the dynamic dimension.

Usage

```
ft_dyns(mrs_data, ft_shift = FALSE, ret_mod = FALSE, fd = TRUE)
```

Arguments

mrs_data	MRS data where the dynamic dimension is in the time-domain.
ft_shift	apply FT shift to the output, default is FALSE.
ret_mod	return the modulus out the transform, default is FALSE.
fd	transform the chemical shift axis to the frequency domain first, default is TRUE.

Value

transformed MRS data.

`ft_shift`*Perform a fft and fftshift on a vector.*

Description

Perform a fft and fftshift on a vector.

Usage

```
ft_shift(vec_in)
```

Arguments

`vec_in` vector input.

Value

output vector.

`ft_shift_mat`*Perform a fft and fftshift on a matrix with each column replaced by its shifted fft.*

Description

Perform a fft and fftshift on a matrix with each column replaced by its shifted fft.

Usage

```
ft_shift_mat(mat_in)
```

Arguments

`mat_in` matrix input.

Value

output matrix.

gausswin_2d	<i>Create a two dimensional Gaussian window function stored as a matrix.</i>
-------------	--

Description

Create a two dimensional Gaussian window function stored as a matrix.

Usage

```
gausswin_2d(xN, yN, x0, y0, xw, yw)
```

Arguments

xN	number of pixels in the x dimension.
yN	number of pixels in the y dimension.
x0	centre of window function in the x direction in units of pixels. Note, only integer values are applied.
y0	centre of window function in the y direction in units of pixels. Note, only integer values are applied.
xw	the reciprocal of the standard deviation of the Gaussian window in x direction.
yw	the reciprocal of the standard deviation of the Gaussian window in y direction.

Value

matrix with dimensions fov_yN x fov_xN.

gen_baseline_reg	<i>Generate baseline regressor.</i>
------------------	-------------------------------------

Description

Generate baseline regressor.

Usage

```
gen_baseline_reg(mrs_data = NULL, tr = NULL, Ndyns = NULL, Ntrans = NULL)
```

Arguments

mrs_data	mrs_data object for timing information.
tr	repetition time.
Ndyns	number of dynamic scans stored, potentially less than Ntrans if block averaging has been performed.
Ntrans	number of dynamic scans acquired.

Value

a single baseline regressor with value of 1.

gen_bold_reg	<i>Generate BOLD regressors.</i>
--------------	----------------------------------

Description

Generate BOLD regressors.

Usage

```
gen_bold_reg(  
  onset,  
  duration = NULL,  
  trial_type = NULL,  
  mrs_data = NULL,  
  tr = NULL,  
  Ndyns = NULL,  
  Ntrans = NULL,  
  match_tr = TRUE,  
  dt = 0.1,  
  normalise = FALSE  
)
```

Arguments

onset	stimulus onset in seconds.
duration	stimulus duration in seconds.
trial_type	string label for the stimulus.
mrs_data	mrs_data object for timing information.
tr	repetition time.
Ndyns	number of dynamic scans stored, potentially less than Ntrans if block averaging has been performed.
Ntrans	number of dynamic scans acquired.
match_tr	match the output to the input mrs_data.
dt	timing resolution for internal calculations.
normalise	normalise the response function to have a maximum value of one.

Value

BOLD regressor data frame.

gen_conv_reg	<i>Generate regressors by convolving a specified response function with a stimulus.</i>
--------------	---

Description

Generate regressors by convolving a specified response function with a stimulus.

Usage

```
gen_conv_reg(
  onset,
  duration = NULL,
  trial_type = NULL,
  mrs_data = NULL,
  tr = NULL,
  Ndyns = NULL,
  Ntrans = NULL,
  resp_fn,
  match_tr = TRUE,
  normalise = FALSE
)
```

Arguments

onset	stimulus onset in seconds.
duration	stimulus duration in seconds.
trial_type	string label for the stimulus.
mrs_data	mrs_data object for timing information.
tr	repetition time.
Ndyns	number of dynamic scans stored, potentially less than Ntrans if block averaging has been performed.
Ntrans	number of dynamic scans acquired.
resp_fn	a data frame specifying the response function to be convolved.
match_tr	match the output to the input mrs_data.
normalise	normalise the response function to have a maximum value of one.

Value

BOLD regressor data frame.

gen_F	<i>Generate the F product operator.</i>
-------	---

Description

Generate the F product operator.

Usage

```
gen_F(sys, op, detect = NULL)
```

Arguments

sys	spin system object.
op	operator, one of "x", "y", "z", "p", "m".
detect	detection nuclei.

Value

F product operator matrix.

gen_F_xy	<i>Generate the Fxy product operator with a specified phase.</i>
----------	--

Description

Generate the Fxy product operator with a specified phase.

Usage

```
gen_F_xy(sys, phase, detect = NULL)
```

Arguments

sys	spin system object.
phase	phase angle in degrees.
detect	detection nuclei.

Value

product operator matrix.

gen_group_reg	<i>Expand a regressor matrix for a group analysis.</i>
---------------	--

Description

Expand a regressor matrix for a group analysis.

Usage

```
gen_group_reg(regressor_df, n)
```

Arguments

regressor_df	input regressor data frame.
n	number of datasets n the group.

gen_I	<i>Generate the I product operator for a single spin.</i>
-------	---

Description

Generate the I product operator for a single spin.

Usage

```
gen_I(n, spin_num, op)
```

Arguments

n	spin index number for the required operator.
spin_num	vector of spin numbers in the system.
op	operator, one of "x", "y", "z", "p", "m".

Value

I product operator matrix.

gen_impulse_reg	<i>Generate impulse regressors.</i>
-----------------	-------------------------------------

Description

Generate impulse regressors.

Usage

```
gen_impulse_reg(
  onset,
  trial_type = NULL,
  mrs_data = NULL,
  tr = NULL,
  Ndyns = NULL,
  Ntrans = NULL
)
```

Arguments

onset	stimulus onset in seconds.
trial_type	string label for the stimulus.
mrs_data	mrs_data object for timing information.
tr	repetition time.
Ndyns	number of dynamic scans stored, potentially less than Ntrans if block averaging has been performed.
Ntrans	number of dynamic scans acquired.

Value

impulse regressors data frame.

gen_numeric_reg	<i>Generate a regressor from a numeric vector.</i>
-----------------	--

Description

Generate a regressor from a numeric vector.

Usage

```
gen_numeric_reg(
  in_vec,
  name,
  mrs_data = NULL,
  tr = NULL,
  Ndyns = NULL,
  Ntrans = NULL
)
```

Arguments

in_vec	a numeric input vector the same length as the number of stored dynamic scans.
name	a character vector representing the regressor name.
mrs_data	mrs_data object for timing information.
tr	repetition time.
Ndyns	number of dynamic scans stored, potentially less than Ntrans if block averaging has been performed.
Ntrans	number of dynamic scans acquired.

Value

a single baseline regressor with value of 1.

gen_poly_reg	<i>Generate polynomial regressors.</i>
--------------	--

Description

Generate polynomial regressors.

Usage

```
gen_poly_reg(degree, mrs_data = NULL, tr = NULL, Ndyns = NULL, Ntrans = NULL)
```

Arguments

degree	the degree of the polynomial.
mrs_data	mrs_data object for timing information.
tr	repetition time.
Ndyns	number of dynamic scans stored, potentially less than Ntrans if block averaging has been performed.
Ntrans	number of dynamic scans acquired.

Value

polynomial regressors.

gen_trap_reg	<i>Generate trapezoidal regressors.</i>
--------------	---

Description

Generate trapezoidal regressors.

Usage

```
gen_trap_reg(
    onset,
    duration,
    trial_type = NULL,
    mrs_data = NULL,
    tr = NULL,
    Ndyns = NULL,
    Ntrans = NULL,
    rise_t = 0,
    fall_t = 0,
    exp_fall = FALSE,
    exp_fall_power = 1,
    smo_sigma = NULL,
    match_tr = TRUE,
    dt = 0.01,
    normalise = FALSE
)
```

Arguments

onset	stimulus onset in seconds.
duration	stimulus duration in seconds.
trial_type	string label for the stimulus.
mrs_data	mrs_data object for timing information.
tr	repetition time.
Ndyns	number of dynamic scans stored, potentially less than Ntrans if block averaging has been performed.
Ntrans	number of dynamic scans acquired.
rise_t	time to reach a plateau from baseline in seconds.
fall_t	time to fall from plateau level back to baseline in seconds.
exp_fall	model an exponential fall instead of linear.
exp_fall_power	exponential fall power.
smo_sigma	standard deviation of Gaussian smoothing kernel in seconds. Set to NULL to disable (default behavior).

match_tr	match the output to the input mrs_data.
dt	timing resolution for internal calculations.
normalise	normalise the response function to have a maximum value of one.

Value

trapezoidal regressor data frame.

get_1h_braino_basis_names

Return a character vector of molecules included in the GE BRAINO phantom.

Description

Return a character vector of molecules included in the GE BRAINO phantom.

Usage

```
get_1h_braino_basis_names()
```

Value

a character vector of molecule names.

get_1h_brain_basis_names

Return a character vector of common 1H molecules found in healthy human brain.

Description

Note, this is a basic set and it may be appropriate to also include Asc, Gly and PEth for high quality MRS data.

Usage

```
get_1h_brain_basis_names(add = NULL, remove = NULL, inc_lip_mm = TRUE)
```

Arguments

add	optional character vector of additional molecular names. Eg c("asc", "gly", "peth").
remove	optional character vector of molecular names to remove from the set. Eg c("m_cr_ch2").
inc_lip_mm	include Lipid and MM basis signals.

Value

a character vector of molecule names.

get_1h_brain_basis_paras

Return a list of mol_parameter objects suitable for 1H brain MRS analyses.

Description

Return a list of mol_parameter objects suitable for 1H brain MRS analyses.

Usage

```
get_1h_brain_basis_paras(ft, metab_lw = NULL, lcm_compat = FALSE)
```

Arguments

ft	transmitter frequency in Hz.
metab_lw	linewidth of metabolite signals (Hz).
lcm_compat	when TRUE, lipid, MM and -CrCH molecules will be excluded from the output.

Value

list of mol_parameter objects.

get_1h_brain_basis_paras_v1

Return a list of mol_parameter objects suitable for 1H brain MRS analyses.

Description

Return a list of mol_parameter objects suitable for 1H brain MRS analyses.

Usage

```
get_1h_brain_basis_paras_v1(ft, metab_lw = NULL, lcm_compat = FALSE)
```

Arguments

ft	transmitter frequency in Hz.
metab_lw	linewidth of metabolite signals (Hz).
lcm_compat	when TRUE, lipid, MM and -CrCH molecules will be excluded from the output.

Value

list of mol_parameter objects.

get_1h_brain_basis_paras_v2

Return a list of mol_parameter objects suitable for 1H brain MRS analyses.

Description

Return a list of mol_parameter objects suitable for 1H brain MRS analyses.

Usage

```
get_1h_brain_basis_paras_v2(ft, metab_lw = NULL, lcm_compat = FALSE)
```

Arguments

ft	transmitter frequency in Hz.
metab_lw	linewidth of metabolite signals (Hz).
lcm_compat	when TRUE, lipid, MM and -CrCH molecules will be excluded from the output.

Value

list of mol_parameter objects.

get_1h_brain_basis_paras_v3

Return a list of mol_parameter objects suitable for 1H brain MRS analyses.

Description

Return a list of mol_parameter objects suitable for 1H brain MRS analyses.

Usage

```
get_1h_brain_basis_paras_v3(ft, metab_lw = NULL, lcm_compat = FALSE)
```

Arguments

ft	transmitter frequency in Hz.
metab_lw	linewidth of metabolite signals (Hz).
lcm_compat	when TRUE, lipid, MM and -CrCH molecules will be excluded from the output.

Value

list of mol_parameter objects.

get_1h_spectre_basis_names

Return a character vector of molecules included in the Gold Star Phantoms SPECTRE phantom.

Description

Return a character vector of molecules included in the Gold Star Phantoms SPECTRE phantom.

Usage

```
get_1h_spectre_basis_names()
```

Value

a character vector of molecule names.

get_2d_psf

Get the point spread function (PSF) for a 2D phase encoded MRSI scan.

Description

Get the point spread function (PSF) for a 2D phase encoded MRSI scan.

Usage

```
get_2d_psf(
  FOV = 160,
  mat_size = 16,
  sampling = "circ",
  hamming = FALSE,
  ensure_odd = TRUE
)
```

Arguments

FOV	field of view in mm.
mat_size	acquisition matrix size (not interpolated).
sampling	can be either "circ" for circular or "rect" for rectangular.
hamming	should Hamming k-space weighting be applied (default FALSE).
ensure_odd	add 1mm to the FOV when required to ensure the output pdf has odd dimensions. Required when using get_mrsi2d_seg.

Value

A matrix of the PSF with 1mm resolution.

get_acq_paras	<i>Return acquisition parameters from a MRS data object.</i>
---------------	--

Description

Return acquisition parameters from a MRS data object.

Usage

```
get_acq_paras(mrs_data)
```

Arguments

mrs_data	MRS data.
----------	-----------

Value

list of acquisition parameters.

get_basis_subset	<i>Return a subset of the input basis.</i>
------------------	--

Description

Return a subset of the input basis.

Usage

```
get_basis_subset(basis, names, invert = FALSE)
```

Arguments

basis	input basis.
names	basis set elements to keep in the returned object.
invert	set to true to return all basis elements except those given in the names argument.

Value

a subset of the input basis.

get_dyns	<i>Extract a subset of dynamic scans.</i>
----------	---

Description

Extract a subset of dynamic scans.

Usage

```
get_dyns(mrs_data, subset)
```

Arguments

mrs_data	dynamic MRS data.
subset	vector containing indices to the dynamic scans to be returned.

Value

MRS data containing the subset of requested dynamics.

get_even_dyns	<i>Return even numbered dynamic scans starting from 1 (2,4,6...).</i>
---------------	---

Description

Return even numbered dynamic scans starting from 1 (2,4,6...).

Usage

```
get_even_dyns(mrs_data)
```

Arguments

mrs_data	dynamic MRS data.
----------	-------------------

Value

dynamic MRS data containing even numbered scans.

get_fh_dyns	<i>Return the first half of a dynamic series.</i>
-------------	---

Description

Return the first half of a dynamic series.

Usage

```
get_fh_dyns(mrs_data)
```

Arguments

mrs_data	dynamic MRS data.
----------	-------------------

Value

first half of the dynamic series.

get_fit_map	<i>Get a data array from a fit result.</i>
-------------	--

Description

Get a data array from a fit result.

Usage

```
get_fit_map(fit_res, name)
```

Arguments

fit_res	fit_result object.
name	name of the quantity to plot, eg "tNAA".

get_fp	<i>Return the first time-domain data point.</i>
--------	---

Description

Return the first time-domain data point.

Usage

```
get_fp(mrs_data)
```

Arguments

mrs_data	MRS data.
----------	-----------

Value

first time-domain data point.

get_guassian_pulse	<i>Generate a gaussian pulse shape.</i>
--------------------	---

Description

Generate a gaussian pulse shape.

Usage

```
get_guassian_pulse(angle, n, trunc = 1)
```

Arguments

angle	pulse angle in degrees.
n	number of points to generate.
trunc	percentage truncation factor.

get_head_dyns	<i>Return the first scans of a dynamic series.</i>
---------------	--

Description

Return the first scans of a dynamic series.

Usage

```
get_head_dyns(mrs_data, n = 1)
```

Arguments

mrs_data	dynamic MRS data.
n	the number of dynamic scans to return.

Value

first scans of a dynamic series.

get_hrf	<i>Generate a double gamma model of the HRF as used in SPM.</i>
---------	---

Description

Generate a double gamma model of the HRF as used in SPM.

Usage

```
get_hrf(end_t = 30, res_t = 0.01)
```

Arguments

end_t	last time point to generate in seconds.
res_t	temporal resolution in seconds, defaults to 10ms.

Value

a data.frame of time and HRF vectors.

get_lcm_cmd	<i>Print the command to run the LCModel command-line program.</i>
-------------	---

Description

Print the command to run the LCModel command-line program.

Usage

```
get_lcm_cmd()
```

get_metab	<i>Extract the metabolite component from an mrs_data object.</i>
-----------	--

Description

Extract the metabolite component from an mrs_data object.

Usage

```
get_metab(mrs_data)
```

Arguments

mrs_data	MRS data.
----------	-----------

Value

metabolite component.

get_mol_names	<i>Return a character array of names that may be used with the get_mol_paras function.</i>
---------------	--

Description

Return a character array of names that may be used with the get_mol_paras function.

Usage

```
get_mol_names()
```

Value

a character array of names.

get_mol_paras	<i>Get a mol_parameters object for a named molecule.</i>
---------------	--

Description

Get a mol_parameters object for a named molecule.

Usage

```
get_mol_paras(name, ...)
```

Arguments

name	the name of the molecule.
...	arguments to pass to molecule definition function.

get_mrsi2d_seg	<i>Calculate the partial volume estimates for each voxel in a 2D MRSI dataset.</i>
----------------	--

Description

Localisation is assumed to be perfect in the z direction and determined by the ker input in the x-y direction.

Usage

```
get_mrsi2d_seg(mrs_data, mri_seg, ker)
```

Arguments

mrs_data	2D MRSI data with multiple voxels in the x-y dimension.
mri_seg	MRI data with values corresponding to the segmentation class. Must be 1mm isotropic resolution.
ker	MRSI PSF kernel in the x-y direction compatible with the mmand package, eg: mmand::shapeKernel(c(10, 10), type = "box").

Value

a data frame of partial volume estimates and individual segmentation maps.

get_mrsi_voi	<i>Generate a MRSI VOI from an mrs_data object.</i>
--------------	---

Description

Generate a MRSI VOI from an mrs_data object.

Usage

```
get_mrsi_voi(mrs_data, target_mri = NULL, map = NULL, ker = mmand::boxKernel())
```

Arguments

mrs_data	MRS data.
target_mri	optional image data to match the intended volume space.
map	optional voi intensity map.
ker	kernel to rescale the map data to the target_mri. Default value is mmand::boxKernel(), use mmand::mnKernel() for a smoothed map.

Value

volume data as a nifti object.

get_mrsi_voxel	<i>Generate a MRSI voxel from an mrs_data object.</i>
----------------	---

Description

Generate a MRSI voxel from an mrs_data object.

Usage

```
get_mrsi_voxel(mrs_data, target_mri, x_pos, y_pos, z_pos)
```

Arguments

mrs_data	MRS data.
target_mri	optional image data to match the intended volume space.
x_pos	x voxel coordinate.
y_pos	y voxel coordinate.
z_pos	z voxel coordinate.

Value

volume data as a nifti object.

get_mrsi_voxel_xy_psf *Generate a MRSI voxel PSF from an mrs_data object.*

Description

Generate a MRSI voxel PSF from an mrs_data object.

Usage

```
get_mrsi_voxel_xy_psf(mrs_data, target_mri, x_pos, y_pos, z_pos)
```

Arguments

mrs_data	MRS data.
target_mri	optional image data to match the intended volume space.
x_pos	x voxel coordinate.
y_pos	y voxel coordinate.
z_pos	z voxel coordinate.

Value

volume data as a nifti object.

get_mrs_affine *Generate an affine for nifti generation.*

Description

Generate an affine for nifti generation.

Usage

```
get_mrs_affine(mrs_data, x_pos = 1, y_pos = 1, z_pos = 1)
```

Arguments

mrs_data	input data.
x_pos	x_position coordinate.
y_pos	y_position coordinate.
z_pos	z_position coordinate.

Value

affine matrix.

get_odd_dyns	<i>Return odd numbered dynamic scans starting from 1 (1,3,5...).</i>
--------------	--

Description

Return odd numbered dynamic scans starting from 1 (1,3,5...).

Usage

```
get_odd_dyns(mrs_data)
```

Arguments

mrs_data	dynamic MRS data.
----------	-------------------

Value

dynamic MRS data containing odd numbered scans.

get_ref	<i>Extract the reference component from an mrs_data object.</i>
---------	---

Description

Extract the reference component from an mrs_data object.

Usage

```
get_ref(mrs_data)
```

Arguments

mrs_data	MRS data.
----------	-----------

Value

reference component.

get_seg_ind	<i>Get the indices of data points lying between two values (end > x > start).</i>
-------------	---

Description

Get the indices of data points lying between two values (end > x > start).

Usage

```
get_seg_ind(scale, start, end)
```

Arguments

scale	full list of values.
start	smallest value in the subset.
end	largest value in the subset.

Value

set of indices.

get_sh_dyns	<i>Return the second half of a dynamic series.</i>
-------------	--

Description

Return the second half of a dynamic series.

Usage

```
get_sh_dyns(mrs_data)
```

Arguments

mrs_data	dynamic MRS data.
----------	-------------------

Value

second half of the dynamic series.

<code>get_slice</code>	<i>Return a single slice from a larger MRSI dataset.</i>
------------------------	--

Description

Return a single slice from a larger MRSI dataset.

Usage

```
get_slice(mrs_data, z_pos)
```

Arguments

- | | |
|-----------------------|-------------------------|
| <code>mrs_data</code> | MRSI data. |
| <code>z_pos</code> | the z index to extract. |

Value

MRS data.

<code>get_spin_num</code>	<i>Return the spin number for a given nucleus.</i>
---------------------------	--

Description

Return the spin number for a given nucleus.

Usage

```
get_spin_num(nucleus)
```

Arguments

- | | |
|----------------------|------------------------|
| <code>nucleus</code> | nucleus name, eg "1H". |
|----------------------|------------------------|

Value

spin number.

get_subset	<i>Extract a subset of MRS data.</i>
------------	--------------------------------------

Description

Extract a subset of MRS data.

Usage

```
get_subset(  
  mrs_data,  
  x_set = NULL,  
  y_set = NULL,  
  z_set = NULL,  
  dyn_set = NULL,  
  coil_set = NULL,  
  fd_set = NULL,  
  td_set = NULL  
)
```

Arguments

mrs_data	MRS data object.
x_set	x indices to include in the output (default all).
y_set	y indices to include in the output (default all).
z_set	z indices to include in the output (default all).
dyn_set	dynamic indices to include in the output (default all).
coil_set	coil indices to include in the output (default all).
fd_set	frequency domain data indices to include in the output (default all).
td_set	time-domain indices to include in the output (default all).

Value

selected subset of MRS data.

get_svs_voi	<i>Generate a SVS acquisition volume from an mrs_data object.</i>
-------------	---

Description

Generate a SVS acquisition volume from an mrs_data object.

Usage

```
get_svs_voi(mrs_data, target_mri)
```

Arguments

mrs_data	MRS data.
target_mri	optional image data to match the intended volume space.

Value

volume data as a nifti object.

get_tail_dyns	<i>Return the last scans of a dynamic series.</i>
---------------	---

Description

Return the last scans of a dynamic series.

Usage

```
get_tail_dyns(mrs_data, n = 1)
```

Arguments

mrs_data	dynamic MRS data.
n	the number of dynamic scans to return.

Value

last scans of a dynamic series.

get_td_amp	<i>Return an array of amplitudes derived from fitting the initial points in the time domain and extrapolating back to t=0.</i>
------------	--

Description

Return an array of amplitudes derived from fitting the initial points in the time domain and extrapolating back to t=0.

Usage

```
get_td_amp(mrs_data, nstart = 10, nend = 50, method = "poly")
```

Arguments

mrs_data	MRS data.
nstart	first data point to fit.
nend	last data point to fit.
method	method for measuring the amplitude, one of "poly", "spline" or "exp".

Value

array of amplitudes.

get_tqn_cmd	<i>Print the command to run the TARQUIN command-line program.</i>
-------------	---

Description

Print the command to run the TARQUIN command-line program.

Usage

```
get_tqn_cmd()
```

get_uncoupled_mol	<i>Generate a mol_parameters object for a simple spin system with one resonance.</i>
-------------------	--

Description

Generate a mol_parameters object for a simple spin system with one resonance.

Usage

```
get_uncoupled_mol(
    name,
    chem_shift,
    nucleus,
    scale_factor,
    lw,
    lg,
    full_name = NULL
)
```

Arguments

name	abbreviated name of the molecule.
chem_shift	chemical shift of the resonance (PPM).
nucleus	nucleus (1H, 31P...).
scale_factor	multiplicative scaling factor. Note, this value can be made complex to adjust the phase of the resonance.
lw	linewidth in Hz.
lg	Lorentz-Gauss lineshape parameter (between 0 and 1).
full_name	long name of the molecule (optional).

Value

mol_parameters object.

get_voi_cog	<i>Calculate the centre of gravity for an image containing 0 and 1's.</i>
-------------	---

Description

Calculate the centre of gravity for an image containing 0 and 1's.

Usage

```
get_voi_cog(voi)
```

Arguments

voi nifti object.

Value

triplet of x,y,z coordinates.

get_voi_seg	<i>Return the white matter, gray matter and CSF composition of a volume.</i>
-------------	--

Description

Return the white matter, gray matter and CSF composition of a volume.

Usage

```
get_voi_seg(voi, mri_seg)
```

Arguments

voi volume data as a nifti object.
mri_seg segmented brain volume as a nifti object.

Value

a vector of partial volumes expressed as percentages.

get_voi_seg_psf	<i>Return the white matter, gray matter and CSF composition of a volume.</i>
-----------------	--

Description

Return the white matter, gray matter and CSF composition of a volume.

Usage

```
get_voi_seg_psf(psf, mri_seg)
```

Arguments

psf volume data as a nifti object.
mri_seg segmented brain volume as a nifti object.

Value

a vector of partial volumes expressed as percentages.

get_voxel	<i>Return a single voxel from a larger mrs dataset.</i>
-----------	---

Description

Return a single voxel from a larger mrs dataset.

Usage

```
get_voxel(mrs_data, x_pos = 1, y_pos = 1, z_pos = 1, dyn = 1, coil = 1)
```

Arguments

mrs_data	MRS data.
x_pos	the x index to plot.
y_pos	the y index to plot.
z_pos	the z index to plot.
dyn	the dynamic index to plot.
coil	the coil element number to plot.

Value

MRS data.

glm_spec	<i>Perform a GLM analysis of dynamic MRS data in the spectral domain.</i>
----------	---

Description

Perform a GLM analysis of dynamic MRS data in the spectral domain.

Usage

```
glm_spec(mrs_data, regressor_df, full_output = FALSE)
```

Arguments

mrs_data	single-voxel dynamics MRS data.
regressor_df	a data frame containing temporal regressors to be applied to each spectral data-point.
full_output	append mrs_data and regressor_df to the output list.

Value

list of statistical results.

glm_spec_fmrs_fl	<i>Perform first-level spectral GLM analysis of an fMRS dataset.</i>
------------------	--

Description

Perform first-level spectral GLM analysis of an fMRS dataset.

Usage

```
glm_spec_fmrs_fl(
  regressor_df,
  analysis_dir = "spant_analysis",
  output_dir = "spec_glm",
  exclude_labels = NULL,
  labels = NULL,
  xlim = c(4, 0.2),
  vline = c(1.35, 1.28, 2.35, 2.29),
  lb = 4,
  return_results = FALSE
)
```

Arguments

regressor_df	a data frame containing temporal regressors to be applied to each spectral data-point.
analysis_dir	directory containing preprocessed data generated by the preproc_svs_dataset function.
output_dir	directory to save glm results.
exclude_labels	vector of labels of scans to exclude, eg poor quality data.
labels	labels to describe each data set.
xlim	spectral range to include in the analysis.
vline	vertical lines to add to the plot.
lb	linebroadening to add in Hz before GLM analysis.
return_results	function will return key outputs, defaults to FALSE.

`glm_spec_fmrs_group` *Perform group-level spectral GLM analysis of an fMRS dataset.*

Description

Perform group-level spectral GLM analysis of an fMRS dataset.

Usage

```
glm_spec_fmrs_group(
  regressor_df,
  analysis_dir = "spant_analysis",
  exclude_labels = NULL,
  labels = NULL
)
```

Arguments

<code>regressor_df</code>	a data frame containing temporal regressors to be applied to each spectral data-point.
<code>analysis_dir</code>	directory containing preprocessed data generated by the <code>preproc_svs_dataset</code> function.
<code>exclude_labels</code>	vector of labels of scans to exclude, eg poor quality data.
<code>labels</code>	labels to describe each data set.

`glm_spec_group_linhyp` *Test a group-level spectral GLM linear hypothesis.*

Description

Test a group-level spectral GLM linear hypothesis.

Usage

```
glm_spec_group_linhyp(hmat, analysis_dir = "spant_analysis")
```

Arguments

<code>hmat</code>	linear hypothesis matrix.
<code>analysis_dir</code>	directory containing preprocessed data generated by the <code>preproc_svs_dataset</code> function.

gridplot	<i>Arrange spectral plots in a grid.</i>
----------	--

Description

Arrange spectral plots in a grid.

Usage

```
gridplot(x, ...)
```

Arguments

x	object for plotting.
...	arguments to be passed to methods.

gridplot.mrs_data	<i>Arrange spectral plots in a grid.</i>
-------------------	--

Description

Arrange spectral plots in a grid.

Usage

```
## S3 method for class 'mrs_data'
gridplot(
  x,
  rows = NA,
  cols = NA,
  mar = c(0, 0, 0, 0),
  oma = c(3.5, 1, 1, 1),
  bty = "o",
  restore_def_par = TRUE,
  ...
)
```

Arguments

x	object of class mrs_data.
rows	number of grid rows.
cols	number of grid columns.
mar	option to adjust the plot margins. See ?par.
oma	outer margin area.

bty option to draw a box around the plot. See ?par.
 restore_def_par restore default plotting par values after the plot has been made.
 ... other arguments to pass to the plot method.

grid_shift_xy	<i>Grid shift MRSI data in the x/y dimension.</i>
---------------	---

Description

Grid shift MRSI data in the x/y dimension.

Usage

```
grid_shift_xy(mrs_data, x_shift, y_shift)
```

Arguments

mrs_data MRSI data in the spatial domain.
 x_shift shift to apply in the x-direction in units of voxels.
 y_shift shift to apply in the y-direction in units of voxels.

Value

shifted data.

hsvd	<i>HSVD of an mrs_data object.</i>
------	------------------------------------

Description

HSVD method as described in: Barkhuijsen H, de Beer R, van Ormondt D. Improved algorithm for noniterative and timedomain model fitting to exponentially damped magnetic resonance signals. J Magn Reson 1987;73:553-557.

Usage

```
hsvd(mrs_data, comps = 40, irlba = TRUE, max_damp = 10)
```

Arguments

mrs_data mrs_data object to be decomposed.
 comps number of Lorentzian components to use for modelling.
 irlba option to use irlba SVD (logical).
 max_damp maximum allowable damping factor.

Value

basis matrix and signal table.

hsvd_filt	<i>HSVD based signal filter.</i>
-----------	----------------------------------

Description

HSVD based signal filter described in: Barkhuijsen H, de Beer R, van Ormondt D. Improved algorithm for noniterative and timedomain model fitting to exponentially damped magnetic resonance signals. J Magn Reson 1987;73:553-557.

Usage

```
hsvd_filt(
  mrs_data,
  xlim = c(-30, 30),
  comps = 40,
  irlba = TRUE,
  max_damp = 10,
  scale = "hz",
  return_model = FALSE
)
```

Arguments

mrs_data	MRS data to be filtered.
xlim	frequency range to filter, default units are Hz which can be changed to ppm using the "scale" argument.
comps	number of Lorentzian components to use for modelling.
irlba	option to use irlba SVD (logical).
max_damp	maximum allowable damping factor.
scale	either "hz" or "ppm" to set the frequency units of xlim.
return_model	by default the filtered spectrum is returned. Set return_model to TRUE to return the HSVD model of the data.

Value

filtered data or model depending on the return_model argument.

hsvd_vec	<i>HSVD of a complex vector.</i>
----------	----------------------------------

Description

HSVD method as described in: Barkhuijsen H, de Beer R, van Ormondt D. Improved algorithm for noniterative and timedomain model fitting to exponentially damped magnetic resonance signals. J Magn Reson 1987;73:553-557.

Usage

```
hsvd_vec(y, fs, comps = 40, irlba = TRUE, max_damp = 0)
```

Arguments

y	time domain signal to be filtered as a vector.
fs	sampling frequency of y.
comps	number of Lorentzian components to use for modelling.
irlba	option to use irlba SVD (logical).
max_damp	maximum allowable damping factor. Default value of 0 ensures resultant model is damped.

Value

basis matrix and signal table.

hz	<i>Return the frequency scale of an MRS dataset in Hz.</i>
----	--

Description

Return the frequency scale of an MRS dataset in Hz.

Usage

```
hz(mrs_data, fs = NULL, N = NULL)
```

Arguments

mrs_data	MRS data.
fs	sampling frequency in Hz.
N	number of data points in the spectral dimension.

Value

frequency scale.

ift_shift	<i>Perform an iffshift and ifft on a vector.</i>
-----------	--

Description

Perform an iffshift and ifft on a vector.

Usage

```
ift_shift(vec_in)
```

Arguments

vec_in	vector input.
--------	---------------

Value

output vector.

ift_shift_mat	<i>Perform an ifft and ifftshift on a matrix with each column replaced by its shifted ifft.</i>
---------------	---

Description

Perform an ifft and ifftshift on a matrix with each column replaced by its shifted ifft.

Usage

```
ift_shift_mat(mat_in)
```

Arguments

mat_in	matrix input.
--------	---------------

Value

output matrix.

Im.mrs_data	<i>Apply Im operator to an MRS dataset.</i>
-------------	---

Description

Apply Im operator to an MRS dataset.

Usage

```
## S3 method for class 'mrs_data'
Im(z)
```

Arguments

z MRS data.

Value

MRS data following Im operator.

image.mrs_data	<i>Image plot method for objects of class mrs_data.</i>
----------------	---

Description

Image plot method for objects of class mrs_data.

Usage

```
## S3 method for class 'mrs_data'
image(
  x,
  xlim = NULL,
  mode = "re",
  col = NULL,
  plot_dim = NULL,
  x_pos = NULL,
  y_pos = NULL,
  z_pos = NULL,
  dyn = 1,
  coil = 1,
  restore_def_par = TRUE,
  y_ticks = NULL,
  hline = NULL,
  hline_lty = 2,
  hline_col = "white",
```

```

    vline = NULL,
    vline_lty = 2,
    vline_col = "white",
    legend = FALSE,
    ...
)

```

Arguments

x	object of class mrs_data.
xlim	the range of values to display on the x-axis, eg xlim = c(4,1).
mode	representation of the complex numbers to be plotted, can be one of: "re", "im", "mod" or "arg".
col	Colour map to use, defaults to viridis.
plot_dim	the dimension to display on the y-axis, can be one of: "dyn", "time_sec", "x", "y", "z", "coil" or NULL. If NULL (the default) all spectra are collapsed into the dynamic dimension and displayed.
x_pos	the x index to plot.
y_pos	the y index to plot.
z_pos	the z index to plot.
dyn	the dynamic index to plot.
coil	the coil element number to plot.
restore_def_par	restore default plotting par values after the plot has been made.
y_ticks	a vector of indices specifying where to place additional red tick marks.
hline	add a horizontal line at the specified value.
hline_lty	linetype for the horizontal line.
hline_col	colour for the horizontal line.
vline	add a vertical line at the specified value.
vline_lty	linetype for the vertical line.
vline_col	colour for the vertical line.
legend	add a colour bar to the plot using the imagePlot function from the fields package.
...	other arguments to pass to the plot method.

img2kspace_xy	<i>Transform 2D MRSI data to k-space in the x-y direction.</i>
---------------	--

Description

Transform 2D MRSI data to k-space in the x-y direction.

Usage

img2kspace_xy(mrs_data)

Arguments

mrs_data 2D MRSI data.

Value

k-space data.

Imzap	<i>Complex rounding function taken from complexplus package to reduce the number of spant dependencies.</i>
-------	---

Description

Complex rounding function taken from complexplus package to reduce the number of spant dependencies.

Usage

Imzap(x, tol = 1e-06)

Arguments

x a scalar or vector, real or complex.
tol a tolerance, 10⁻⁶ by default. Prevents possible numerical problems. Can be set to 0 if desired.

install_cli	<i>Install the spant command-line interface scripts to a system path.</i>
-------------	---

Description

This should be run following each new install of spant to ensure consistency. Typical command line usage : `sudo Rscript -e "spant::install_cli()"`

Usage

```
install_cli(path = NULL)
```

Arguments

path	optional path to install the scripts. Defaults to : <code>"/usr/local/bin"</code> .
------	---

interleave_dys	<i>Interleave the first and second half of a dynamic series.</i>
----------------	--

Description

Interleave the first and second half of a dynamic series.

Usage

```
interleave_dys(mrs_data)
```

Arguments

mrs_data	dynamic MRS data.
----------	-------------------

Value

interleaved data.

int_spec	<i>Integrate a spectral region.</i>
----------	-------------------------------------

Description

See spec_op function for a more complete set of spectral operations.

Usage

```
int_spec(mrs_data, xlim = NULL, freq_scale = "ppm", mode = "re")
```

Arguments

mrs_data	MRS data.
xlim	spectral range to be integrated (defaults to full range).
freq_scale	units of xlim, can be : "ppm", "hz" or "points".
mode	spectral mode, can be : "re", "im", "mod" or "cplx".

Value

an array of integral values.

inv_even_dyns	<i>Invert even numbered dynamic scans starting from 1 (2,4,6...).</i>
---------------	---

Description

Invert even numbered dynamic scans starting from 1 (2,4,6...).

Usage

```
inv_even_dyns(mrs_data)
```

Arguments

mrs_data	dynamic MRS data.
----------	-------------------

Value

dynamic MRS data with inverted even numbered scans.

inv_odd_dyns	<i>Invert odd numbered dynamic scans starting from 1 (1,3,5...).</i>
--------------	--

Description

Invert odd numbered dynamic scans starting from 1 (1,3,5...).

Usage

```
inv_odd_dyns(mrs_data)
```

Arguments

mrs_data	dynamic MRS data.
----------	-------------------

Value

dynamic MRS data with inverted odd numbered scans.

is.def	<i>Check if an object is defined, which is the same as being not NULL.</i>
--------	--

Description

Check if an object is defined, which is the same as being not NULL.

Usage

```
is.def(x)
```

Arguments

x	object to test for being NULL.
---	--------------------------------

Value

logical value.

is_fd	<i>Check if the chemical shift dimension of an MRS data object is in the frequency domain.</i>
-------	--

Description

Check if the chemical shift dimension of an MRS data object is in the frequency domain.

Usage

```
is_fd(mrs_data)
```

Arguments

mrs_data	MRS data.
----------	-----------

Value

logical value.

kspace2img_xy	<i>Transform 2D MRSI data from k-space to image space in the x-y direction.</i>
---------------	---

Description

Transform 2D MRSI data from k-space to image space in the x-y direction.

Usage

```
kspace2img_xy(mrs_data)
```

Arguments

mrs_data	2D MRSI data.
----------	---------------

Value

MRSI data in image space.

l2_reg

Perform l2 regularisation artefact suppression.

Description

Perform l2 regularisation artefact suppression using the method proposed by Bilgic et al. JMRI 40(1):181-91 2014.

Usage

```
l2_reg(
  mrs_data,
  thresh = 0.05,
  b = 1e-11,
  A = NA,
  xlim = NA,
  thresh_xlim = NULL,
  A_append = NULL,
  ret_norms = FALSE
)
```

Arguments

mrs_data	input data for artefact suppression.
thresh	threshold parameter to extract lipid signals from mrs_data based on the spectral integration of the thresh_xlim region in magnitude mode.
b	regularisation parameter.
A	set of spectra containing the artefact basis signals. The thresh parameter is ignored when A is specified.
xlim	spectral limits in ppm to restrict the reconstruction range. Defaults to the full spectral width.
thresh_xlim	spectral limits in ppm to integrate for the threshold map.
A_append	additional spectra to append to the A basis.
ret_norms	return the residual norm and solution norms.

Value

l2 reconstructed mrs_data object.

lb	<i>Apply line-broadening (apodisation) to MRS data or basis object.</i>
----	---

Description

Apply line-broadening (apodisation) to MRS data or basis object.

Usage

```
lb(x, lb, lg = 1)

## S3 method for class 'list'
lb(x, lb, lg = 1)

## S3 method for class 'mrs_data'
lb(x, lb, lg = 1)

## S3 method for class 'basis_set'
lb(x, lb, lg = 1)
```

Arguments

x	input mrs_data or basis_set object.
lb	amount of line-broadening in Hz.
lg	Lorentz-Gauss lineshape parameter (between 0 and 1).

Value

line-broadened data.

lofdc	<i>Correct linear frequency drift.</i>
-------	--

Description

Correct linear frequency drift.

Usage

```
lofdc(
  mrs_data,
  max_hz_s = 0.1,
  tr = NULL,
  ret_corr_only = TRUE,
  outlier_thresh = 3,
```

```
xlim = c(4, 0.5),  
order = 1  
)
```

Arguments

mrs_data	MRS data to be corrected.
max_hz_s	the maximum drift rate to search over.
tr	mrs_data repetition time.
ret_corr_only	return the corrected mrs_data object only.
outlier_thresh	threshold to remove outliers.
xlim	spectral width (in ppm) to evaluate outliers.
order	correction order.

Value

drift corrected mrs_data object.

lw2alpha	<i>Covert a linewidth in Hz to an equivalent alpha value in the time-domain ie: $x * \exp(-t * \alpha)$.</i>
----------	---

Description

Covert a linewidth in Hz to an equivalent alpha value in the time-domain ie: $x * \exp(-t * \alpha)$.

Usage

```
lw2alpha(lw)
```

Arguments

lw	linewidth in Hz.
----	------------------

Value

beta damping value.

lw2beta	<i>Covert a linewidth in Hz to an equivalent beta value in the time-domain ie: $x * \exp(-t * t * \text{beta})$.</i>
---------	---

Description

Covert a linewidth in Hz to an equivalent beta value in the time-domain ie: $x * \exp(-t * t * \text{beta})$.

Usage

```
lw2beta(lw)
```

Arguments

lw	linewidth in Hz.
----	------------------

Value

beta damping value.

make_basis_from_raw	<i>Make a basis-set object from a directory containing LCModel formatted RAW files.</i>
---------------------	---

Description

Make a basis-set object from a directory containing LCModel formatted RAW files.

Usage

```
make_basis_from_raw(dir_path, ft, fs, ref)
```

Arguments

dir_path	path to the directory containing LCModel RAW files. One file per signal.
ft	transmitter frequency in Hz.
fs	sampling frequency in Hz.
ref	reference value for ppm scale.

Value

a basis-set object.

mask_dyns	<i>Mask an MRS dataset in the dynamic dimension.</i>
-----------	--

Description

Mask an MRS dataset in the dynamic dimension.

Usage

```
mask_dyns(mrs_data, mask)
```

Arguments

mrs_data	MRS data object.
mask	vector of boolean values specifying the dynamics to mask, where a value of TRUE indicates the spectrum should be removed.

Value

masked dataset.

mask_fit_res	<i>Mask fit result spectra depending on a vector of bool values.</i>
--------------	--

Description

Mask fit result spectra depending on a vector of bool values.

Usage

```
mask_fit_res(fit_result, mask_vec, amps_only = FALSE)
```

Arguments

fit_result	fit result object to be masked.
mask_vec	a Boolean vector with the same number of rows as there are rows in the results table.
amps_only	only mask the amplitude and associated error estimate columns.

Value

a masked fit result object.

mask_xy	<i>Mask an MRSI dataset in the x-y direction</i>
---------	--

Description

Mask an MRSI dataset in the x-y direction

Usage

mask_xy(mrs_data, x_dim, y_dim)

Arguments

- mrs_data MRS data object.
- x_dim x dimension output length.
- y_dim y dimension output length.

Value

masked MRS data.

mask_xy_corners	<i>Mask the four corners of an MRSI dataset in the x-y plane.</i>
-----------------	---

Description

Mask the four corners of an MRSI dataset in the x-y plane.

Usage

mask_xy_corners(mrs_data)

Arguments

- mrs_data MRS data object.

Value

masked MRS data.

mask_xy_ellipse	<i>Mask the voxels outside an elliptical region spanning the MRSI dataset in the x-y plane.</i>
-----------------	---

Description

Mask the voxels outside an elliptical region spanning the MRSI dataset in the x-y plane.

Usage

```
mask_xy_ellipse(mrs_data)
```

Arguments

mrs_data	MRS data object.
----------	------------------

Value

masked MRS data.

mask_xy_mat	<i>Mask a 2D MRSI dataset in the x-y dimension.</i>
-------------	---

Description

Mask a 2D MRSI dataset in the x-y dimension.

Usage

```
mask_xy_mat(mrs_data, mask, value = NA)
```

Arguments

mrs_data	MRS data object.
mask	matrix of boolean values specifying the voxels to mask, where a value of TRUE indicates the voxel should be removed.
value	the value to set masked data to (usually NA or 0).

Value

masked dataset.

mat2mrs_data	<i>Convert a matrix (with spectral points in the column dimension and dynamics in the row dimensions) into a mrs_data object.</i>
--------------	---

Description

Convert a matrix (with spectral points in the column dimension and dynamics in the row dimensions) into a mrs_data object.

Usage

```
mat2mrs_data(
  mat,
  mrs_data = NULL,
  fs = NULL,
  ft = NULL,
  ref = NULL,
  nuc = NULL,
  fd = FALSE
)
```

Arguments

mat	data matrix.
mrs_data	example data to copy acquisition parameters from.
fs	sampling frequency in Hz.
ft	transmitter frequency in Hz.
ref	reference value for ppm scale.
nuc	resonant nucleus.
fd	flag to indicate if the matrix is in the frequency domain (logical).

Value

mrs_data object.

matexp	<i>Matrix exponential function taken from complexplus package to reduce the number of spant dependencies.</i>
--------	---

Description

Matrix exponential function taken from complexplus package to reduce the number of spant dependencies.

Usage

```
matexp(x)
```

Arguments

x a square complex matrix.

Value

the matrix exponential of x.

max_mrs	<i>Apply the max operator to an MRS dataset.</i>
---------	--

Description

Apply the max operator to an MRS dataset.

Usage

```
max_mrs(mrs_data)
```

Arguments

mrs_data MRS data.

Value

MRS data following max operator.

max_mrs_interp	<i>Apply the max operator to an interpolated MRS dataset.</i>
----------------	---

Description

Apply the max operator to an interpolated MRS dataset.

Usage

```
max_mrs_interp(mrs_data, interp_f = 4)
```

Arguments

mrs_data MRS data.
interp_f interpolation factor.

Value

Array of maximum values (real only).

mean.list	<i>Calculate the mean spectrum from an mrs_data object.</i>
-----------	---

Description

Calculate the mean spectrum from an mrs_data object.

Usage

```
## S3 method for class 'list'
mean(x, ...)
```

Arguments

x	object of class mrs_data.
...	other arguments to pass to the colMeans function.

Value

mean mrs_data object.

mean.mrs_data	<i>Calculate the mean spectrum from an mrs_data object.</i>
---------------	---

Description

Calculate the mean spectrum from an mrs_data object.

Usage

```
## S3 method for class 'mrs_data'
mean(x, ...)
```

Arguments

x	object of class mrs_data.
...	other arguments to pass to the colMeans function.

Value

mean mrs_data object.

mean_dyns	<i>Calculate the mean dynamic data.</i>
-----------	---

Description

Calculate the mean dynamic data.

Usage

```
mean_dyns(mrs_data, subset = NULL)
```

Arguments

mrs_data	dynamic MRS data.
subset	vector containing indices to the dynamic scans to be averaged.

Value

mean dynamic data.

mean_dyn_blocks	<i>Calculate the mean of adjacent dynamic scans.</i>
-----------------	--

Description

Calculate the mean of adjacent dynamic scans.

Usage

```
mean_dyn_blocks(mrs_data, block_size)
```

Arguments

mrs_data	dynamic MRS data.
block_size	number of adjacent dynamics scans to average over.

Value

dynamic data averaged in blocks.

mean_dyn_pairs	<i>Calculate the pairwise means across a dynamic data set.</i>
----------------	--

Description

Calculate the pairwise means across a dynamic data set.

Usage

```
mean_dyn_pairs(mrs_data)
```

Arguments

mrs_data	dynamic MRS data.
----------	-------------------

Value

mean dynamic data of adjacent dynamic pairs.

mean_mrs_list	<i>Return the mean of a list of mrs_data objects.</i>
---------------	---

Description

Return the mean of a list of mrs_data objects.

Usage

```
mean_mrs_list(mrs_list)
```

Arguments

mrs_list	list of mrs_data objects.
----------	---------------------------

Value

mean mrs_data object.

mean_vec_blocks	<i>Calculate the mean of adjacent blocks in a vector.</i>
-----------------	---

Description

Calculate the mean of adjacent blocks in a vector.

Usage

```
mean_vec_blocks(x, block_size)
```

Arguments

x	input vector.
block_size	number of adjacent elements to average over.

Value

vector data averaged in blocks.

median_dyns	<i>Calculate the median dynamic data.</i>
-------------	---

Description

Calculate the median dynamic data.

Usage

```
median_dyns(mrs_data)
```

Arguments

mrs_data	dynamic MRS data.
----------	-------------------

Value

median dynamic data.

Mod.mrs_data	<i>Apply Mod operator to an MRS dataset.</i>
--------------	--

Description

Apply Mod operator to an MRS dataset.

Usage

```
## S3 method for class 'mrs_data'  
Mod(z)
```

Arguments

z MRS data.

Value

MRS data following Mod operator.

mod_td	<i>Apply the Modulus operator to the time-domain MRS signal.</i>
--------	--

Description

Apply the Modulus operator to the time-domain MRS signal.

Usage

```
mod_td(mrs_data)
```

Arguments

mrs_data MRS data input.

Value

time-domain modulus of input.

mrs_data2basis	<i>Convert an mrs_data object to basis object - where basis signals are spread across the dynamic dimension in the MRS data.</i>
----------------	--

Description

Convert an mrs_data object to basis object - where basis signals are spread across the dynamic dimension in the MRS data.

Usage

```
mrs_data2basis(mrs_data, names)
```

Arguments

mrs_data	mrs_data object with basis signals spread across the dynamic dimension.
names	list of names corresponding to basis signals.

Value

basis set object.

mrs_data2bids	<i>Create a BIDS file structure from a vector of MRS data paths or list of mrs_data objects.</i>
---------------	--

Description

Create a BIDS file structure from a vector of MRS data paths or list of mrs_data objects.

Usage

```
mrs_data2bids(
  mrs_data,
  output_dir,
  suffix = NULL,
  sub = NULL,
  ses = NULL,
  task = NULL,
  acq = NULL,
  nuc = NULL,
  voi = NULL,
  rec = NULL,
  run = NULL,
  echo = NULL,
```

```
    inv = NULL,  
    skip_existing = TRUE  
  )
```

Arguments

mrs_data	vector of MRS data paths or list of mrs_data objects.
output_dir	the base directory to create the BIDS structure.
suffix	optional vector of file suffixes. Default behaviour is to automatically determine these from the input data, however it is recommended that they are specified to allow more efficient skipping of existing data.
sub	optional vector of subject labels. If not specified, these will be automatically generated as a series of increasing zero-padded integer values corresponding to the mrs_data input indices.
ses	optional vector of session labels.
task	optional vector of task labels.
acq	optional vector of acquisition labels.
nuc	optional vector of nucleus labels.
voi	optional vector of volume of interest labels.
rec	optional vector of reconstruction labels.
run	optional vector of run indices.
echo	optional vector of echo time indices.
inv	optional vector of inversion indices.
skip_existing	skip any data files that have already been converted. Defaults to TRUE, set to FALSE to force an overwrite of any existing data files.

mrs_data2list	<i>Split MRS data containing multiple spectra into a list of single spectra datasets.</i>
---------------	---

Description

Split MRS data containing multiple spectra into a list of single spectra datasets.

Usage

```
mrs_data2list(mrs_data)
```

Arguments

mrs_data	input MRS dataset
----------	-------------------

Value

list of MRS datasets

mrs_data2mat	<i>Convert mrs_data object to a matrix, with spectral points in the column dimension and dynamics in the row dimension.</i>
--------------	---

Description

Convert mrs_data object to a matrix, with spectral points in the column dimension and dynamics in the row dimension.

Usage

```
mrs_data2mat(mrs_data, collapse = TRUE)
```

Arguments

mrs_data	MRS data object or list of MRS data objects.
collapse	collapse all other dimensions along the dynamic dimension, eg a 16x16 MRSI grid would be first collapsed across 256 dynamic scans.

Value

MRS data matrix.

mrs_data2spec_mat	<i>Convert mrs_data object to a matrix, with spectral points in the column dimension and dynamics in the row dimension.</i>
-------------------	---

Description

Convert mrs_data object to a matrix, with spectral points in the column dimension and dynamics in the row dimension.

Usage

```
mrs_data2spec_mat(mrs_data, collapse = TRUE)
```

Arguments

mrs_data	MRS data object or list of MRS data objects.
collapse	collapse all other dimensions along the dynamic dimension, eg a 16x16 MRSI grid would be first collapsed across 256 dynamic scans.

Value

MRS data matrix.

mrs_data2vec	<i>Convert mrs_data object to a vector.</i>
--------------	---

Description

Convert mrs_data object to a vector.

Usage

```
mrs_data2vec(mrs_data, dyn = 1, x_pos = 1, y_pos = 1, z_pos = 1, coil = 1)
```

Arguments

mrs_data	MRS data object.
dyn	dynamic index.
x_pos	x index.
y_pos	y index.
z_pos	z index.
coil	coil element index.

Value

MRS data vector.

mr_data2bids	<i>Create a BIDS file structure from a vector of data paths or list of mri/mrs data objects.</i>
--------------	--

Description

Create a BIDS file structure from a vector of data paths or list of mri/mrs data objects.

Usage

```
mr_data2bids(
  mr_data,
  suffix,
  output_dir,
  sub = NULL,
  ses = NULL,
  task = NULL,
  acq = NULL,
  nuc = NULL,
  voi = NULL,
```

```

    rec = NULL,
    run = NULL,
    echo = NULL,
    inv = NULL,
    skip_existing = TRUE,
    mri_format = "nifti",
    deface_mri = FALSE
)

```

Arguments

mr_data	vector of data paths or list of mri/mrs objects.
suffix	vector of file suffixes, eg : c("svs", "mrsi", "T1w").
output_dir	the base directory to create the BIDS structure.
sub	optional vector of subject labels. If not specified, these will be automatically generated as a series of increasing zero-padded integer values corresponding to the mrs_data input indices.
ses	optional vector of session labels.
task	optional vector of task labels.
acq	optional vector of acquisition labels.
nuc	optional vector of nucleus labels.
voi	optional vector of volume of interest labels.
rec	optional vector of reconstruction labels.
run	optional vector of run indices.
echo	optional vector of echo time indices.
inv	optional vector of inversion indices.
skip_existing	skip any data files that have already been converted. Defaults to TRUE, set to FALSE to force an overwrite of any existing data files.
mri_format	defaults to "nifti", can also be "dicom" provided the divest packages is installed.
deface_mri	option to apply fsl_deface to the mri as a preprocessing step. Defaults to FALSE, requires the fsLR package to be installed when TRUE.

mvfftshift	<i>Perform a fftshift on a matrix, with each column replaced by its shifted result.</i>
------------	---

Description

Perform a fftshift on a matrix, with each column replaced by its shifted result.

Usage

```
mvfftshift(x)
```

Arguments

x matrix input.

Value

output matrix.

mvifftshift	<i>Perform an ifftshift on a matrix, with each column replaced by its shifted result.</i>
-------------	---

Description

Perform an ifftshift on a matrix, with each column replaced by its shifted result.

Usage

mvifftshift(x)

Arguments

x matrix input.

Value

output matrix.

n2coord	<i>Print fit coordinates from a single index.</i>
---------	---

Description

Print fit coordinates from a single index.

Usage

n2coord(n, fit_res)

Arguments

n fit index.
fit_res fit_result object.

Ncoils	<i>Return the total number of coil elements in an MRS dataset.</i>
--------	--

Description

Return the total number of coil elements in an MRS dataset.

Usage

```
Ncoils(mrs_data)
```

Arguments

mrs_data	MRS data.
----------	-----------

Ndyns	<i>Return the total number of dynamic scans in an MRS dataset.</i>
-------	--

Description

Return the total number of dynamic scans in an MRS dataset.

Usage

```
Ndyns(mrs_data)
```

Arguments

mrs_data	MRS data.
----------	-----------

nifti_flip_lr	<i>Flip the x data dimension order of a nifti image. This corresponds to flipping MRI data in the left-right direction, assuming the data is saved in neurological format (can check with fsorient program).</i>
---------------	--

Description

Flip the x data dimension order of a nifti image. This corresponds to flipping MRI data in the left-right direction, assuming the data is saved in neurological format (can check with fsorient program).

Usage

```
nifti_flip_lr(x)
```

Arguments

x nifti object to be processed.

Value

nifti object with reversed x data direction.

Npts	<i>Return the number of data points in an MRS dataset.</i>
------	--

Description

Return the number of data points in an MRS dataset.

Usage

Npts(mrs_data)

Arguments

mrs_data MRS data.

Value

number of data points.

Nspec	<i>Return the total number of spectra in an MRS dataset.</i>
-------	--

Description

Return the total number of spectra in an MRS dataset.

Usage

Nspec(mrs_data)

Arguments

mrs_data MRS data.

Ntrans	<i>Return the total number of acquired transients for an MRS dataset.</i>
--------	---

Description

Return the total number of acquired transients for an MRS dataset.

Usage

Ntrans(mrs_data)

Arguments

mrs_data	MRS data.
----------	-----------

Nx	<i>Return the total number of x locations in an MRS dataset.</i>
----	--

Description

Return the total number of x locations in an MRS dataset.

Usage

Nx(mrs_data)

Arguments

mrs_data	MRS data.
----------	-----------

Ny	<i>Return the total number of y locations in an MRS dataset.</i>
----	--

Description

Return the total number of y locations in an MRS dataset.

Usage

Ny(mrs_data)

Arguments

mrs_data	MRS data.
----------	-----------

Nz	<i>Return the total number of z locations in an MRS dataset.</i>
----	--

Description

Return the total number of z locations in an MRS dataset.

Usage

Nz(mrs_data)

Arguments

mrs_data MRS data.

one_page_pdf	<i>Export a one-page pdf of a single fit result</i>
--------------	---

Description

Export a one-page pdf of a single fit result

Usage

one_page_pdf(fit_res, pdf_out_path, title = NULL)

Arguments

fit_res fit_result object.
pdf_out_path path to the exported pdf file.
title output title.

ortho3

Display an orthographic projection plot of a nifti object.

Description

Display an orthographic projection plot of a nifti object.

Usage

```
ortho3(
  underlay,
  overlay = NULL,
  xyz = NULL,
  zlim = NULL,
  zlim_ol = NULL,
  alpha = 0.7,
  col_ol = viridisLite::viridis(64),
  orient_lab = TRUE,
  rescale = 1,
  crosshairs = TRUE,
  ch_lwd = 1,
  colourbar = TRUE,
  bg = "black",
  mar = c(0, 0, 0, 0),
  smallplot = c(0.63, 0.65, 0.07, 0.42),
  legend_axis_cex = 0.75
)
```

Arguments

underlay	underlay image to be shown in grayscale.
overlay	optional overlay image.
xyz	x, y, z slice coordinates to display.
zlim	underlay intensity limits.
zlim_ol	overlay intensity limits.
alpha	transparency of overlay.
col_ol	colour palette of overlay.
orient_lab	display orientation labels (default TRUE).
rescale	rescale factor for the underlay and overlay images.
crosshairs	display the crosshairs (default TRUE).
ch_lwd	crosshair linewidth.
colourbar	display a colourbar for the overlay (default TRUE).
bg	plot background colour.

mar	plot margins.
smallplot	smallplot option for positioning the colourbar.
legend_axis_cex	font expansion factor for the legend axis text.

ortho3_inter	<i>Display an interactive orthographic projection plot of a nifti object.</i>
--------------	---

Description

Display an interactive orthographic projection plot of a nifti object.

Usage

```
ortho3_inter(
  underlay,
  overlay = NULL,
  xyz = NULL,
  zlim = NULL,
  zlim_ol = NULL,
  alpha = 0.7,
  ...
)
```

Arguments

underlay	underlay image to be shown in grayscale.
overlay	optional overlay image.
xyz	x, y, z slice coordinates to display.
zlim	underlay intensity limits.
zlim_ol	overlay intensity limits.
alpha	transparency of overlay.
...	other options to be passed to the ortho3 function.

peak_info	<i>Search for the highest peak in a spectral region and return the frequency, height and FWHM.</i>
-----------	--

Description

Search for the highest peak in a spectral region and return the frequency, height and FWHM.

Usage

```
peak_info(  
  mrs_data,  
  xlim = c(4, 0.5),  
  interp_f = 4,  
  scale = "ppm",  
  mode = "real"  
)
```

Arguments

mrs_data	an object of class mrs_data.
xlim	frequency range (default units of PPM) to search for the highest peak.
interp_f	interpolation factor, defaults to 4x.
scale	the units to use for the frequency scale, can be one of: "ppm", "hz" or "points".
mode	spectral mode, can be : "real", "imag" or "mod".

Value

list of arrays containing the highest peak frequency, height and FWHM in units of PPM and Hz.

pg_extrap_xy	<i>Papoulis-Gerchberg (PG) algorithm method for k-space extrapolation.</i>
--------------	--

Description

PG method as described in: Haupt CI, Schuff N, Weiner MW, Maudsley AA. Removal of lipid artifacts in 1H spectroscopic imaging by data extrapolation. Magn Reson Med. 1996 May;35(5):678-87. Extrapolation is performed to expand k-space coverage by a factor of 2, with the aim to reduce Gibbs ringing.

Usage

```
pg_extrap_xy(  
    mrs_data,  
    img_mask = NULL,  
    kspace_mask = NULL,  
    intensity_thresh = 0.15,  
    iters = 50  
)
```

Arguments

mrs_data	MRS data object.
img_mask	a boolean matrix of voxels with strong signals to be extrapolated. Must be twice the dimensions of the input data.
kspace_mask	a boolean matrix of kspace points that have been sampled. Typically a circle for MRSI, but defaults to the full rectangular area of k-space covered by the input data. Must match the x-y dimensions of the input data.
intensity_thresh	used to define img_mask based on the strength of the signal in each voxel. Defaults to intensities greater than 15% of the maximum. Ignored if img_mask is specified as argument.
iters	number of iterations to perform.

Value

extrapolated mrs_data object.

phase	<i>Apply phasing parameters to MRS data.</i>
-------	--

Description

Apply phasing parameters to MRS data.

Usage

```
phase(mrs_data, zero_order, first_order = 0)
```

Arguments

mrs_data	MRS data.
zero_order	zero'th order phase term in degrees.
first_order	first order (frequency dependent) phase term in ms.

Value

MRS data with applied phase parameters.

phase_ref_1h_brain	<i>Corrected zero order phase and chemical shift offset in 1H MRS data from the brain.</i>
--------------------	--

Description

Corrected zero order phase and chemical shift offset in 1H MRS data from the brain.

Usage

```
phase_ref_1h_brain(  
  mrs_data,  
  mean_ref = FALSE,  
  ret_corr_only = TRUE,  
  xlim = c(4, 1.9),  
  p_deg = 3,  
  sp_N = 2,  
  basis_type = "poly"  
)
```

Arguments

mrs_data	MRS data to be corrected.
mean_ref	apply the phase and offset of the mean spectrum to all others. Default is FALSE.
ret_corr_only	return the corrected data only.
xlim	frequency range in ppm to consider.
p_deg	polynomial baseline order.
sp_N	number of spline functions, note the true number will be sp_N + sp_deg.
basis_type	may be one of "poly" or "spline".

Value

corrected MRS data.

plot.fit_result	<i>Plot the fitting results of an object of class fit_result.</i>
-----------------	---

Description

Plot the fitting results of an object of class fit_result.

Usage

```
## S3 method for class 'fit_result'
plot(
  x,
  dyn = 1,
  x_pos = 1,
  y_pos = 1,
  z_pos = 1,
  coil = 1,
  xlim = NULL,
  data_only = FALSE,
  label = NULL,
  plot_sigs = NULL,
  n = NULL,
  sub_bl = FALSE,
  mar = NULL,
  restore_def_par = TRUE,
  ylim = NULL,
  y_scale = FALSE,
  show_grid = TRUE,
  grid_nx = NULL,
  grid_ny = NA,
  invert_fit = FALSE,
  ...
)
```

Arguments

<code>x</code>	fit_result object.
<code>dyn</code>	the dynamic index to plot.
<code>x_pos</code>	the x index to plot.
<code>y_pos</code>	the y index to plot.
<code>z_pos</code>	the z index to plot.
<code>coil</code>	the coil element number to plot.
<code>xlim</code>	the range of values to display on the x-axis, eg <code>xlim = c(4,1)</code> .
<code>data_only</code>	display only the processed data (logical).
<code>label</code>	character string to add to the top left of the plot window.
<code>plot_sigs</code>	a character vector of signal names to add to the plot.
<code>n</code>	single index element to plot (overrides other indices when given).
<code>sub_bl</code>	subtract the baseline from the data and fit (logical).
<code>mar</code>	option to adjust the plot margins. See <code>?par</code> .
<code>restore_def_par</code>	restore default plotting par values after the plot has been made.
<code>ylim</code>	range of values to display on the y-axis, eg <code>ylim = c(0,10)</code> .

y_scale	option to display the y-axis values (logical).
show_grid	plot gridlines behind the data (logical). Defaults to TRUE.
grid_nx	number of cells of the grid in x and y direction. When NULL the grid aligns with the tick marks on the corresponding default axis (i.e., tickmarks as computed by axTicks). When NA, no grid lines are drawn in the corresponding direction.
grid_ny	as above.
invert_fit	show the fit result "upside-down"/
...	further arguments to plot method.

plot.mrs_data	<i>Plotting method for objects of class mrs_data.</i>
---------------	---

Description

Plotting method for objects of class mrs_data.

Usage

```
## S3 method for class 'mrs_data'
plot(
  x,
  dyn = 1,
  x_pos = 1,
  y_pos = 1,
  z_pos = 1,
  coil = 1,
  fd = TRUE,
  x_units = NULL,
  xlim = NULL,
  y_scale = FALSE,
  x_ax = TRUE,
  mode = "re",
  lwd = NULL,
  bty = NULL,
  label = "",
  restore_def_par = TRUE,
  mar = NULL,
  xaxis_lab = NULL,
  yaxis_lab = NULL,
  xat = NULL,
  xlabs = TRUE,
  yat = NULL,
  ylabs = TRUE,
  show_grid = TRUE,
  grid_nx = NULL,
```

```

    grid_ny = NA,
    col = NULL,
    alpha = NULL,
    bl_lty = NULL,
    hline = NULL,
    hline_lty = 2,
    hline_col = "red",
    vline = NULL,
    vline_lty = 2,
    vline_col = "red",
    ...
)

```

Arguments

x	object of class <code>mrs_data</code> .
dyn	the dynamic index to plot.
x_pos	the x index to plot.
y_pos	the y index to plot.
z_pos	the z index to plot.
coil	the coil element number to plot.
fd	display data in the frequency-domain (default), or time-domain (logical).
x_units	the units to use for the x-axis, can be one of: "ppm", "hz", "points" or "seconds".
xlim	the range of values to display on the x-axis, eg <code>xlim = c(4,1)</code> .
y_scale	option to display the y-axis values (logical).
x_ax	option to display the x-axis values (logical).
mode	representation of the complex numbers to be plotted, can be one of: "re", "im", "mod" or "arg".
lwd	plot linewidth.
bty	option to draw a box around the plot. See <code>?par</code> .
label	character string to add to the top left of the plot window.
restore_def_par	restore default plotting <code>par</code> values after the plot has been made.
mar	option to adjust the plot margins. See <code>?par</code> .
xaxis_lab	x-axis label.
yaxis_lab	y-axis label.
xat	x-axis tick label values.
xlabs	x-axis tick labels.
yat	y-axis tick label values.
ylabs	y-axis tick labels.
show_grid	plot gridlines behind the data (logical). Defaults to <code>TRUE</code> .

grid_nx	number of cells of the grid in x and y direction. When NULL the grid aligns with the tick marks on the corresponding default axis (i.e., tickmarks as computed by axTicks). When NA, no grid lines are drawn in the corresponding direction.
grid_ny	as above.
col	set the line colour, eg col = rgb(0.5, 0.5, 0.5).
alpha	set the line transparency, eg alpha = 0.5 is 50% transparency. Overrides any transparency levels set by col.
bl_lty	linetype for the y = 0 baseline trace. A default value NULL results in no baseline being plotted.
hline	add a horizontal line at the specified value.
hline_lty	linetype for the horizontal line.
hline_col	colour for the horizontal line.
vline	add a vertical line at the specified value.
vline_lty	linetype for the vertical line.
vline_col	colour for the vertical line.
...	other arguments to pass to the plot method.

plot_bc	<i>Convenience function to plot a baseline estimate with the original data.</i>
---------	---

Description

Convenience function to plot a baseline estimate with the original data.

Usage

```
plot_bc(orig_data, bc_data, ...)
```

Arguments

orig_data	the original data.
bc_data	the baseline corrected data.
...	other arguments to pass to the stackplot function.

plot_reg	<i>Plot regressors as an image.</i>
----------	-------------------------------------

Description

Plot regressors as an image.

Usage

```
plot_reg(regressor_df)
```

Arguments

regressor_df input regressor data frame.

plot_slice_fit	<i>Plot a 2D slice from an MRSI fit result object.</i>
----------------	--

Description

Plot a 2D slice from an MRSI fit result object.

Usage

```
plot_slice_fit(  
  fit_res,  
  map,  
  map_denom = NULL,  
  slice = 1,  
  zlim = NULL,  
  interp = 1  
)
```

Arguments

fit_res	fit_result object.
map	fit result values to display as a colour map. Can be specified as a character string or array of numeric values. Defaults to "tNAA".
map_denom	fit result values to divide the map argument by. Can be specified as a character string (eg "tCr") or array of numeric values.
slice	slice to plot in the z direction.
zlim	range of values to plot.
interp	interpolation factor.

plot_slice_fit_inter *Plot a 2D slice from an MRSI fit result object.*

Description

Plot a 2D slice from an MRSI fit result object.

Usage

```
plot_slice_fit_inter(
  fit_res,
  map = NULL,
  map_denom = NULL,
  slice = 1,
  zlim = NULL,
  interp = 1,
  xlim = NULL
)
```

Arguments

fit_res	fit_result object.
map	fit result values to display as a colour map. Can be specified as a character string or array of numeric values. Defaults to "tNAA".
map_denom	fit result values to divide the map argument by. Can be specified as a character string (eg "tCr") or array of numeric values.
slice	slice to plot in the z direction.
zlim	range of values to plot.
interp	interpolation factor.
xlim	spectral plot limits for the x axis.

plot_slice_map *Plot a slice from a 7 dimensional array.*

Description

Plot a slice from a 7 dimensional array.

Usage

```

plot_slice_map(
    data,
    zlim = NULL,
    mask_map = NULL,
    mask_cutoff = 20,
    interp = 1,
    slice = 1,
    dyn = 1,
    coil = 1,
    ref = 1,
    denom = NULL,
    horizontal = FALSE
)

```

Arguments

data	7d array of values to be plotted.
zlim	smallest and largest values to be plotted.
mask_map	matching map with logical values to indicate if the corresponding values should be plotted.
mask_cutoff	minimum values to plot (as a percentage of the maximum).
interp	map interpolation factor.
slice	the slice index to plot.
dyn	the dynamic index to plot.
coil	the coil element number to plot.
ref	reference index to plot.
denom	map to use as a denominator.
horizontal	display the colourbar horizontally (logical).

plot_slice_map_inter	<i>Plot an interactive slice map from a data array where voxels can be selected to display a corresponding spectrum.</i>
----------------------	--

Description

Plot an interactive slice map from a data array where voxels can be selected to display a corresponding spectrum.

Usage

```
plot_slice_map_inter(  
  mrs_data,  
  map = NULL,  
  xlim = NULL,  
  slice = 1,  
  zlim = NULL,  
  mask_map = NULL,  
  denom = NULL,  
  mask_cutoff = 20,  
  interp = 1,  
  mode = "re",  
  y_scale = FALSE,  
  ylim = NULL,  
  coil = 1,  
  fd = TRUE  
)
```

Arguments

mrs_data	spectral data.
map	array of values to be plotted, defaults to the integration of the modulus of the full spectral width.
xlim	spectral region to plot.
slice	the slice index to plot.
zlim	smallest and largest values to be plotted.
mask_map	matching map with logical values to indicate if the corresponding values should be plotted.
denom	map to use as a denominator.
mask_cutoff	minimum values to plot (as a percentage of the maximum).
interp	map interpolation factor.
mode	representation of the complex spectrum to be plotted, can be one of: "re", "im", "mod" or "arg".
y_scale	option to display the y-axis values (logical).
ylim	intensity range to plot.
coil	coil element to plot.
fd	display data in the frequency-domain (default), or time-domain (logical).

plot_spec_sd	<i>Plot the spectral standard deviation.</i>
--------------	--

Description

Plot the spectral standard deviation.

Usage

```
plot_spec_sd(mrs_data, xlim = NULL, scale_sd = 1.96, ...)
```

Arguments

mrs_data	MRS data to be plotted.
xlim	plotting limits in ppm.
scale_sd	scaling factor for the standard deviation trace.
...	other arguments passed to the stackplot function.

plot_voi_overlay	<i>Plot a volume as an image overlay.</i>
------------------	---

Description

Plot a volume as an image overlay.

Usage

```
plot_voi_overlay(mri, voi, export_path = NULL, zlim = NULL, ...)
```

Arguments

mri	image data as a nifti object or path to data file.
voi	volume data as a nifti object or path to data file.
export_path	optional path to save the image in png format.
zlim	underlay intensity limits.
...	additional arguments to the ortho3 function.

plot_voi_overlay_seg *Plot a volume as an overlay on a segmented brain volume.*

Description

Plot a volume as an overlay on a segmented brain volume.

Usage

```
plot_voi_overlay_seg(mri_seg, voi, export_path = NULL, ...)
```

Arguments

mri_seg	segmented brain volume as a nifti object.
voi	volume data as a nifti object.
export_path	optional path to save the image in png format.
...	additional arguments to the ortho3 function.

ppm *Return the ppm scale of an MRS dataset or fit result.*

Description

Return the ppm scale of an MRS dataset or fit result.

Usage

```
ppm(x, ft = NULL, ref = NULL, fs = NULL, N = NULL)
```

```
## S3 method for class 'mrs_data'
```

```
ppm(x, ft = NULL, ref = NULL, fs = NULL, N = NULL)
```

```
## S3 method for class 'fit_result'
```

```
ppm(x, ft = NULL, ref = NULL, fs = NULL, N = NULL)
```

Arguments

x	MRS dataset or fit result.
ft	transmitter frequency in Hz, does not apply when the object is a fit result.
ref	reference value for ppm scale, does not apply when the object is a fit result.
fs	sampling frequency in Hz, does not apply when the object is a fit result.
N	number of data points in the spectral dimension, does not apply when the object is a fit result.

Value

ppm scale.

precomp	<i>Save function results to file and load on subsequent calls to avoid repeat computation.</i>
---------	--

Description

Save function results to file and load on subsequent calls to avoid repeat computation.

Usage

```
precomp(file, fun, ...)
```

Arguments

file	file name to write the results.
fun	function to run.
...	arguments to be passed to fun.

preproc_svs	<i>Preprocess and perform quality assessment of a single SVS data set.</i>
-------------	--

Description

Preprocess and perform quality assessment of a single SVS data set.

Usage

```
preproc_svs(path, label = NULL, output_dir = NULL, ref_inds = NULL)
```

Arguments

path	path to the fMRS data file or IMA directory.
label	a label to describe the data set.
output_dir	output directory.
ref_inds	a vector of 1-based indices for any water reference dynamic scans.

preproc_svs_dataset	<i>Preprocess and perform quality assessment of one or more SVS data sets.</i>
---------------------	--

Description

Preprocess and perform quality assessment of one or more SVS data sets.

Usage

```
preproc_svs_dataset(
  paths,
  labels = NULL,
  output_dir = "spant_analysis",
  exclude_labels = NULL,
  overwrite = FALSE,
  ref_inds = NULL,
  return_results = FALSE
)
```

Arguments

paths	paths to the fMRS data file or IMA directory.
labels	labels to describe each data set.
output_dir	output directory.
exclude_labels	vector of labels of scans to exclude, eg poor quality data.
overwrite	overwrite saved results, defaults to FALSE.
ref_inds	a vector of 1-based indices for any water reference dynamic scans.
return_results	function will return key outputs, defaults to FALSE.

print.fit_result	<i>Print a summary of an object of class fit_result.</i>
------------------	--

Description

Print a summary of an object of class fit_result.

Usage

```
## S3 method for class 'fit_result'
print(x, ...)
```

Arguments

x	fit_result object.
...	further arguments.

<code>print.mrs_data</code>	<i>Print a summary of mrs_data parameters.</i>
-----------------------------	--

Description

Print a summary of mrs_data parameters.

Usage

```
## S3 method for class 'mrs_data'
print(x, full = FALSE, ...)
```

Arguments

<code>x</code>	mrs_data object.
<code>full</code>	print all parameters (default FALSE).
<code>...</code>	further arguments.

<code>qn_states</code>	<i>Get the quantum coherence matrix for a spin system.</i>
------------------------	--

Description

Get the quantum coherence matrix for a spin system.

Usage

```
qn_states(sys)
```

Arguments

<code>sys</code>	spin system object.
------------------	---------------------

Value

quantum coherence number matrix.

rats

Robust Alignment to a Target Spectrum (RATS).

Description

Robust Alignment to a Target Spectrum (RATS).

Usage

```
rats(
  mrs_data,
  ref = NULL,
  xlim = c(4, 0.5),
  max_shift = 20,
  p_deg = 2,
  sp_N = 2,
  sp_deg = 3,
  max_t = 0.2,
  basis_type = "poly",
  rescale_output = TRUE,
  phase_corr = TRUE,
  ret_corr_only = TRUE,
  zero_freq_shift_t0 = FALSE,
  list_mean_ref = TRUE,
  remove_freq_outliers = FALSE,
  freq_outlier_thresh = 3,
  remove_phase_outliers = FALSE,
  phase_outlier_thresh = 3,
  remove_amp_outliers = FALSE,
  amp_outlier_thresh = 3
)
```

Arguments

mrs_data	MRS data to be corrected.
ref	optional MRS data to use as a reference, the mean of all dynamics is used if this argument is not supplied.
xlim	optional frequency range to perform optimisation, set to NULL to use the full range.
max_shift	maximum allowable frequency shift in Hz.
p_deg	polynomial degree used for baseline modelling. Negative values disable baseline modelling.
sp_N	number of spline functions, note the true number will be sp_N + sp_deg.
sp_deg	degree of spline functions.

max_t	truncate the FID when longer than max_t to reduce time taken, set to NULL to use the entire FID.
basis_type	may be one of "poly" or "spline".
rescale_output	rescale the bl_matched_spec and bl output to improve consistency between dynamic scans.
phase_corr	apply phase correction (in addition to frequency). TRUE by default.
ret_corr_only	return the corrected mrs_data object only.
zero_freq_shift_t0	perform a linear fit to the frequency shifts and set the (linearly modeled) shift to be 0 Hz for the first dynamic scan.
list_mean_ref	if ref is not specified and a list is provided, use the list mean scan as reference. Otherwise use the mean of each list element as its own reference.
remove_freq_outliers	remove dynamics based on their frequency shift.
freq_outlier_thresh	threshold to remove frequency outliers.
remove_phase_outliers	remove dynamics based on their phase shift.
phase_outlier_thresh	threshold to remove phase outliers.
remove_amp_outliers	remove dynamics based on their amplitude change.
amp_outlier_thresh	threshold to remove amplitude outliers.

Value

a list containing the corrected data; phase and shift values in units of degrees and Hz respectively.

Re.mrs_data	<i>Apply Re operator to an MRS dataset.</i>
-------------	---

Description

Apply Re operator to an MRS dataset.

Usage

```
## S3 method for class 'mrs_data'
Re(z)
```

Arguments

z MRS data.

Value

MRS data following Re operator.

read_basis	<i>Read a basis file in LCModel .basis format.</i>
------------	--

Description

Read a basis file in LCModel .basis format.

Usage

```
read_basis(basis_file, ref = def_ref(), sort_basis = TRUE)
```

Arguments

basis_file	path to basis file.
ref	assumed ppm reference value.
sort_basis	sort the basis set based on signal names.

Value

basis object.

read_dkd_moco_log	<i>Read the log from Dinesh's MoCo sLASER sequence.</i>
-------------------	---

Description

Read the log from Dinesh's MoCo sLASER sequence.

Usage

```
read_dkd_moco_log(path, date, end_time)
```

Arguments

path	path to the log file.
date	scan date, eg "01-01-2025".
end_time	scan time, eg "14:00".

Value

data.frame of moco parameters.

read_ima_coil_dir	<i>Read a directory containing Siemens MRS IMA files and combine along the coil dimension. Note that the coil ID is inferred from the sorted file name and should be checked when consistency is required between two directories.</i>
-------------------	--

Description

Read a directory containing Siemens MRS IMA files and combine along the coil dimension. Note that the coil ID is inferred from the sorted file name and should be checked when consistency is required between two directories.

Usage

```
read_ima_coil_dir(dir, extra = NULL, verbose = FALSE)
```

Arguments

dir	data directory path.
extra	an optional data frame to provide additional variables for use in subsequent analysis steps, eg id or grouping variables.
verbose	output extra information to the console.

Value

mrs_data object.

read_ima_dyn_dir	<i>Read a directory containing Siemens MRS IMA files and combine along the dynamic dimension. Note that the coil ID is inferred from the sorted file name and should be checked when consistency is required.</i>
------------------	---

Description

Read a directory containing Siemens MRS IMA files and combine along the dynamic dimension. Note that the coil ID is inferred from the sorted file name and should be checked when consistency is required.

Usage

```
read_ima_dyn_dir(dir, extra = NULL, verbose = FALSE)
```

Arguments

dir	data directory path.
extra	an optional data frame to provide additional variables for use in subsequent analysis steps, eg id or grouping variables.
verbose	output extra information to the console.

Value

mrs_data object.

read_lcm_coord	<i>Read an LCModel formatted coord file containing fit information.</i>
----------------	---

Description

Read an LCModel formatted coord file containing fit information.

Usage

```
read_lcm_coord(coord_f)
```

Arguments

coord_f	path to the coord file.
---------	-------------------------

Value

list containing a table of fit point and results structure containing signal amplitudes, errors and fitting diagnostics.

read_mrs	<i>Read MRS data from the filesystem.</i>
----------	---

Description

Read MRS data from the filesystem.

Usage

```
read_mrs(
  path,
  format = NULL,
  ft = NULL,
  fs = NULL,
  ref = NULL,
  n_ref_scans = NULL,
  full_fid = FALSE,
  omit_svs_ref_scans = TRUE,
  verbose = FALSE,
  extra = NULL,
  fid_filt_dist = NULL
)
```

Arguments

path	file name or directory containing the MRS data.
format	string describing the data format. Must be one of the following : "spar_sdat", "rda", "dicom", "twix", "pfile", "list_data", "paravis", "dpt", "lcm_raw", "rds", "nifti", "varian", "jmrui_txt". If not specified, the format will be guessed from the filename extension, or will be assumed to be a Siemens ima dynamic data if the path is a directory.
ft	transmitter frequency in Hz (required for list_data format).
fs	sampling frequency in Hz (required for list_data format).
ref	reference value for ppm scale (required for list_data format).
n_ref_scans	override the number of water reference scans detected in the file header (GE p-file only).
full_fid	export all data points, including those before the start of the FID (default = FALSE), TWIX format only.
omit_svs_ref_scans	remove any reference scans sometimes saved in SVS twix data (default = TRUE).
verbose	print data file information (default = FALSE).
extra	an optional data frame to provide additional variables for use in subsequent analysis steps, eg id or grouping variables.
fid_filt_dist	indicate if the data has a distorted FID due to a brick-wall filter being used to downsample the data. Default is to auto detect this from the data, but TRUE or FALSE options can be given to override detection.

Value

MRS data object.

Examples

```
fname <- system.file("extdata", "philips_spar_sdat_WS.SDAT", package = "spant")
mrs_data <- read_mrs(fname)
print(mrs_data)
```

`read_mrs_tqn`*Read MRS data using the TARQUIN software package.*

Description

Read MRS data using the TARQUIN software package.

Usage

```
read_mrs_tqn(fname, fname_ref = NA, format, id = NA, group = NA)
```

Arguments

<code>fname</code>	the filename containing the MRS data.
<code>fname_ref</code>	a second filename containing reference MRS data.
<code>format</code>	format of the MRS data. Can be one of the following: siemens, philips, ge, dcm, dpt, rda, lcm, varian, bruker, jmrui_txt.
<code>id</code>	optional ID string.
<code>group</code>	optional group string.

Value

MRS data object.

Examples

```
fname <- system.file("extdata", "philips_spar_sdat_WS.SDAT", package="spant")
## Not run:
mrs_data <- read_mrs_tqn(fname, format="philips")

## End(Not run)
```

read_pulse_ascii	<i>Read an ASCII formatted pulse file.</i>
------------------	--

Description

Read an ASCII formatted pulse file.

Usage

```
read_pulse_ascii(fname, deg2rad = TRUE)
```

Arguments

fname	ASCII formatted pulse file path.
deg2rad	convert phase values stored in degrees to radians.

Value

pulse waveform and header.

read_pulse_bruker	<i>Read a Bruker formatted pulse file</i>
-------------------	---

Description

Read a Bruker formatted pulse file

Usage

```
read_pulse_bruker(fname)
```

Arguments

fname	Bruker formatted pulse file path.
-------	-----------------------------------

Value

pulse waveform and header.

read_pulse_pta	<i>Read a .pta formatted pulse file compatible with Siemens PulseTool.</i>
----------------	--

Description

Read a .pta formatted pulse file compatible with Siemens PulseTool.

Usage

```
read_pulse_pta(fname)
```

Arguments

fname	pta formatted pulse file path.
-------	--------------------------------

Value

pulse waveform and header.

read_siemens_txt_hdr	<i>Read the text format header found in Siemens IMA and TWIX data files.</i>
----------------------	--

Description

Read the text format header found in Siemens IMA and TWIX data files.

Usage

```
read_siemens_txt_hdr(input, version = "vd", verbose = FALSE, offset = 0)
```

Arguments

input	file name to read or raw data.
version	software version, can be "vb" or "vd".
verbose	print information to the console.
offset	offset to begin searching for the text header.

Value

a list of parameter values

read_tqn_fit	<i>Reader for csv fit results generated by TARQUIN.</i>
--------------	---

Description

Reader for csv fit results generated by TARQUIN.

Usage

```
read_tqn_fit(fit_f)
```

Arguments

fit_f TARQUIN fit file.

Value

A data frame of the fit data points.

Examples

```
## Not run:
fit <- read_tqn_fit(system.file("extdata", "fit.csv", package="spant"))

## End(Not run)
```

read_tqn_result	<i>Reader for csv results generated by TARQUIN.</i>
-----------------	---

Description

Reader for csv results generated by TARQUIN.

Usage

```
read_tqn_result(result_f, remove_rcs = TRUE)
```

Arguments

result_f TARQUIN result file.
remove_rcs omit row, column and slice ids from output.

Value

list of amplitudes, crlbs and diagnostics.

Examples

```
## Not run:
result <- read_tqn_result(system.file("extdata", "result.csv", package="spant"))

## End(Not run)
```

recon_imag	<i>Reconstruct complex time-domain data from the real part of frequency-domain data.</i>
------------	--

Description

Reconstruct complex time-domain data from the real part of frequency-domain data.

Usage

```
recon_imag(mrs_data)
```

Arguments

mrs_data MRS data.

Value

reconstructed MRS data.

recon_imag_vec	<i>Reconstruct complex time-domain data from the real part of frequency-domain data.</i>
----------------	--

Description

Reconstruct complex time-domain data from the real part of frequency-domain data.

Usage

```
recon_imag_vec(data)
```

Arguments

data data points in the frequency domain.

Value

reconstructed signal.

recon_twix_2d_mrsi	<i>Reconstruct 2D MRSI data from a twix file loaded with read_mrs.</i>
--------------------	--

Description

Reconstruct 2D MRSI data from a twix file loaded with read_mrs.

Usage

recon_twix_2d_mrsi(twix_mrs)

Arguments

twix_mrs raw dynamic data.

Value

reconstructed data.

rectangular_mask	<i>Create a rectangular mask stored as a matrix of logical values.</i>
------------------	--

Description

Create a rectangular mask stored as a matrix of logical values.

Usage

rectangular_mask(xN, yN, x0, y0, xw, yw, angle)

Arguments

xN	number of pixels in the x dimension.
yN	number of pixels in the y dimension.
x0	centre of rectangle in the x direction in units of pixels.
y0	centre of rectangle in the y direction in units of pixels.
xw	width in the x direction in units of pixels.
yw	width in the y direction in units of pixels.
angle	angle of rotation in degrees.

Value

logical mask matrix with dimensions fov_yN x fov_xN.

rep_array_dim	<i>Repeat an array over a given dimension.</i>
---------------	--

Description

Repeat an array over a given dimension.

Usage

```
rep_array_dim(x, rep_dim, n)
```

Arguments

x	array.
rep_dim	dimension to extend.
n	number of times to repeat.

Value

extended array.

rep_dyn	<i>Replicate a scan in the dynamic dimension.</i>
---------	---

Description

Replicate a scan in the dynamic dimension.

Usage

```
rep_dyn(mrs_data, times)
```

Arguments

mrs_data	MRS data to be replicated.
times	number of times to replicate.

Value

replicated data object.

rep_mrs	<i>Replicate a scan over a given dimension.</i>
---------	---

Description

Replicate a scan over a given dimension.

Usage

```
rep_mrs(  
  mrs_data,  
  x_rep = 1,  
  y_rep = 1,  
  z_rep = 1,  
  dyn_rep = 1,  
  coil_rep = 1,  
  warn = TRUE  
)
```

Arguments

mrs_data	MRS data to be replicated.
x_rep	number of x replications.
y_rep	number of y replications.
z_rep	number of z replications.
dyn_rep	number of dynamic replications.
coil_rep	number of coil replications.
warn	print a warning when the data dimensions do not change.

Value

replicated data object.

resample_basis	<i>Resample a basis-set to match a mrs_data acquisition.</i>
----------------	--

Description

Resample a basis-set to match a mrs_data acquisition.

Usage

```
resample_basis(basis, mrs_data, ref_freq_match = TRUE)
```

Arguments

basis	the basis to be resampled.
mrs_data	the mrs_data to match the number of data points and sampling frequency.
ref_freq_match	apply a frequency shift to the basis to match the reference frequency (usually 4.65 or 4.68) of the mrs_data.

Value

resampled basis set object.

resample_img	<i>Resample an image to match a target image space.</i>
--------------	---

Description

Resample an image to match a target image space.

Usage

```
resample_img(source, target, interp = 3L)
```

Arguments

source	image data as a nifti object.
target	image data as a nifti object.
interp	interpolation parameter, see niftyreg.linear definition.

Value

resampled image data as a nifti object.

resample_voi	<i>Resample a VOI to match a target image space using nearest-neighbour interpolation.</i>
--------------	--

Description

Resample a VOI to match a target image space using nearest-neighbour interpolation.

Usage

```
resample_voi(voi, mri)
```

Arguments

voi volume data as a nifti object.
mri image data as a nifti object.

Value

volume data as a nifti object.

reslice_to_mrs	<i>Reslice a nifti object to match the orientation of mrs data.</i>
----------------	---

Description

Reslice a nifti object to match the orientation of mrs data.

Usage

```
reslice_to_mrs(mri, mrs, interp = 3L)
```

Arguments

mri nifti object to be resliced.
mrs mrs_data object for the target orientation.
interp interpolation parameter, see niftyreg.linear definition.

Value

resliced imaging data.

reson_table2mrs_data	<i>Generate mrs_data from a table of single Lorentzian resonances.</i>
----------------------	--

Description

Generate mrs_data from a table of single Lorentzian resonances.

Usage

```
reson_table2mrs_data(  
  reson_table,  
  acq_paras = def_acq_paras(),  
  back_extrap_pts = 0  
)
```

Arguments

reson_table as produced by the hsvd function.
acq_paras list of acquisition parameters. See
back_extrap_pts number of data points to back extrapolate [def_acq_paras](#)

Value

mrs_data object.

re_weighting	<i>Apply a weighting to the FID to enhance spectral resolution.</i>
--------------	---

Description

Apply a weighting to the FID to enhance spectral resolution.

Usage

```
re_weighting(mrs_data, re, alpha)
```

Arguments

mrs_data data to be enhanced.
re resolution enhancement factor (rising exponential factor).
alpha alpha factor (Gaussian decay)

Value

resolution enhanced mrs_data.

rm_dyns	<i>Remove a subset of dynamic scans.</i>
---------	--

Description

Remove a subset of dynamic scans.

Usage

```
rm_dyns(mrs_data, subset)
```

Arguments

mrs_data	dynamic MRS data.
subset	vector containing indices to the dynamic scans to be removed.

Value

MRS data without the specified dynamic scans.

scale_amp_legacy	<i>Apply water reference scaling to a fitting results object to yield metabolite quantities in units of "mmol per Kg wet weight".</i>
------------------	---

Description

See the LCModel manual (section 10.2) on water-scaling for details on the assumptions and relevant references. Use this type of concentration scaling to compare fit results with LCModel and TARQUIN defaults. Otherwise scale_amp_molal_pvc is the preferred method. Note, the LCModel manual (section 1.3) states:

Usage

```
scale_amp_legacy(fit_result, ref_data, w_att = 0.7, w_conc = 35880, ...)
```

Arguments

fit_result	a result object generated from fitting.
ref_data	water reference MRS data object.
w_att	water attenuation factor (default = 0.7). Assumes water T2 of 80ms and a TE = 30 ms. $\exp(-30\text{ms} / 80\text{ms}) \sim 0.7$.
w_conc	assumed water concentration (default = 35880). Default value corresponds to typical white matter. Set to 43300 for gray matter, and 55556 for phantom measurements.
...	additional arguments to get_td_amp function.

Details

"Concentrations should be labelled 'mmol per Kg wet weight'. We use the shorter (incorrect) abbreviation mM. The actual mM is the mmol per Kg wet weight multiplied by the specific gravity of the tissue, typically 1.04 in brain."

Value

a fit_result object with a rescaled results table.

scale_amp_molal	<i>Apply water reference scaling to a fitting results object to yield metabolite quantities in millimolar (mM) units (mol / kg of tissue water).</i>
-----------------	--

Description

Note, this function assumes the volume contains a homogeneous voxel, eg pure WM, GM or CSF. Also note that in the case of a homogeneous voxel the relative densities of MR-visible water (eg GM=0.78, WM=0.65, and CSF=0.97) cancel out and don't need to be considered. Use scale_amp_molal_pvc for volumes containing multiple compartments. Details of this method can be found in "Use of tissue water as a concentration reference for proton spectroscopic imaging" by Gasparovic et al MRM 2006 55(6):1219-26.

Usage

```
scale_amp_molal(
  fit_result,
  ref_data,
  te,
  tr,
  water_t1,
  water_t2,
  metab_t1,
  metab_t2,
  ...
)
```

Arguments

fit_result	result object generated from fitting.
ref_data	water reference MRS data object.
te	the MRS TE in seconds.
tr	the MRS TR in seconds.
water_t1	assumed water T1 value.
water_t2	assumed water T2 value.
metab_t1	assumed metabolite T1 value.
metab_t2	assumed metabolite T2 value.
...	additional arguments to get_td_amp function.

Value

A fit_result object with a rescaled results table.

scale_amp_molal_pvc	<i>Apply water reference scaling to a fitting results object to yield metabolite quantities in millimolar (mM) units (mol / kg of tissue water).</i>
---------------------	--

Description

Details of this method can be found in "Use of tissue water as a concentration reference for proton spectroscopic imaging" by Gasparovic et al MRM 2006 55(6):1219-26. 1.5 Tesla relaxation assumptions are taken from this paper. For 3 Tesla data, relaxation assumptions are taken from "NMR relaxation times in the human brain at 3.0 Tesla" by Wansapura et al J Magn Reson Imaging 1999 9(4):531-8.

Usage

```
scale_amp_molal_pvc(fit_result, ref_data, p_vols, te, tr, ...)
```

Arguments

fit_result	result object generated from fitting.
ref_data	water reference MRS data object.
p_vols	a numeric vector of partial volumes expressed as percentages. For example, a voxel containing 100% white matter tissue would use : p_vols = c(WM = 100, GM = 0, CSF = 0).
te	the MRS TE in seconds.
tr	the MRS TR in seconds.
...	additional arguments to get_td_amp function.

Value

A fit_result object with a rescaled results table.

scale_amp_molar	<i>Apply water reference scaling to a fitting results object to yield metabolite quantities in millimolar (mM) units (mol / Litre of tissue). This function is depreciated, please use scale_amp_legacy instead.</i>
-----------------	--

Description

See the LCModel manual (section 10.2) on water-scaling for details on the assumptions and relevant references. Use this type of concentration scaling to compare fit results with LCModel and TARQUIN defaults. Otherwise scale_amp_molal_pvc is generally the preferred method.

Usage

```
scale_amp_molar(fit_result, ref_data, w_att = 0.7, w_conc = 35880, ...)
```

Arguments

<code>fit_result</code>	a result object generated from fitting.
<code>ref_data</code>	water reference MRS data object.
<code>w_att</code>	water attenuation factor (default = 0.7). Assumes water T2 of 80ms and a TE = 30 ms. $\exp(-30\text{ms} / 80\text{ms}) \sim 0.7$.
<code>w_conc</code>	assumed water concentration (default = 35880). Default value corresponds to typical white matter. Set to 43300 for gray matter, and 55556 for phantom measurements.
<code>...</code>	additional arguments to <code>get_td_amp</code> function.

Value

a `fit_result` object with a rescaled results table.

`scale_amp_molar2molal_pvc`

Convert default LCM/TARQUIN concentration scaling to molal units with partial volume correction.

Description

Convert default LCM/TARQUIN concentration scaling to molal units with partial volume correction.

Usage

```
scale_amp_molar2molal_pvc(fit_result, p_vols, te, tr)
```

Arguments

<code>fit_result</code>	a <code>fit_result</code> object to apply partial volume correction.
<code>p_vols</code>	a numeric vector of partial volumes expressed as percentages. For example, a voxel containing 100% white matter tissue would use : <code>p_vols = c(WM = 100, GM = 0, CSF = 0)</code> .
<code>te</code>	the MRS TE.
<code>tr</code>	the MRS TR.

Value

a `fit_result` object with a rescaled results table.

scale_amp_ratio	<i>Scale fitted amplitudes to a ratio of signal amplitude.</i>
-----------------	--

Description

Scale fitted amplitudes to a ratio of signal amplitude.

Usage

```
scale_amp_ratio(fit_result, name, use_mean_value = FALSE)
```

Arguments

- fit_result a result object generated from fitting.
- name the signal name to use as a denominator (usually, "tCr" or "tNAA").
- use_mean_value scales the result by the mean of the signal when set to TRUE.

Value

a fit_result object with a rescaled results table.

scale_amp_ratio_value	<i>Scale fitted amplitudes to a ratio of signal amplitude.</i>
-----------------------	--

Description

Scale fitted amplitudes to a ratio of signal amplitude.

Usage

```
scale_amp_ratio_value(fit_result, value)
```

Arguments

- fit_result a result object generated from fitting.
- value the number use as a denominator.

Value

a fit_result object with a rescaled results table.

scale_amp_water_ratio	<i>Scale metabolite amplitudes as a ratio to the unsuppressed water amplitude.</i>
-----------------------	--

Description

Scale metabolite amplitudes as a ratio to the unsuppressed water amplitude.

Usage

```
scale_amp_water_ratio(fit_result, ref_data, ...)
```

Arguments

fit_result	a result object generated from fitting.
ref_data	a water reference MRS data object.
...	additional arguments to get_td_amp function.

Value

a fit_result object with a rescaled results table.

scale_basis_amp	<i>Scale a basis object by a scalar.</i>
-----------------	--

Description

Scale a basis object by a scalar.

Usage

```
scale_basis_amp(basis, amp)
```

Arguments

basis	basis_set object to be scaled.
amp	multiplicative factor with length 1.

Value

basis_set object multiplied by the amplitude scale factor.

scale_basis_from_singlet

Scale a basis-set to be consistent with spant assumptions for water scaling.

Description

For correct water scaling, spant assumes the time-domain amplitude ($t = 0$) for a single proton is 0.5. Internally simulated basis-sets will be correctly scaled, however imported basis-sets should be assumed to be un-scaled and this function should be used. Note that the singlet specified should only contain one resonance, and that any additional signals (eg TSP or residual water) will result in incorrect scaling. Therefore, only simulated basis sets are appropriate for use with this function.

Usage

```
scale_basis_from_singlet(basis, name, protons)
```

Arguments

basis	basis set to be scaled.
name	the name of the singlet to be used as a scaling reference.
protons	the number of MRS visible protons contributing to the singlet resonance.

Value

a scaled basis.

scale_mrs_amp

Scale an mrs_data object by a scalar or vector or amplitudes.

Description

Scale an mrs_data object by a scalar or vector or amplitudes.

Usage

```
scale_mrs_amp(mrs_data, amp)
```

Arguments

mrs_data	data to be scaled.
amp	multiplicative factor, must have length equal to 1 or Nspec(mrs_data).

Value

mrs_data object multiplied by the amplitude scale factor.

scale_spec	<i>Scale mrs_data to a spectral region.</i>
------------	---

Description

Scale mrs_data to a spectral region.

Usage

```
scale_spec(
  mrs_data,
  xlim = NULL,
  operator = "sum",
  freq_scale = "ppm",
  mode = "re",
  mean_dyns = NULL,
  ret_scale_factor = FALSE
)
```

Arguments

mrs_data	MRS data.
xlim	spectral range to be integrated (defaults to full range).
operator	can be "sum" (default), "mean", "l2", "max", "min" or "max-min".
freq_scale	units of xlim, can be : "ppm", "Hz" or "points".
mode	spectral mode, can be : "re", "im", "mod" or "cplx".
mean_dyns	mean the dynamic scans before applying the operator. The same scaling value will be applied to each individual dynamic.
ret_scale_factor	option to return the scaling factor in addition to the scaled data.

Value

normalised data.

sd.list	<i>Calculate the standard deviation spectrum from an mrs_data object.</i>
---------	---

Description

Calculate the standard deviation spectrum from an mrs_data object.

Usage

```
## S3 method for class 'list'  
sd(x, na.rm = FALSE)  
  
sd(x, na.rm)
```

Arguments

x	object of class mrs_data.
na.rm	remove NA values.

Value

sd mrs_data object.

sd.mrs_data	<i>Calculate the standard deviation spectrum from an mrs_data object.</i>
-------------	---

Description

Calculate the standard deviation spectrum from an mrs_data object.

Usage

```
## S3 method for class 'mrs_data'  
sd(x, na.rm = FALSE)
```

Arguments

x	object of class mrs_data.
na.rm	remove NA values.

Value

sd mrs_data object.

seconds	<i>Return a time scale vector to match the FID of an MRS data object.</i>
---------	---

Description

Return a time scale vector to match the FID of an MRS data object.

Usage

```
seconds(mrs_data)
```

Arguments

mrs_data	MRS data.
----------	-----------

Value

time scale vector in units of seconds.

segment_t1_fsl	<i>Segment T1 weighted MRI data using FSL FAST and write to file. Runs deface and bet as preprocessing steps by default.</i>
----------------	--

Description

This function requires a working installation of FSL and uses the fslr package. You may need to specify the fsl install directory, eg: 'options(fsl.path = "/path/to/fsl")'

Usage

```
segment_t1_fsl(mri_path, deface = FALSE, bet_fit = 0.5)
```

Arguments

mri_path	path to the volumetric T1 data.
deface	deface the input T1 data before analysis. Defaults to FALSE.
bet_fit	fractional intensity threshold for bet brain extraction. Values should be between 0 and 1. Defaults to 0.5 with smaller values giving larger brain estimates.

seq_cpmg_ideal	<i>CPMG style sequence with ideal pulses.</i>
----------------	---

Description

CPMG style sequence with ideal pulses.

Usage

```
seq_cpmg_ideal(spin_params, ft, ref, TE = 0.03, echoes = 4)
```

Arguments

spin_params	spin system definition.
ft	transmitter frequency in Hz.
ref	reference value for ppm scale.
TE	echo time in seconds.
echoes	number of echoes.

Value

list of resonance amplitudes and frequencies.

seq_mega_press_ideal	<i>MEGA-PRESS sequence with ideal localisation pulses and Gaussian shaped editing pulse.</i>
----------------------	--

Description

MEGA-PRESS sequence with ideal localisation pulses and Gaussian shaped editing pulse.

Usage

```
seq_mega_press_ideal(
  spin_params,
  ft,
  ref,
  ed_freq = 1.89,
  TE1 = 0.015,
  TE2 = 0.053,
  BW = 110,
  steps = 50
)
```

Arguments

spin_params	spin system definition.
ft	transmitter frequency in Hz.
ref	reference value for ppm scale.
ed_freq	editing pulse frequency in ppm.
TE1	TE1 sequence parameter in seconds (TE=TE1+TE2).
TE2	TE2 sequence parameter in seconds.
BW	editing pulse bandwidth in Hz.
steps	number of hard pulses used to approximate the editing pulse.

Value

list of resonance amplitudes and frequencies.

seq_press_2d_shaped *PRESS sequence with shaped refocusing pulses.*

Description

PRESS sequence with shaped refocusing pulses.

Usage

```
seq_press_2d_shaped(
  spin_params,
  ft,
  ref,
  TE1 = 0.01,
  TE2 = 0.02,
  pulse_file,
  pulse_dur,
  pulse_file_format,
  refoc_flip_angle = 180,
  xy_pulse_ppm = NULL,
  resamp = TRUE,
  fs_resamp = 1e-04
)
```

Arguments

spin_params	spin system definition.
ft	transmitter frequency in Hz.
ref	reference value for ppm scale.
TE1	TE1 sequence parameter in seconds (TE=TE1+TE2).

TE2	TE2 sequence parameter in seconds.
pulse_file	path to refocusing pulse file.
pulse_dur	refocusing pulse duration.
pulse_file_format	file format for the refocusing pulse.
refoc_flip_angle	refocusing pulse flip angle in degrees (defaults to 180).
xy_pulse_ppm	a vector of ppm values for the offset of each sub-simulation.
resamp	option to resample the pulse shape.
fs_resamp	sampling frequency (Hz) to resample.

Value

list of resonance amplitudes and frequencies.

seq_press_ideal	<i>PRESS sequence with ideal pulses.</i>
-----------------	--

Description

PRESS sequence with ideal pulses.

Usage

seq_press_ideal(spin_params, ft, ref, TE1 = 0.01, TE2 = 0.02)

Arguments

spin_params	spin system definition.
ft	transmitter frequency in Hz.
ref	reference value for ppm scale.
TE1	TE1 sequence parameter in seconds (TE=TE1+TE2).
TE2	TE2 sequence parameter in seconds.

Value

list of resonance amplitudes and frequencies.

seq_pulse_acquire	<i>Simple pulse and acquire sequence with ideal pulses.</i>
-------------------	---

Description

Simple pulse and acquire sequence with ideal pulses.

Usage

```
seq_pulse_acquire(spin_params, ft, ref, nuc = "1H", acq_delay = 0)
```

Arguments

spin_params	spin system definition.
ft	transmitter frequency in Hz.
ref	reference value for ppm scale.
nuc	acquisition nucleus.
acq_delay	delay between excitation and acquisition.

Value

list of resonance amplitudes and frequencies.

seq_slaser_ideal	<i>sLASER sequence with ideal pulses.</i>
------------------	---

Description

sLASER sequence with ideal pulses.

Usage

```
seq_slaser_ideal(spin_params, ft, ref, TE1 = 0.008, TE2 = 0.011, TE3 = 0.009)
```

Arguments

spin_params	spin system definition.
ft	transmitter frequency in Hz.
ref	reference value for ppm scale.
TE1	first echo time (between exc. and 1st echo) in seconds.
TE2	second echo time (between 2nd echo and 4th echo) in seconds.
TE3	third echo time (between 4th echo and 5th echo) in seconds.

Value

list of resonance amplitudes and frequencies.

seq_spin_echo_ideal	<i>Spin echo sequence with ideal pulses.</i>
---------------------	--

Description

Spin echo sequence with ideal pulses.

Usage

```
seq_spin_echo_ideal(spin_params, ft, ref, nuc = "1H", TE = 0.03)
```

Arguments

spin_params	spin system definition.
ft	transmitter frequency in Hz.
ref	reference value for ppm scale.
nuc	acquisition nucleus.
TE	echo time in seconds.

Value

list of resonance amplitudes and frequencies.

seq_steam_ideal	<i>STEAM sequence with ideal pulses.</i>
-----------------	--

Description

STEAM sequence with ideal pulses.

Usage

```
seq_steam_ideal(spin_params, ft, ref, TE = 0.03, TM = 0.02, amp_scale = 2)
```

Arguments

spin_params	spin system definition.
ft	transmitter frequency in Hz.
ref	reference value for ppm scale.
TE	sequence parameter in seconds.
TM	sequence parameter in seconds.
amp_scale	amplitude scaling factor. Set to 2 (default) to ensure correct scaling for water reference scaling. Set to 1 to maintain the inherent loss of signal associated with STEAM.

Value

list of resonance amplitudes and frequencies.

seq_steam_ideal_cof	<i>STEAM sequence with ideal pulses and coherence order filtering to simulate gradient crushers.</i>
---------------------	--

Description

See Landheer et al NMR Biomed 2021 34(5):e4129 and Landheer et al MRM 2019 Apr;81(4):2209-2222 for more details on the coherence order filtering method.

Usage

```
seq_steam_ideal_cof(spin_params, ft, ref, TE = 0.03, TM = 0.02, amp_scale = 2)
```

Arguments

spin_params	spin system definition.
ft	transmitter frequency in Hz.
ref	reference value for ppm scale.
TE	sequence parameter in seconds.
TM	sequence parameter in seconds.
amp_scale	amplitude scaling factor. Set to 2 (default) to ensure correct scaling for water reference scaling. Set to 1 to maintain the inherent loss of signal associated with STEAM.

Value

list of resonance amplitudes and frequencies.

seq_steam_ideal_young	<i>STEAM sequence with ideal pulses using the z-rotation gradient simulation method described by Young et al JMR 140, 146-152 (1999).</i>
-----------------------	---

Description

STEAM sequence with ideal pulses using the z-rotation gradient simulation method described by Young et al JMR 140, 146-152 (1999).

Usage

```
seq_steam_ideal_young(  
    spin_params,  
    ft,  
    ref,  
    TE = 0.03,  
    TM = 0.02,  
    amp_scale = 2  
)
```

Arguments

spin_params	spin system definition.
ft	transmitter frequency in Hz.
ref	reference value for ppm scale.
TE	sequence parameter in seconds.
TM	sequence parameter in seconds.
amp_scale	amplitude scaling factor. Set to 2 (default) to ensure correct scaling for water reference scaling. Set to 1 to maintain the inherent loss of signal associated with STEAM.

Value

list of resonance amplitudes and frequencies.

set_def_acq_params	<i>Set the default acquisition parameters.</i>
--------------------	--

Description

Set the default acquisition parameters.

Usage

```
set_def_acq_params(  
    ft = getOption("spant.def_ft"),  
    fs = getOption("spant.def_fs"),  
    N = getOption("spant.def_N"),  
    ref = getOption("spant.def_ref"),  
    nuc = getOption("spant.nuc")  
)
```

Arguments

ft	transmitter frequency in Hz.
fs	sampling frequency in Hz.
N	number of data points in the spectral dimension.
ref	reference value for ppm scale.
nuc	resonant nucleus.

set_lcm_cmd	<i>Set the command to run the LCModel command-line program.</i>
-------------	---

Description

Set the command to run the LCModel command-line program.

Usage

```
set_lcm_cmd(cmd)
```

Arguments

cmd	path to binary.
-----	-----------------

set_lw	<i>Apply line-broadening to an mrs_data object to achieve a specified linewidth.</i>
--------	--

Description

Apply line-broadening to an mrs_data object to achieve a specified linewidth.

Usage

```
set_lw(mrs_data, lw, xlim = c(4, 0.5), lg = 1, mask_narrow = TRUE)
```

Arguments

mrs_data	data in.
lw	target linewidth in units of ppm.
xlim	region to search for peaks to obtain a linewidth estimate.
lg	Lorentz-Gauss lineshape parameter.
mask_narrow	masks spectra where the requested linewidth is too narrow, if set FALSE the spectra are not changed.

Value

line-broadened data.

set_mask_xy_mat	<i>Set the masked voxels in a 2D MRSI dataset to given spectrum.</i>
-----------------	--

Description

Set the masked voxels in a 2D MRSI dataset to given spectrum.

Usage

```
set_mask_xy_mat(mrs_data, mask, mask_mrs_data)
```

Arguments

- mrs_data MRSI data object.
- mask matrix of boolean values specifying the voxels to set, where a value of TRUE indicates the voxel should be set to mask_mrs_data.
- mask_mrs_data the spectral data to be assigned to the masked voxels.

Value

updated dataset.

set_Ntrans	<i>Set the number of transients for an mrs_data object.</i>
------------	---

Description

Set the number of transients for an mrs_data object.

Usage

```
set_Ntrans(mrs_data, n_trans)
```

Arguments

- mrs_data MRS data.
- n_trans number of acquired transients.

set_precomp_mode	<i>Set the precompute mode.</i>
------------------	---------------------------------

Description

Set the precompute mode.

Usage

```
set_precomp_mode(mode = NA)
```

Arguments

mode	can be one of: "default", "overwrite", "clean" or "disabled".
------	---

set_precomp_verbose	<i>Set the verbosity of the precompute function.</i>
---------------------	--

Description

Set the verbosity of the precompute function.

Usage

```
set_precomp_verbose(verbose = NA)
```

Arguments

verbose	can be TRUE or FALSE.
---------	-----------------------

set_ref	<i>Set the ppm reference value (eg ppm value at 0Hz).</i>
---------	---

Description

Set the ppm reference value (eg ppm value at 0Hz).

Usage

```
set_ref(mrs_data, ref)
```

Arguments

mrs_data	MRS data.
ref	reference value for ppm scale.

set_td_pts	<i>Set the number of time-domain data points, truncating or zero-filling as appropriate.</i>
------------	--

Description

Set the number of time-domain data points, truncating or zero-filling as appropriate.

Usage

```
set_td_pts(mrs_data, pts)
```

Arguments

mrs_data	MRS data.
pts	number of data points.

Value

MRS data with pts data points.

set_tqn_cmd	<i>Set the command to run the TARQUIN command-line program.</i>
-------------	---

Description

Set the command to run the TARQUIN command-line program.

Usage

```
set_tqn_cmd(cmd)
```

Arguments

cmd	path to binary.
-----	-----------------

set_tr	<i>Set the repetition time of an MRS dataset.</i>
--------	---

Description

Set the repetition time of an MRS dataset.

Usage

```
set_tr(mrs_data, tr)
```

Arguments

mrs_data	MRS data.
tr	repetition time in seconds.

Value

updated mrs_data set.

shift	<i>Apply a frequency shift to MRS data.</i>
-------	---

Description

Apply a frequency shift to MRS data.

Usage

```
shift(mrs_data, shift, units = "ppm")
```

Arguments

mrs_data	MRS data.
shift	frequency shift (in ppm by default).
units	of the shift ("ppm" or "hz").

Value

frequency shifted MRS data.

shift_basis	<i>Apply frequency shifts to basis set signals.</i>
-------------	---

Description

Apply frequency shifts to basis set signals.

Usage

```
shift_basis(basis, shifts)
```

Arguments

basis	the basis to apply the shift to.
shifts	a vector of frequency shifts to apply in ppm units. Must be the same length as there are basis elements, or one value to be applied to all elements.

Value

modified basis set object.

sim_basis	<i>Simulate a basis set object.</i>
-----------	-------------------------------------

Description

Simulate a basis set object.

Usage

```
sim_basis(  
  mol_list,  
  pul_seq = seq_pulse_acquire,  
  acq_paras = def_acq_paras(),  
  xlim = NULL,  
  auto_scale = FALSE,  
  use_basis_cache = FALSE,  
  verbose = FALSE,  
  ...  
)
```

Arguments

mol_list	list of mol_parameter objects. Alternatively, a character vector matching molecules may also be provided. Use the get_mol_names function for a full list of molecules.
pul_seq	pulse sequence function to use.
acq_paras	list of acquisition parameters or an mrs_data object. See def_acq_paras
xlim	ppm range limiting signals to be simulated.
auto_scale	scale the basis based on the intensity of a singlet resonance. Needed for sequences with spatial simulation.
use_basis_cache	create and use a cache of simulated basis sets stored in the "spant_basis_cache" folder in the users home directory. Defaults to FALSE.
verbose	output simulation progress and timings.
...	extra parameters to pass to the pulse sequence function.

Value

basis object.

sim_basis_1h_brain	<i>Simulate a basis-set suitable for 1H brain MRS analysis acquired with a PRESS sequence. Note, ideal pulses are assumed.</i>
--------------------	--

Description

Simulate a basis-set suitable for 1H brain MRS analysis acquired with a PRESS sequence. Note, ideal pulses are assumed.

Usage

```
sim_basis_1h_brain(
  pul_seq = seq_press_ideal,
  acq_paras = def_acq_paras(),
  xlim = c(0.5, 4.2),
  lcm_compat = FALSE,
  ...
)
```

Arguments

pul_seq	pulse sequence function to use.
acq_paras	list of acquisition parameters or an mrs_data object. See def_acq_paras .
xlim	range of frequencies to simulate in ppm.
lcm_compat	exclude lipid and MM signals for use with default LCModel options.
...	extra parameters to pass to the pulse sequence function.

Value

basis object.

sim_basis_1h_brain_press

Simulate a basis-set suitable for 1H brain MRS analysis acquired with a PRESS sequence. Note, ideal pulses are assumed.

Description

Simulate a basis-set suitable for 1H brain MRS analysis acquired with a PRESS sequence. Note, ideal pulses are assumed.

Usage

```
sim_basis_1h_brain_press(  
  acq_paras = def_acq_paras(),  
  xlim = c(0.5, 4.2),  
  lcm_compat = FALSE,  
  TE1 = 0.01,  
  TE2 = 0.02  
)
```

Arguments

acq_paras	list of acquisition parameters or an mrs_data object. See def_acq_paras
xlim	range of frequencies to simulate in ppm.
lcm_compat	exclude lipid and MM signals for use with default LCModel options.
TE1	TE1 of PRESS sequence (TE = TE1 + TE2).
TE2	TE2 of PRESS sequence.

Value

basis object.

sim_basis_mm_lip_lcm	<i>Simulate a macromolecular and lipid basis-set suitable for 1H brain MRS analysis.</i>
----------------------	--

Description

Simulate a macromolecular and lipid basis-set suitable for 1H brain MRS analysis.

Usage

```
sim_basis_mm_lip_lcm(acq_paras = def_acq_paras())
```

Arguments

acq_paras list of acquisition parameters or an mrs_data object. See [def_acq_paras](#)

Value

basis object.

sim_basis_tqn	<i>Simulate a basis file using TARQUIN.</i>
---------------	---

Description

Simulate a basis file using TARQUIN.

Usage

```
sim_basis_tqn(  
  fs = def_fs(),  
  ft = def_ft(),  
  N = def_N(),  
  ref = def_ref(),  
  opts = NULL  
)
```

Arguments

fs	sampling frequency
ft	transmitter frequency
N	number of data points
ref	chemical shift reference
opts	list of options to pass to TARQUIN.

Examples

```
## Not run:
write_basis_tqn('test.basis',mrs_data,c("--echo","0.04"))

## End(Not run)
```

sim_brain_1h	<i>Simulate MRS data with a similar appearance to normal brain (by default).</i>
--------------	--

Description

Simulate MRS data with a similar appearance to normal brain (by default).

Usage

```
sim_brain_1h(
  acq_paras = def_acq_paras(),
  type = "normal_v2",
  pul_seq = seq_slaser_ideal,
  xlim = c(0.5, 4.2),
  full_output = FALSE,
  amps = NULL,
  basis_lb = NULL,
  zero_lip_mm = FALSE,
  remove_lip_mm = FALSE,
  ...
)
```

Arguments

acq_paras	list of acquisition parameters or an mrs_data object. See def_acq_paras .
type	type of spectrum, only "normal" is implemented currently.
pul_seq	pulse sequence function to use.
xlim	range of frequencies to simulate in ppm.
full_output	when FALSE (default) only output the simulated MRS data. When TRUE output a list containing the MRS data, basis set object and corresponding amplitudes.
amps	a vector of basis amplitudes may be specified to modify the output spectrum.
basis_lb	apply additional Gaussian line-broadening to the basis (Hz).
zero_lip_mm	zero the amplitudes of any lipid or macromolecular components based on their name starting with "MM" or "Lip".
remove_lip_mm	remove any lipid or macromolecular basis components based on their name starting with "MM" or "Lip".
...	extra parameters to pass to the pulse sequence function.

Value

see full_output option.

sim_mol	<i>Simulate a mol_parameter object.</i>
---------	---

Description

Simulate a mol_parameter object.

Usage

```
sim_mol(  
    mol,  
    pul_seq = seq_pulse_acquire,  
    ft = def_ft(),  
    ref = def_ref(),  
    fs = def_fs(),  
    N = def_N(),  
    xlim = NULL,  
    ...  
)
```

Arguments

mol	mol_parameter object.
pul_seq	pulse sequence function to use.
ft	transmitter frequency in Hz.
ref	reference value for ppm scale.
fs	sampling frequency in Hz.
N	number of data points in the spectral dimension.
xlim	ppm range limiting signals to be simulated.
...	extra parameters to pass to the pulse sequence function.

Value

mrs_data object.

sim_noise	<i>Simulate an mrs_data object containing simulated Gaussian noise.</i>
-----------	---

Description

Simulate an mrs_data object containing simulated Gaussian noise.

Usage

```
sim_noise(  
  sd = 0.1,  
  fs = def_fs(),  
  ft = def_ft(),  
  N = def_N(),  
  ref = def_ref(),  
  nuc = def_nuc(),  
  dyns = 1,  
  fd = TRUE  
)
```

Arguments

sd	standard deviation of the noise.
fs	sampling frequency in Hz.
ft	transmitter frequency in Hz.
N	number of data points in the spectral dimension.
ref	reference value for ppm scale.
nuc	resonant nucleus.
dyns	number of dynamic scans to generate.
fd	return data in the frequency-domain (TRUE) or time-domain (FALSE)

Value

mrs_data object.

sim_resonances	<i>Simulate a MRS data object containing a set of simulated resonances.</i>
----------------	---

Description

Simulate a MRS data object containing a set of simulated resonances.

Usage

```
sim_resonances(  
  freq = 0,  
  amp = 1,  
  lw = 0,  
  lg = 0,  
  phase = 0,  
  freq_ppm = TRUE,  
  acq_paras = def_acq_paras(),  
  fp_scale = TRUE,  
  back_extrap_pts = 0,  
  sum_resonances = TRUE  
)
```

Arguments

freq	resonance frequency.
amp	resonance amplitude.
lw	line width in Hz.
lg	Lorentz-Gauss lineshape parameter (between 0 and 1).
phase	phase in degrees.
freq_ppm	frequencies are given in ppm units if set to TRUE, otherwise Hz are assumed.
acq_paras	list of acquisition parameters. See def_acq_paras
fp_scale	multiply the first data point by 0.5.
back_extrap_pts	number of data points to back extrapolate.
sum_resonances	sum all resonances (default is TRUE), otherwise return a dynamic mrs_data object.

Value

MRS data object.

Examples

```
sim_data <- sim_resonances(freq = 2, lw = 5)
```

sim_th_excit_profile	<i>Simulate an ideal pulse excitation profile by smoothing a top-hat function with a Gaussian.</i>
----------------------	--

Description

Simulate an ideal pulse excitation profile by smoothing a top-hat function with a Gaussian.

Usage

```
sim_th_excit_profile(bw = 1500, sigma = 50, fa = 180)
```

Arguments

bw	top-hat bandwidth (Hz).
sigma	Gaussian width smoothing parameter (Hz).
fa	intended flip angle of the pulse.

Value

data frame containing the frequency scale, excitation profile and corresponding flip-angles.

sim_zero	<i>Simulate an mrs_data object containing complex zero valued samples.</i>
----------	--

Description

Simulate an mrs_data object containing complex zero valued samples.

Usage

```
sim_zero(
  fs = def_fs(),
  ft = def_ft(),
  N = def_N(),
  ref = def_ref(),
  nuc = def_nuc(),
  dyns = 1
)
```

Arguments

fs	sampling frequency in Hz.
ft	transmitter frequency in Hz.
N	number of data points in the spectral dimension.
ref	reference value for ppm scale.
nuc	resonant nucleus.
dyns	number of dynamic scans to generate.

Value

mrs_data object.

smooth_dyns	<i>Smooth data across the dynamic dimension with a Gaussian kernel.</i>
-------------	---

Description

Smooth data across the dynamic dimension with a Gaussian kernel.

Usage

```
smooth_dyns(mrs_data, sigma)
```

Arguments

mrs_data	data to be smoothed.
sigma	standard deviation of the underlying Gaussian kernel in seconds.

Value

smoothed mrs_data object.

sort_basis	Sort the basis-set elements alphabetically.
------------	---

Description

Sort the basis-set elements alphabetically.

Usage

```
sort_basis(basis)
```

Arguments

basis	input basis.
-------	--------------

Value

sorted basis.

spant_abfit_benchmark	Simulate and fit some spectra with ABfit for benchmarking purposes. Basic timing and performance metrics will be printed.
-----------------------	--

Description

Simulate and fit some spectra with ABfit for benchmarking purposes. Basic timing and performance metrics will be printed.

Usage

```
spant_abfit_benchmark(noise_reps = 10, return_res = FALSE, opts = abfit_opts())
```

Arguments

noise_reps	number of spectra to fit with differing noise samples.
return_res	return a list of fit_result objects.
opts	ABfit options structure.

`spant_simulation_benchmark`

Simulate a typical metabolite basis set for benchmarking. Timing metrics will be printed on completion.

Description

Simulate a typical metabolite basis set for benchmarking. Timing metrics will be printed on completion.

Usage

```
spant_simulation_benchmark(sim_reps = 10, N = 1024)
```

Arguments

<code>sim_reps</code>	number of times to simulate the basis set.
<code>N</code>	number of FID data points to simulate.

`spant_sim_fmrs_dataset`

Simulate an example fMRS dataset for a block design fMRS experiment and export a BIDS structure.

Description

Simulate an example fMRS dataset for a block design fMRS experiment and export a BIDS structure.

Usage

```
spant_sim_fmrs_dataset(output_dir = NULL)
```

Arguments

<code>output_dir</code>	output directory for the BIDS data. Defaults to : "HOME/sim_fmrs_dataset/data".
-------------------------	---

spec_decomp	<i>Decompose an mrs_data object into white and gray matter spectra.</i>
-------------	---

Description

An implementation of the method published by Goryawala et al MRM 79(6) 2886-2895 (2018). "Spectral decomposition for resolving partial volume effects in MRSI".

Usage

```
spec_decomp(mrs_data, wm, gm, norm_fractions = TRUE)
```

Arguments

mrs_data	data to be decomposed into white and gray matter spectra.
wm	vector of white matter contributions to each voxel.
gm	vector of gray matter contributions to each voxel.
norm_fractions	option to normalise the wm, gm vectors for each voxel.

Value

a list of two mrs_data objects corresponding to the two tissue types.

spec_op	<i>Perform a mathematical operation on a spectral region.</i>
---------	---

Description

Perform a mathematical operation on a spectral region.

Usage

```
spec_op(
  mrs_data,
  xlim = NULL,
  operator = "sum",
  freq_scale = "ppm",
  mode = "re"
)
```

Arguments

mrs_data	MRS data.
xlim	spectral range to be integrated (defaults to full range).
operator	can be "sum" (default), "mean", "I2", "max", "max_cplx", "min" or "max-min".
freq_scale	units of xlim, can be : "ppm", "hz" or "points".
mode	spectral mode, can be : "re", "im", "mod" or "cplx".

Value

an array of integral values.

spin_sys	<i>Create a spin system object for pulse sequence simulation.</i>
----------	---

Description

Create a spin system object for pulse sequence simulation.

Usage

```
spin_sys(spin_params, ft, ref, precomp_jc_H = NULL, precomp_Iz = NULL)
```

Arguments

spin_params	an object describing the spin system properties.
ft	transmitter frequency in Hz.
ref	reference value for ppm scale.
precomp_jc_H	use a precomputed J-coupling H matrix to save time.
precomp_Iz	use precomputed Iz matrices to save time.

Value

spin system object.

spm_pve2categorical	<i>Convert SPM style segmentation files to a single categorical image where the numerical values map as: 0) Other, 1) CSF, 2) GM and 3) WM.</i>
---------------------	---

Description

Convert SPM style segmentation files to a single categorical image where the numerical values map as: 0) Other, 1) CSF, 2) GM and 3) WM.

Usage

```
spm_pve2categorical(fname)
```

Arguments

fname	any of the segmentation files (eg c1_MY_T1.nii).
-------	--

Value

nifti object.

ssp	<i>Signal space projection method for lipid suppression.</i>
-----	--

Description

Signal space projection method as described in: Tsai SY, Lin YR, Lin HY, Lin FH. Reduction of lipid contamination in MR spectroscopy imaging using signal space projection. Magn Reson Med 2019 Mar;81(3):1486-1498.

Usage

```
ssp(mrs_data, comps = 5, xlim = c(1.5, 0.8))
```

Arguments

mrs_data	MRS data object.
comps	the number of spatial components to use.
xlim	spectral range (in ppm) covering the lipid signals.

Value

lipid suppressed mrs_data object.

stackplot	<i>Produce a plot with multiple traces.</i>
-----------	---

Description

Produce a plot with multiple traces.

Usage

```
stackplot(x, ...)
```

Arguments

x	object for plotting.
...	arguments to be passed to methods.

stackplot.fit_result	<i>Plot the fitting results of an object of class fit_result with individual basis set components shown.</i>
----------------------	--

Description

Plot the fitting results of an object of class `fit_result` with individual basis set components shown.

Usage

```
## S3 method for class 'fit_result'
stackplot(
  x,
  xlim = NULL,
  y_offset = 0,
  dyn = 1,
  x_pos = 1,
  y_pos = 1,
  z_pos = 1,
  coil = 1,
  n = NULL,
  sub_bl = FALSE,
  labels = FALSE,
  label_names = NULL,
  sig_col = "black",
  restore_def_par = TRUE,
  omit_signals = NULL,
  combine_lipmm = FALSE,
  combine_metab = FALSE,
```

```

    mar = NULL,
    show_grid = TRUE,
    grid_nx = NULL,
    grid_ny = NA,
    invert_fit = FALSE,
    ...
)

```

Arguments

x	fit_result object.
xlim	the range of values to display on the x-axis, eg xlim = c(4,1).
y_offset	separate basis signals in the y-axis direction by this value.
dyn	the dynamic index to plot.
x_pos	the x index to plot.
y_pos	the y index to plot.
z_pos	the z index to plot.
coil	the coil element number to plot.
n	single index element to plot (overrides other indices when given).
sub_bl	subtract the baseline from the data and fit (logical).
labels	print signal labels at the right side of the plot.
label_names	provide a character vector of signal names to replace the defaults determined from the basis set.
sig_col	colour of individual signal components.
restore_def_par	restore default plotting par values after the plot has been made.
omit_signals	a character vector of basis signal names to be removed from the plot.
combine_lipmm	combine all basis signals with names starting with "Lip" or "MM".
combine_metab	combine all basis signals with names not starting with "Lip" or "MM".
mar	option to adjust the plot margins. See ?par.
show_grid	plot gridlines behind the data (logical). Defaults to TRUE.
grid_nx	number of cells of the grid in x and y direction. When NULL the grid aligns with the tick marks on the corresponding default axis (i.e., tickmarks as computed by axTicks). When NA, no grid lines are drawn in the corresponding direction.
grid_ny	as above.
invert_fit	show the fit result "upside-down"/
...	further arguments to plot method.

stackplot.mrs_data	<i>Stackplot plotting method for objects of class mrs_data.</i>
--------------------	---

Description

Stackplot plotting method for objects of class mrs_data.

Usage

```
## S3 method for class 'mrs_data'
stackplot(
  x,
  xlim = NULL,
  mode = "re",
  x_units = NULL,
  fd = TRUE,
  col = NULL,
  alpha = NULL,
  x_offset = 0,
  y_offset = 0,
  plot_dim = NULL,
  x_pos = NULL,
  y_pos = NULL,
  z_pos = NULL,
  dyn = 1,
  coil = 1,
  bty = NULL,
  labels = NULL,
  lab_cex = 1,
  bl_lty = NULL,
  restore_def_par = TRUE,
  show_grid = NULL,
  grid_nx = NULL,
  grid_ny = NA,
  lwd = NULL,
  vline = NULL,
  vline_lty = 2,
  vline_col = "red",
  mar = NULL,
  ...
)
```

Arguments

x	object of class mrs_data.
xlim	the range of values to display on the x-axis, eg xlim = c(4,1).

mode	representation of the complex numbers to be plotted, can be one of: "re", "im", "mod" or "arg".
x_units	the units to use for the x-axis, can be one of: "ppm", "hz", "points" or "seconds".
fd	display data in the frequency-domain (default), or time-domain (logical).
col	set the colour of the line, eg col = rgb(1, 0, 0, 0.5).
alpha	set the line transparency, eg alpha = 0.5 is 50% transparency. Overrides any transparency levels set by col.
x_offset	separate plots in the x-axis direction by this value. Default value is 0.
y_offset	separate plots in the y-axis direction by this value.
plot_dim	the dimension to display on the y-axis, can be one of: "dyn", "x", "y", "z", "coil" or NULL. If NULL (the default) all spectra will be collapsed into the dynamic dimension and displayed.
x_pos	the x index to plot.
y_pos	the y index to plot.
z_pos	the z index to plot.
dyn	the dynamic index to plot.
coil	the coil element number to plot.
bty	option to draw a box around the plot. See ?par.
labels	add labels to each data item.
lab_cex	label size.
bl_lty	linetype for the y = 0 baseline trace. A default value NULL results in no baseline being plotted.
restore_def_par	restore default plotting par values after the plot has been made.
show_grid	plot gridlines behind the data (logical). Defaults to TRUE.
grid_nx	number of cells of the grid in x and y direction. When NULL the grid aligns with the tick marks on the corresponding default axis (i.e., tickmarks as computed by axTicks). When NA, no grid lines are drawn in the corresponding direction.
grid_ny	as above.
lwd	plot linewidth.
vline	x-value to draw a vertical line.
vline_lty	linetype for the vertical line.
vline_col	colour for the vertical line.
mar	option to adjust the plot margins. See ?par.
...	other arguments to pass to the matplot method.

sub_first_dyn	<i>Subtract the first dynamic spectrum from a dynamic series.</i>
---------------	---

Description

Subtract the first dynamic spectrum from a dynamic series.

Usage

```
sub_first_dyn(mrs_data, scale = 1)
```

Arguments

mrs_data	dynamic MRS data.
scale	scale factor for the first spectrum.

Value

subtracted data.

sub_mean_dyns	<i>Subtract the mean dynamic spectrum from a dynamic series.</i>
---------------	--

Description

Subtract the mean dynamic spectrum from a dynamic series.

Usage

```
sub_mean_dyns(mrs_data, scale = 1)
```

Arguments

mrs_data	dynamic MRS data.
scale	scale factor for the mean spectrum.

Value

subtracted data.

sub_median_dyns	<i>Subtract the median dynamic spectrum from a dynamic series.</i>
-----------------	--

Description

Subtract the median dynamic spectrum from a dynamic series.

Usage

```
sub_median_dyns(mrs_data, scale = 1)
```

Arguments

mrs_data	dynamic MRS data.
scale	scale factor for the medium spectrum.

Value

subtracted data.

sum_coils	<i>Calculate the sum across receiver coil elements.</i>
-----------	---

Description

Calculate the sum across receiver coil elements.

Usage

```
sum_coils(mrs_data)
```

Arguments

mrs_data	MRS data split across receiver coil elements.
----------	---

Value

sum across coil elements.

sum_dyns	<i>Calculate the sum of data dynamics.</i>
----------	--

Description

Calculate the sum of data dynamics.

Usage

```
sum_dyns(mrs_data)
```

Arguments

mrs_data	dynamic MRS data.
----------	-------------------

Value

sum of data dynamics.

sum_mrs	<i>Sum two mrs_data objects.</i>
---------	----------------------------------

Description

Sum two mrs_data objects.

Usage

```
sum_mrs(a, b, force = FALSE)
```

Arguments

a	first mrs_data object to be summed.
b	second mrs_data object to be summed.
force	set to TRUE to force mrs_data objects to be summed, even if they are in different time/frequency domains.

Value

a + b

sum_mrs_list	<i>Return the sum of a list of mrs_data objects.</i>
--------------	--

Description

Return the sum of a list of mrs_data objects.

Usage

```
sum_mrs_list(mrs_list)
```

Arguments

mrs_list list of mrs_data objects.

Value

sum mrs_data object.

svs_1h_brain_analysis	<i>Standard SVS 1H brain analysis pipeline.</i>
-----------------------	---

Description

Standard SVS 1H brain analysis pipeline.

Usage

```
svs_1h_brain_analysis(
  metab,
  basis = NULL,
  w_ref = NULL,
  mri_seg = NULL,
  mri = NULL,
  output_dir = NULL,
  extra = NULL,
  decimate = NULL,
  rats_corr = TRUE,
  ecc = FALSE,
  comb_dyns = TRUE,
  hsvd_filt = FALSE,
  scale_amps = TRUE,
  te = NULL,
  tr = NULL,
  preproc_only = FALSE,
  method = "ABFIT",
  opts = NULL
)
```

Arguments

metab	filepath or mrs_data object containing MRS metabolite data.
basis	basis set object to use for analysis.
w_ref	filepath or mrs_data object containing MRS water reference data.
mri_seg	filepath or nifti object containing segmented MRI data.
mri	filepath or nifti object containing anatomical MRI data.
output_dir	directory path to output fitting results.
extra	data.frame with one row containing additional information to be attached to the fit results table.
decimate	option to decimate the input data by a factor of two. The default value of NULL does not perform decimation unless the spectral width is greater than 20 PPM.
rats_corr	option to perform rats correction, defaults to TRUE.
ecc	option to perform water reference based eddy current correction, defaults to FALSE.
comb_dyns	option to combine dynamic scans, defaults to TRUE.
hsvd_filt	option to apply hsvd water removal, defaults to FALSE.
scale_amps	option to scale metabolite amplitude estimates, defaults to TRUE.
te	metabolite mrs data echo time in seconds.
tr	metabolite mrs data repetition time in seconds.
preproc_only	only perform the preprocessing steps and omit fitting. The preprocessed metabolite data will be returned in this case.
method	analysis method to use, see fit_mrs help.
opts	options to pass to the analysis method.

Value

a fit_result or mrs_data object depending on the preproc_only option.

svs_1h_brain_analysis_dev

Standard SVS 1H brain analysis pipeline.

Description

Note this function is still under development and liable to changes.

Usage

```
svs_1h_brain_analysis_dev(
  metab,
  w_ref = NULL,
  output_dir = NULL,
  basis = NULL,
  p_vols = NULL,
  append_basis = NULL,
  remove_basis = NULL,
  dfp_corr = FALSE,
  omit_bad_dynamics = FALSE,
  te = NULL,
  tr = NULL,
  output_ratio = "tCr",
  ecc = FALSE,
  abfit_opts = NULL,
  verbose = FALSE
)
```

Arguments

<code>metab</code>	filepath or <code>mrs_data</code> object containing MRS metabolite data.
<code>w_ref</code>	filepath or <code>mrs_data</code> object containing MRS water reference data.
<code>output_dir</code>	directory path to output fitting results.
<code>basis</code>	precompiled basis set object to use for analysis.
<code>p_vols</code>	a numeric vector of partial volumes expressed as percentages. Defaults to 100% white matter. A voxel containing 100% gray matter tissue would use : <code>p_vols = c(WM = 0, GM = 100, CSF = 0)</code> .
<code>append_basis</code>	names of extra signals to add to the default basis. Eg <code>append_basis = c("peth", "cit")</code> . Cannot be used with precompiled basis sets.
<code>remove_basis</code>	names of signals to remove from the basis. Cannot be used with precompiled basis sets.
<code>dfp_corr</code>	perform dynamic frequency and phase correction using the RATS method.
<code>omit_bad_dynamics</code>	detect and remove bad dynamics.
<code>te</code>	metabolite mrs data echo time in seconds. If not supplied this will be guessed from the <code>metab</code> data file.
<code>tr</code>	metabolite mrs data repetition time in seconds. If not supplied this will be guessed from the <code>metab</code> data file.
<code>output_ratio</code>	optional string to specify a metabolite ratio to output. Defaults to "tCr" and multiple metabolites may be specified for multiple outputs. Set as <code>NULL</code> to omit.
<code>ecc</code>	option to perform water reference based eddy current correction, defaults to <code>FALSE</code> .
<code>abfit_opts</code>	options to pass to <code>ABfit</code> .
<code>verbose</code>	output potentially useful information.

Examples

```

metab <- system.file("extdata", "philips_spar_sdat_WS.SDAT",
                     package = "spant")
w_ref <- system.file("extdata", "philips_spar_sdat_W.SDAT",
                     package = "spant")

## Not run:
fit_result <- svs_1h_brain_analysis(metab, w_ref, "fit_res_dir")

## End(Not run)

```

svs_1h_brain_batch_analysis

Batch interface to the standard SVS 1H brain analysis pipeline.

Description

Batch interface to the standard SVS 1H brain analysis pipeline.

Usage

```

svs_1h_brain_batch_analysis(
  metab_list,
  w_ref_list = NULL,
  mri_seg_list = NULL,
  mri_list = NULL,
  output_dir_list = NULL,
  extra = NULL,
  ...
)

```

Arguments

<code>metab_list</code>	list of file paths or <code>mrs_data</code> objects containing MRS metabolite data.
<code>w_ref_list</code>	list of file paths or <code>mrs_data</code> objects containing MRS water reference data.
<code>mri_seg_list</code>	list of file paths or <code>nifti</code> objects containing segmented MRI data.
<code>mri_list</code>	list of file paths or <code>nifti</code> objects containing anatomical MRI data.
<code>output_dir_list</code>	list of directory paths to output fitting results.
<code>extra</code>	a data frame with the same number of rows as <code>metab_list</code> , containing additional information to be attached to the fit results table.
<code>...</code>	additional options to be passed to the <code>svs_1h_brain_analysis</code> function.

Value

a list of `fit_result` objects.

sv_res_table	<i>Output a table of fit amplitudes and error estimates for a single-voxel fit.</i>
--------------	---

Description

Output a table of fit amplitudes and error estimates for a single-voxel fit.

Usage

```
sv_res_table(fit_res, format_out = FALSE)
```

Arguments

fit_res	input vector.
format_out	reduce the accuracy of values to aid table formatting.

Value

data.frame of values.

td2fd	<i>Transform time-domain data to the frequency-domain.</i>
-------	--

Description

Transform time-domain data to the frequency-domain.

Usage

```
td2fd(mrs_data)
```

Arguments

mrs_data	MRS data in time-domain representation.
----------	---

Value

MRS data in frequency-domain representation.

tdsr	<i>Time-domain spectral registration.</i>
------	---

Description

An implementation of the method published by Near et al MRM 73:44-50 (2015).

Usage

```
tdsr(mrs_data, ref = NULL, xlim = c(4, 0.5), max_t = 0.2)
```

Arguments

mrs_data	MRS data to be corrected.
ref	optional MRS data to use as a reference, the mean of all dynamics is used if this argument is not supplied.
xlim	optional frequency range to perform optimisation, set to NULL to use the full range.
max_t	truncate the FID when longer than max_t to reduce time taken.

Value

a list containing the corrected data; phase and shift values in units of degrees and Hz respectively.

td_conv_filt	<i>Time-domain convolution based filter.</i>
--------------	--

Description

Time-domain convolution based filter described by: Marion D, Ikura M, Bax A. Improved solvent suppression in one-dimensional and twodimensional NMR spectra by convolution of time-domain data. J Magn Reson 1989;84:425-430.

Usage

```
td_conv_filt(mrs_data, K = 25, ext = 1)
```

Arguments

mrs_data	MRS data to be filtered.
K	window width in data points.
ext	point separation for linear extrapolation.

te	<i>Return the echo time of an MRS dataset.</i>
----	--

Description

Return the echo time of an MRS dataset.

Usage

te(mrs_data)

Arguments

mrs_data MRS data.

Value

echo time in seconds.

tr	<i>Return the repetition time of an MRS dataset.</i>
----	--

Description

Return the repetition time of an MRS dataset.

Usage

tr(mrs_data)

Arguments

mrs_data MRS data.

Value

repetition time in seconds.

t_test_spec	<i>Perform a t-test on spectral data points.</i>
-------------	--

Description

Perform a t-test on spectral data points.

Usage

```
t_test_spec(mrs_data, group)
```

Arguments

mrs_data	an mrs_data object with spectra in the dynamic dimension.
group	vector describing the group membership of each dynamic spectrum.

Value

a list of statistical results.

varpro_3_para_opts	<i>Return a list of options for VARPRO based fitting with 3 free parameters.</i>
--------------------	--

Description

Return a list of options for VARPRO based fitting with 3 free parameters.

Usage

```
varpro_3_para_opts(
  nstart = 20,
  init_damping = 2,
  maxiters = 200,
  max_shift = 5,
  max_damping = 5,
  anal_jac = FALSE,
  bl_smth_pts = 80
)
```

Arguments

nstart	position in the time-domain to start fitting, units of data points.
init_damping	starting value for the global Gaussian line-broadening term - measured in Hz.
maxiters	maximum number of levmar iterations to perform.
max_shift	maximum global shift allowed, measured in Hz.
max_damping	maximum damping allowed, FWHM measured in Hz.
anal_jac	option to use the analytic or numerical Jacobian (logical).
bl_smth_pts	number of data points to use in the baseline smoothing calculation.

Value

list of options.

varpro_basic_opts	<i>Return a list of options for a basic VARPRO analysis.</i>
-------------------	--

Description

Return a list of options for a basic VARPRO analysis.

Usage

```
varpro_basic_opts(method = "fd_re", nnls = TRUE, ppm_left = 4, ppm_right = 0.2)
```

Arguments

method	one of "td", "fd", "fd_re".
nnls	restrict basis amplitudes to non-negative values.
ppm_left	downfield frequency limit for the fitting range (ppm).
ppm_right	upfield frequency limit for the fitting range (ppm).

Value

full list of options.

varpro_opts	<i>Return a list of options for VARPRO based fitting.</i>
-------------	---

Description

Return a list of options for VARPRO based fitting.

Usage

```
varpro_opts(
  nstart = 20,
  init_g_damping = 2,
  maxiters = 200,
  max_shift = 5,
  max_g_damping = 5,
  max_ind_damping = 5,
  anal_jac = TRUE,
  bl_smth_pts = 80
)
```

Arguments

nstart	position in the time-domain to start fitting, units of data points.
init_g_damping	starting value for the global Gaussian line-broadening term - measured in Hz.
maxiters	maximum number of levmar iterations to perform.
max_shift	maximum shift allowed to each element in the basis set, measured in Hz.
max_g_damping	maximum permitted global Gaussian line-broadening.
max_ind_damping	maximum permitted Lorentzian line-broadening for each element in the basis set, measured in Hz.
anal_jac	option to use the analytic or numerical Jacobian (logical).
bl_smth_pts	number of data points to use in the baseline smoothing calculation.

Value

list of options.

Examples

```
varpro_opts(nstart = 10)
```

vec2mrs_data	<i>Convert a vector into a mrs_data object.</i>
--------------	---

Description

Convert a vector into a mrs_data object.

Usage

```
vec2mrs_data(  
  vec,  
  mrs_data = NULL,  
  fs = NULL,  
  ft = NULL,  
  ref = NULL,  
  nuc = NULL,  
  dyns = 1,  
  fd = FALSE  
)
```

Arguments

vec	the data vector.
mrs_data	example data to copy acquisition parameters from.
fs	sampling frequency in Hz.
ft	transmitter frequency in Hz.
ref	reference value for ppm scale.
nuc	resonant nucleus.
dyns	replicate the data across the dynamic dimension.
fd	flag to indicate if the vector is in the frequency domain (logical).

Value

mrs_data object.

write_basis	<i>Write a basis object to an LCMModel .basis formatted file.</i>
-------------	---

Description

Write a basis object to an LCMModel .basis formatted file.

Usage

```
write_basis(basis, basis_file, fwhmba = 0.1)
```

Arguments

basis	basis object to be exported.
basis_file	path to basis file to be generated.
fwhmba	parameter used by LCMModel.

write_basis_tqn	<i>Generate a basis file using TARQUIN.</i>
-----------------	---

Description

Generate a basis file using TARQUIN.

Usage

```
write_basis_tqn(basis_file, metab_data, opts = NULL)
```

Arguments

basis_file	filename of the basis file to be generated.
metab_data	MRS data object to match the generated basis parameters.
opts	list of options to pass to TARQUIN.

Examples

```
## Not run:  
write_basis_tqn('test.basis',mrs_data,c("--echo","0.04"))  
  
## End(Not run)
```

write_mrs	<i>Write MRS data object to file.</i>
-----------	---------------------------------------

Description

Write MRS data object to file.

Usage

```
write_mrs(mrs_data, fname, format = NULL, force = FALSE)
```

Arguments

mrs_data	object to be written to file, or list of mrs_data objects.
fname	one or more filenames to output.
format	string describing the data format. Must be one of the following : "nifti", "dpt", "lcm_raw", "rds". If not specified, the format will be guessed from the filename extension.
force	set to TRUE to overwrite any existing files.

write_mrs_nifti	<i>Write MRS data object to file in NIFTI format.</i>
-----------------	---

Description

Write MRS data object to file in NIFTI format.

Usage

```
write_mrs_nifti(mrs_data, fname)
```

Arguments

mrs_data	object to be written to file.
fname	the filename of the output NIFTI MRS data.

write_pulse_ascii	<i>Write an ASCII formatted pulse file.</i>
-------------------	---

Description

Write an ASCII formatted pulse file.

Usage

```
write_pulse_ascii(pulse, path)
```

Arguments

pulse	pulse data object.
path	file path for export.

zero_fade_spec	<i>Fade a spectrum to zero by frequency domain multiplication with a tanh function. Note this operation distorts data points at the end of the FID.</i>
----------------	---

Description

Fade a spectrum to zero by frequency domain multiplication with a tanh function. Note this operation distorts data points at the end of the FID.

Usage

```
zero_fade_spec(mrs_data, start_ppm, end_ppm)
```

Arguments

mrs_data	data to be faded.
start_ppm	start point of the fade in ppm units.
end_ppm	end point of the fade in ppm units.

Value

modified mrs_data object.

zero_higher_orders	<i>Zero all coherences including and above a given order.</i>
--------------------	---

Description

Zero all coherences including and above a given order.

Usage

zero_higher_orders(sys, rho, order)

Arguments

- sys spin system object.
- rho density matrix.
- order states higher than or equal to this argument will be set to zero.

Value

density matrix.

zero_td_pts_end	<i>Set mrs_data object data points at the end of the FID to zero.</i>
-----------------	---

Description

Set mrs_data object data points at the end of the FID to zero.

Usage

zero_td_pts_end(mrs_data, pts)

Arguments

- mrs_data MRS data.
- pts number of end points to set to zero.

Value

modified mrs_data object.

zf	<i>Zero-fill MRS data in the time domain.</i>
----	---

Description

Zero-fill MRS data in the time domain.

Usage

```
zf(x, factor = 2, offset = 0)

## S3 method for class 'list'
zf(x, factor = 2, offset = 0)

## S3 method for class 'mrs_data'
zf(x, factor = 2, offset = 0)

## S3 method for class 'basis_set'
zf(x, factor = 2, offset = 0)
```

Arguments

x	input mrs_data or basis_set object.
factor	zero-filling factor, factor of 2 returns a dataset with twice the original data points.
offset	number of points from the end of the FID to insert the zero values.

Value

zero-filled data.

zf_xy	<i>Zero-fill MRSI data in the k-space x-y direction.</i>
-------	--

Description

Zero-fill MRSI data in the k-space x-y direction.

Usage

```
zf_xy(mrs_data, factor = 2)
```

Arguments

mrs_data	MRSI data.
factor	zero-filling factor, a factor of 2 returns a dataset with twice the original points in the x-y directions. Factors smaller than one are permitted, such that a factor of 0.5 returns half the k-space points in the x-y directions.

Value

zero-filled data.

Index

abfit_opts, [11](#), [15](#)
abfit_opts_v1_9_0, [14](#)
abfit_reg_opts, [15](#)
acquire, [19](#)
add_noise, [19](#)
add_noise_spec_snr, [20](#)
align, [20](#)
apodise_xy, [21](#)
append_basis, [22](#)
append_coils, [22](#)
append_dyns, [23](#)
append_regs, [23](#)
apply_axes, [24](#)
apply_mrs, [24](#)
apply_pulse, [25](#)
Arg.mrs_data, [26](#)
array2mrs_data, [26](#)
auto_phase, [27](#)
auto_phase_bl, [28](#)

back_extrap_ar, [28](#)
basis2dyn_mrs_data, [29](#)
basis2mrs_data, [30](#)
bbase, [30](#)
bc_als, [31](#)
bc_constant, [32](#)
bc_gauss, [32](#)
bc_poly, [33](#)
bc_spline, [33](#)
beta2lw, [34](#)
bin_spec, [34](#)

calc_basis_corr_mat, [35](#)
calc_basis_crlbs, [35](#)
calc_coil_noise_cor, [36](#)
calc_coil_noise_sd, [36](#)
calc_design_efficiency, [37](#)
calc_ed_from_lambda, [37](#)
calc_peak_info_vec, [38](#)
calc_sd_poly, [38](#)

calc_spec_diff, [39](#)
calc_spec_snr, [39](#)
check_lcm, [40](#)
check_tqn, [40](#)
circ_mask, [41](#)
coherence_filter, [41](#)
collapse_to_dyns, [42](#)
comb_coils, [42](#)
comb_coils_mrsi_gls, [43](#)
comb_coils_svs_gls, [44](#)
comb_fit_list_dyns, [44](#)
comb_fit_list_fit_tables, [45](#)
comb_fit_list_result_tables, [46](#)
comb_fit_tables, [46](#)
comb_metab_ref, [47](#)
Conj.mrs_data, [47](#)
conv_mrs, [48](#)
crop_basis, [48](#)
crop_spec, [49](#)
crop_td_pts, [49](#)
crop_td_pts_end, [50](#)
crop_td_pts_pot, [50](#)
crop_xy, [51](#)
crossprod_3d, [51](#)

decimate_mrs_fd, [52](#)
decimate_mrs_td, [52](#)
deconv_mrs, [53](#)
def_acq_paras, [53](#), [181](#), [205–208](#), [211](#)
def_fs, [54](#)
def_ft, [54](#)
def_N, [55](#)
def_nuc, [55](#)
def_ref, [55](#)
dicom_reader, [56](#)
diff_mrs, [56](#)
downsample_mrs_fd, [57](#)
downsample_mrs_td, [57](#)
dyn_acq_times, [58](#)

ecc, 58
 elliptical_mask, 59
 est_noise_sd, 60

 fd2td, 60
 fd_conv_filt, 61
 fd_gauss_smo, 61
 find_bids_mrs, 62
 find_mrs_files, 62
 fit_amps, 63
 fit_diags, 63
 fit_mrs, 64
 fit_res2csv, 65
 fit_svs, 66
 fit_svs_edited, 69
 fit_svs_group_results, 73
 fit_svs_gui, 73
 fit_t1_ti_array, 73
 fit_t1_tr_array, 74
 fit_t2_te_array, 75
 fp_phase, 75
 fp_phase_correct, 76
 fp_scale, 76
 fs, 77
 ft_dyns, 77
 ft_shift, 78
 ft_shift_mat, 78

 gausswin_2d, 79
 gen_baseline_reg, 79
 gen_bold_reg, 80
 gen_conv_reg, 81
 gen_F, 82
 gen_F_xy, 82
 gen_group_reg, 83
 gen_I, 83
 gen_impulse_reg, 84
 gen_numeric_reg, 84
 gen_poly_reg, 85
 gen_trap_reg, 86
 get_1h_brain_basis_names, 87
 get_1h_brain_basis_paras, 88
 get_1h_brain_basis_paras_v1, 88
 get_1h_brain_basis_paras_v2, 89
 get_1h_brain_basis_paras_v3, 89
 get_1h_braino_basis_names, 87
 get_1h_spectre_basis_names, 90
 get_2d_psf, 90
 get_acq_paras, 91

 get_basis_subset, 91
 get_dyns, 92
 get_even_dyns, 92
 get_fh_dyns, 93
 get_fit_map, 93
 get_fp, 94
 get_guassian_pulse, 94
 get_head_dyns, 95
 get_hrf, 95
 get_lcm_cmd, 96
 get_metab, 96
 get_mol_names, 96
 get_mol_paras, 97
 get_mrs_affine, 99
 get_mrsi2d_seg, 97
 get_mrsi_voi, 98
 get_mrsi_voxel, 98
 get_mrsi_voxel_xy_psf, 99
 get_odd_dyns, 100
 get_ref, 100
 get_seg_ind, 101
 get_sh_dyns, 101
 get_slice, 102
 get_spin_num, 102
 get_subset, 103
 get_svs_voi, 104
 get_tail_dyns, 104
 get_td_amp, 105
 get_tqn_cmd, 105
 get_uncoupled_mol, 106
 get_voi_cog, 106
 get_voi_seg, 107
 get_voi_seg_psf, 107
 get_voxel, 108
 glm_spec, 108
 glm_spec_fmrs_fl, 109
 glm_spec_fmrs_group, 110
 glm_spec_group_linhyp, 110
 grid_shift_xy, 112
 gridplot, 111
 gridplot.mrs_data, 111

 hsvd, 112
 hsvd_filt, 113
 hsvd_vec, 114
 hz, 114

 ift_shift, 115
 ift_shift_mat, 115

Im.mrs_data, 116
 image.mrs_data, 116
 img2kspace_xy, 118
 Imzap, 118
 install_cli, 119
 int_spec, 120
 interleave_dyns, 119
 inv_even_dyns, 120
 inv_odd_dyns, 121
 is.def, 121
 is_fd, 122

 kspace2img_xy, 122

 l2_reg, 123
 lb, 124
 lofdc, 124
 lw2alpha, 125
 lw2beta, 126

 make_basis_from_raw, 126
 mask_dyns, 127
 mask_fit_res, 127
 mask_xy, 128
 mask_xy_corners, 128
 mask_xy_ellipse, 129
 mask_xy_mat, 129
 mat2mrs_data, 130
 matexp, 130
 max_mrs, 131
 max_mrs_interp, 131
 mean.list, 132
 mean.mrs_data, 132
 mean_dyn_blocks, 133
 mean_dyn_pairs, 134
 mean_dyns, 133
 mean_mrs_list, 134
 mean_vec_blocks, 135
 median_dyns, 135
 Mod.mrs_data, 136
 mod_td, 136
 mr_data2bids, 140
 mrs_data2basis, 137
 mrs_data2bids, 137
 mrs_data2list, 138
 mrs_data2mat, 139
 mrs_data2spec_mat, 139
 mrs_data2vec, 140
 mvfftshift, 141

 mvfftshift, 142

 n2coord, 142
 Ncoils, 143
 Ndyns, 143
 nifti_flip_lr, 143
 Npts, 144
 Nspec, 144
 Ntrans, 145
 Nx, 145
 Ny, 145
 Nz, 146

 one_page_pdf, 146
 ortho3, 147
 ortho3_inter, 148

 peak_info, 149
 pg_extrap_xy, 149
 phase, 150
 phase_ref_1h_brain, 151
 plot.fit_result, 151
 plot.mrs_data, 153
 plot_bc, 155
 plot_reg, 156
 plot_slice_fit, 156
 plot_slice_fit_inter, 157
 plot_slice_map, 157
 plot_slice_map_inter, 158
 plot_spec_sd, 160
 plot_voi_overlay, 160
 plot_voi_overlay_seg, 161
 ppm, 161
 precomp, 162
 preproc_svs, 162
 preproc_svs_dataset, 163
 print.fit_result, 163
 print.mrs_data, 164

 qn_states, 164

 rats, 165
 Re.mrs_data, 166
 re_weighting, 181
 read_basis, 167
 read_dkd_moco_log, 167
 read_ima_coil_dir, 168
 read_ima_dyn_dir, 168
 read_lcm_coord, 169

read_mrs, 169
 read_mrs(), 67, 70
 read_mrs_tqn, 171
 read_pulse_ascii, 172
 read_pulse_bruker, 172
 read_pulse_pta, 173
 read_siemens_txt_hdr, 173
 read_tqn_fit, 174
 read_tqn_result, 174
 recon_imag, 175
 recon_imag_vec, 175
 recon_twix_2d_mrsi, 176
 rectangular_mask, 176
 rep_array_dim, 177
 rep_dyn, 177
 rep_mrs, 178
 resample_basis, 178
 resample_img, 179
 resample_voi, 179
 reslice_to_mrs, 180
 reson_table2mrs_data, 180
 rm_dyns, 181

 scale_amp_legacy, 182
 scale_amp_molal, 183
 scale_amp_molal_pvc, 184
 scale_amp_molar, 184
 scale_amp_molar2molal_pvc, 185
 scale_amp_ratio, 186
 scale_amp_ratio_value, 186
 scale_amp_water_ratio, 187
 scale_basis_amp, 187
 scale_basis_from_singlet, 188
 scale_mrs_amp, 188
 scale_spec, 189
 sd(sd.list), 189
 sd.list, 189
 sd.mrs_data, 190
 seconds, 191
 segment_t1_fsl, 191
 seq_cpmg_ideal, 192
 seq_mega_press_ideal, 192
 seq_press_2d_shaped, 193
 seq_press_ideal, 194
 seq_pulse_acquire, 195
 seq_slaser_ideal, 195
 seq_spin_echo_ideal, 196
 seq_steam_ideal, 196
 seq_steam_ideal_cof, 197
 seq_steam_ideal_young, 197
 set_def_acq_paras, 198
 set_lcm_cmd, 199
 set_lw, 199
 set_mask_xy_mat, 200
 set_Ntrans, 200
 set_precomp_mode, 201
 set_precomp_verbose, 201
 set_ref, 201
 set_td_pts, 202
 set_tqn_cmd, 202
 set_tr, 203
 shift, 203
 shift_basis, 204
 sim_basis, 204
 sim_basis_1h_brain, 205
 sim_basis_1h_brain_press, 206
 sim_basis_mm_lip_lcm, 207
 sim_basis_tqn, 207
 sim_brain_1h, 208
 sim_mol, 209
 sim_noise, 210
 sim_resonances, 211
 sim_th_excit_profile, 212
 sim_zero, 212
 smooth_dyns, 213
 sort_basis, 214
 spant (spant-package), 10
 spant-package, 10
 spant_abfit_benchmark, 214
 spant_sim_fmrs_dataset, 215
 spant_simulation_benchmark, 215
 spec_decomp, 216
 spec_op, 216
 spin_sys, 217
 spm_pve2categorical, 218
 ssp, 218
 stackplot, 219
 stackplot.fit_result, 219
 stackplot.mrs_data, 221
 sub_first_dyn, 223
 sub_mean_dyns, 223
 sub_median_dyns, 224
 sum_coils, 224
 sum_dyns, 225
 sum_mrs, 225
 sum_mrs_list, 226
 sv_res_table, 230

svs_1h_brain_analysis, [226](#)
svs_1h_brain_analysis_dev, [227](#)
svs_1h_brain_batch_analysis, [229](#)

t_test_spec, [233](#)
td2fd, [230](#)
td_conv_filt, [231](#)
tdsr, [231](#)
te, [232](#)
tr, [232](#)

varpro_3_para_opts, [233](#)
varpro_basic_opts, [234](#)
varpro_opts, [235](#)
vec2mrs_data, [236](#)

write_basis, [237](#)
write_basis_tqn, [237](#)
write_mrs, [238](#)
write_mrs_nifti, [238](#)
write_pulse_ascii, [239](#)

zero_fade_spec, [239](#)
zero_higher_orders, [240](#)
zero_td_pts_end, [240](#)
zf, [241](#)
zf_xy, [241](#)